

|T200 Series|

**Advanced Vector Control
Inverter User's Manual**

- Thank you very much for your buying T200 series high- performance Vector Control Inverter.
- Before use, please read this manual thoroughly to ensure proper usage. Keep this manual at an easily accessible place so that can refer anytime as necessary.

Change date	Change description
2023.11.10	D0.19 Changed to speed display (for the speed set with P1.04)
2024.2.26	Increased power 18.5 to 37KW, added input phase loss protection description
2024.4.18	增加 220V 3.7KW
2024.6.22	增加 45-55KW 机型，尺寸，规格，增加变频器铭牌后缀说明，修改键盘左移键为 JOG 键，增加 380V 0.4-2.2KW 单管机型尺寸

1.Safety Precautions

Please read this operation manual carefully before installation, operation, maintenance or inspection In this manual, the safety precautions were sorted to -WARNING' or "CAUTION".



Warning

Indicates a potentially dangerous situation which, if can not avoid will result in death or serious injury.



Careful

Indicates a potentially dangerous situation which, if can not avoid will cause minor or moderate injury and damage the device. This Symbol is also used for warning any un-safety operation.

In some cases, even the contents of "CAUTION" still can cause serious accident. Please follow these important precautions in any situation.

•NOTE indicate the necessary operation to ensure the device run properly.

Warning Marks are placed on the front cover of the inverter.

Please follow these indications when using the inverter.

WARNING

DANGER

- Risk of injury and electric shock.
- Read the manual and follow the safety instruction before use.
- Isolate from supply and wait 10minutes before removing his cover.
- Ensure proper earth connection.
- Mount the inverter on a non-combustible surface.

2.Inspection



Careful

- Do not install or use any inverter that is damaged or have fault part; otherwise may cause injury.

Check the following items when unpacking the inverter

- ① Inspect the entire exterior of the inverter to ensure there are no scratches or other damage caused by the transportation.
- ② Ensure there is operation manual and warranty card in the packing box.
- ③ Inspect the nameplate and ensure it is what you ordered.
- ④ Ensure the optional parts are what you need if have ordered any optional parts.

Please contact the local agent if there is any damage in the inverter or optional parts.

3.Disassemble and installation warning



Warning

- The person without passing the training manipulate the device or any rule in the “Warning” being violated, will cause severe injury or property loss. Only the person, who has passed the training on the design, installation, is permitted to operate this equipment.
- Input power cable must be connected tightly, and the equipment must be grounded securely.
- Even if the inverter is not running, the following terminals still have dangerous voltage:
 - Power terminals R、S、T
 - Motor connection terminals U、V、W
- When power off, should not install the inverter until 10 minutes after, which can ensure the device discharge completely.
- The section area of grounding conductor must no less than 10mm^2 , Or according to below data, select the maximum value of the two as the grounding conductor area :

Power supply cable area of conductor $S \text{ mm}^2$ Area of grounding conductor

$S \leq 6$	S
$16 < S \leq 35$	16
$35 < S$	$S/2$



Careful

- When moving the inverter please lift by its base and don't lift by the panel, otherwise may cause the main unit fall off which may result in personal injury.
- Install the inverter on the fireproofing material (such as metal) to prevent fire.
- When need install two or more inverters in one cabinet, cooling fan should be provided to make sure that the air temperature is lower than 40°C , otherwise it could cause fire or damage the device.

Contents

Chapter 1 Introduction	错误！未定义书签。
1-1 Technology Features	错误！未定义书签。
1-2 Description of Name Plate	错误！未定义书签。
1-3 Selection Guide	错误！未定义书签。
Chapter 2 Installation and wiring	错误！未定义书签。
2-1 Environment and installation requirements	错误！未定义书签。
2-2 Keyboard can not be pulled out	错误！未定义书签。
2-3 Inverter wiring	错误！未定义书签。
2-4 Control terminal	错误！未定义书签。
Chapter 3 Operation	错误！未定义书签。
3-1 Operator Panel instructions	错误！未定义书签。
3-2 Operation Process	错误！未定义书签。
3-3 Running State	错误！未定义书签。
3-4 Quick Testing	错误！未定义书签。
Chapter 4 Detailed Function Description	30
Group P0 Basic Function	30
Group P1 Motor Parameters	41
Group P2 Vector Control Parameters	错误！未定义书签。
Group P3 V/F Control Parameters	错误！未定义书签。
Group P4 Input Terminals	错误！未定义书签。
Group P5 Output Terminals	69
Group P6 Start/Stop Control	错误！未定义书签。
Group P7 Operation Panel and Display	错误！未定义书签。
Group P8 Auxiliary Functions	错误！未定义书签。
Group P9 Fault and Protection	错误！未定义书签。
Group PA Process Control PID Function	错误！未定义书签。
Group PC Multi-Reference and Simple PLC Function	错误！未定义书签。
Group PD Communication Parameters	错误！未定义书签。
Group PP User function code	错误！未定义书签。
Group C5 Control Optimization Parameters	错误！未定义书签。
Group D0 Monitoring Parameters	错误！未定义书签。
Chapter 5 Fault checking and ruled out	125
5-1 Fault alarm and countermeasures	错误！未定义书签。
5-2 Common Faults and Solutions	错误！未定义书签。
Appendix A Function parameter profiles	135

Appendix B T200 Modbus Communication protocol	173
---	-----

Chapter 1 Introduction

1-1 Technology Features

ITEM		T200
Basic function	Maximum frequency	0～600.00Hz
	Carrier frequency	0.5kHz～16kHz The carrier frequency can be automatically adjusted based on the load features.
	Input frequency resolution	Digital setting: 0.01Hz Analog setting: maximum frequency×0.025%
	Control mode	Voltage/Frequency control (V/F) Sensorless flux vector control (No PG) Closed loop vector control (Have PG)
	Startup torque	G Type: 0.5Hz/150% (No PG) ; P Type: 0.5Hz/100%
	Speed range	1: 100 (No PG)
	Speed stability accuracy	±0.5% (No PG)
	Torque control accuracy	±5% (Have PG)
	Overload capacity	G type: 60s for 150% of the rated current, 3s for 180% of the rated current. P type: 60s for 120% of the rated current, 3s for 150% of the rated current
	Torque boost	Fixed boost Customized boost 0.1%～30.0%
	V/F curve	Straight-line V/F curve Multi-point V/F curve N-power V/F curve (1.2-power, 1.4-power, 1.6-power, 1.8-power, square)
	V/F separation	Two types: complete separation; half separation
	Ramp mode	Straight-line ramp S-curve ramp Four groups of acceleration/deceleration time with the range of 0.0～6500.0s

	DC braking	DC braking frequency: 0.00 Hz to maximum frequency Braking time: 0.0-100.0s Braking action current value: 0.0%–100.0%
	JOG control	Jog frequency range: 0.00Hz~50.00Hz. JOG acceleration/deceleration time0.0s~6500.0s。
	Onboard Multiple preset speeds	It implements up to 16 speeds via the simple PLC function or by input terminal states
	Onboard PID	It realizes process-controlled closed loop control system easily.
	Auto voltage regulation (AVR)	It can keep constant output voltage automatically when the mains voltage changes.
	Over-voltage/ Over-current stall control	The current and voltage are limited automatically during the running process so as to avoid frequent tripping due to over-voltage/over-current.
	Rapid current limit	It helps to avoid frequent over-current faults of the inverter.
	Torque limit and torque control	It can limit the torque automatically and prevent frequent over-current tripping during the running process.

Individual function	High performance	Control of asynchronous motor is implemented through the high-performance current vector control technology.
	Instantaneous stop doesn't stop	The load feedback energy compensates the voltage reduction so that the AC drive can continue to run for a short time.
	Timing control	Timing range 0.0Min~6500.0Min
	Communication methods	RS-485
	Running command channel	Given by the panel, control terminals, Serial communication port, can be switched by many ways

Operation	Frequency source	10 kinds of frequency source, given by digital analog voltage, analog current, Pulse, serial port. can be switched by many ways
	Auxiliary frequency source	There are ten auxiliary frequency sources. It can implement fine tuning of auxiliary frequency and frequency synthesis
	Input terminals	5 digital input terminals, one of which supports up to 100 kHz high-speed pulse input; 1 analog input terminal, supports 0-10V voltage input or 4–20 mA current input.
	Output terminal	1 digital output terminal 1 relay output terminal 1 analog output terminal :that supports 0–20 mA current output or 0–10 V voltage output
Display and operation panel	LED display	It displays the parameters.
	Key locking and function selection	It can lock the keys partially or completely and define the function range of some keys so as to prevent misfunction.
	Protection mode	Motor short-circuit detection at power-on, input output phase loss protection, over-current protection, over-voltage protection, under voltage protection, overheat protection and overload protection.
Environment	Installation location	Indoor, avoid direct sunlight, dust, corrosive gas, combustible gas, oil fog, steam, drip or salt.
	Altitude	Lower than 1000 m(Lower the grades when using higher then 1000m)
	Ambient temperature	-10℃ ~ 40℃ (Lower the grades if the ambient temperature is between 40℃ and 50℃)
	Humidity	Less than 95%RH, without condensing
	Vibration	Less than 5.9m/s ² (0.6g)
	Storage temperature	− 20℃~+ 60℃

1-2 Description of Name Plate

MODEL : T200-3R7G/5R5P-4-□


INPUT: 3PH 380V 50Hz/60Hz

OUTPUT: 3PH 380V 9.0A/13.0A

FREQ RANGE: 0.1-600Hz 3.7KW/5.5KW



2008311714



1-3 Selection Guide

Model	Input voltage	Rated output power (KW)	Rated input current(A)	Rated output current (A)	Motor power (KW)
T200-0R4G-2	1PH AC 220V±15%	0.4	5.4	2.1	0.4
T200-0R75G-2		0.75	7.2	3.8	0.75
T200-1R5G-2		1.5	10.0	7.2	1.5
T200-2R2G-2		2.2	16	9.0	2.2
T200-3R7G-2		3.7	23	13.0	3.7
T200-0R4G-4	3PH AC 380V±15%	0.4	3.4	1.5	0.4
T200-0R75G-4		0.75	3.8	2.1	0.75
T200-1R5G-4		1.5	5.0	3.8	1.5
T200-2R2G-4		2.2	5.8	5.1	2.2
T200-3R0G-4		3.0	8.5	7.2	3.0
T200-3R7G/5R5P-4		3.7/5.5	10.0/15.0	9.0/13.0	3.7/5.5
T200-5R5G/7R5P-4		5.5/7.5	15.0/20.0	13.0/17.0	5.5/7.5
T200-7R5G/11P-4		7.5/11	20.0/26.0	17.0/25.0	7.5/11
T200-11G/15P-4		11/15	26.0/35.0	25.0/32.0	11/15
T200-15G/18.5P-4		15/18.5	35.0/38.0	32.0/37.0	15/18.5
T200-18.5G/22P-4		18.5/22	38.0/46.0	37.0/45.0	18.5/22
T200-22G/30P-4		22/30	46.0/62	45.0/60	22/30
T200-30G/37P-4		30/37	62/76	60/75	30/37
T200-37G/45P-4		37/45	76/92	75/90	37/45
T200-45G/55P-4		45/55	92/113	90/110	45/55
T200-55G/75P-4		55/75	113/157	110/152	55/75

Chapter 2 Installation and wiring

2-1 Environment and installation requirements

Inverter's installation environment on the service life of inverter, and has direct influence on the normal function, Inverter can't satisfy the specification of environment, protection or fault could lead to the Inverter.

T200 series inverter of wall hung inverter, please use the vertical installation so that the air convection and the heat dissipation effect can be better.

Inverter's installation environment, please make sure must comply with

(01)- 10°C to + 40°C ambient temperature

(02) Environment humidity 0 ~ 95% and no condensation

(03) Avoid direct sunlight

(04) Environment does not contain corrosive gas and liquid

(05) Environment without dust, floating fiber, cotton and metal particles

(06) Away from the radioactive material and fuel

(07) Away from electromagnetic interference source (such as electric welding machine, big power machine)


(08) Installed planar solid, no vibration, if it cannot avoid vibration, please add anti-vibration pads to reduce the vibration

(09) Please install the inverter in the well ventilated place, easy to check and maintain, and install on the solid non-combustible material, away from the heating element (such as braking resistance, etc.)


(10) Inverter installation please reserve enough space, especially many inverters' installation, please pay attention to the placement of the frequency Inverter, and configure cooling fans, make the environment temperature lower than 45°C.

2-1-1 The inverter's outside shape and the installation dimensions

① AC220V 0.4--1.5KW & 380V 0.75-2.2kw, "D" type





② AC220V 2.2KW & AC380V 0.4--3.7KW





Note: 380V models do not have built-in filters as standard, and can be equipped with built-in filters.

③ AC220V 3.7KW & AC380V 5.5--7.5KW





Note: 380V models do not have built-in filters as standard, and can be equipped with built-in filters.

④ AC380V 11--15KW





Note: 380V models do not have built-in filters as standard, and can be equipped with built-in filters.

⑤ AC380V 18.5--22KW





⑥ AC380V 30--37KW



Note: Optional built-in DC reactor.

⑦AC380V 45--55KW




Note: Optional built-in DC reactor.

2-2 Keyboard can not be pulled out

2-3 The Inverter Wiring

2-3-1 The inverter wiring of the main part



2-3-2 The descriptions of peripheral devices

(1)AC power

Use with in the permissible power supply specifications of the inverter.

(2)Moulded case circuit breaker:(MCCB)

When the power supply voltage is low or the input terminal short circuit occurs,the breaker can provide protection,during inspection,maintenance or the inverter is not running,you can cut off this breaker to separate this inverter from the power supply.

(3)Magnetic contract(MC)

The contractor can turn on and turn off the power of the inverter to ensure safety.


(4)AC current reactor

a: Suppress high harmonic to protect the inverter to ensure safety

b: Improve power factor

(5)Brake resistor

When the motor is braking, the resistor can avoid DC bus high voltage of the inverter ,and improve the braking ability of the internal brake unit, connect of brake resistor as below:



2-3-3 Precautions main circuit wiring

(1)Circuit wiring ,refer to requirements of electrical codes.

(2)Application of supply power to output terminals(U,V,W)of the invert will damage it,so never perform such wiring.

(3)Power supply's wiring ,please use isolated wire and wire pipe if possible.and make isolated wire and wire pipe link to the earth.

(4)The inverter and welding device, high-power motor,high-power load can't use a earth cable.

(5)The ground terminal E,ground impedance is lower than 100Ω

(6)Use the shortest earth cable possible.

(7) Many inverters are earthed, pay attention not to cause ground loops. As below:



Good



Good




Not good

(8) The power cables and the control cables must be separated in the main circuit, keep the power cables more than 10 cm away from the paralleled control cables, when the power cables and the control cables are crossed, make them vertical. Don't make the power cables and the control cables together, or the interference will cause.

(9) Under normal circumstances, the distance between the inverters and the motors is less than 30m, the current produced by the parasitic capacitance may cause over-current protection, mis-action, inverter's fault and equipment operating faults. The maximum distance is 100m, when the distance is long, please select the output side filter, and reduce the carrier frequency.

(10) Don't install an absorbing capacitor or other capacitance-resistance absorbing devices at output side of the inverter.



(11) Ensure the terminals are all locked tightly, the cables are connected well with the terminals, prevent the looseness due to an action of shaking, cause sparks and the short circuit

(12) To minimize the interference, it is recommended that the contactor and relay should be connected to the surge absorber.

2-3-4 Device recommended specifications

Model	Input voltage	Motor output (KW)	Main Circuit Cable Type (mm ²)	Breaker Selection (A)	Magnetic contractor (A)
T200-0R4G-2	220V±15% 1PH	0.4	0.75	10	9
T200-0R75G-2		0.75	0.75	16	12
T200-1R5G-2		1.5	1.5	25	18
T200-2R2G-2		2.2	2.5	32	25
T200-3R7G-2		3.7	2.5	40	32
T200-0R4G-4	3PH 380V±15%	0.4	0.75	6	9
T200-0R75G-4		0.75	0.75	6	9
T200-1R5G-4		1.5	0.75	10	9
T200-2R2G-4		2.2	0.75	10	9
T200-3R0G-4		3.0	1.5	16	12
T200-3R7G/5R5P-4		3.7/5.5	1.5	16	12
T200-5R5G/7R5P-4		5.5/7.5	2.5	20	18
T200-7R5G/11P-4		7.5/11	4	32	25
T200-11G/15P-4		11/15	4	40	32
T200-15G/18.5P-4		15/18.5	6	50	38
T200-18.5G/22P-4		18.5/22	10	80	65
T200-22G/30P-4		22/30	10	80	65
T200-30G/37P-4		30/37	16	100	65


T200-37G/45P-4		37/45	25	100	80
T200-45G/55P-4		45/55	35	160	95
T200-55G/75P-4		55/75	50	160	115

*The above data are for reference only.


2-3-5 Main circuit terminals and description

1. Main circuit terminal arrangement T200 series inverter is as follows:


a.1PH AC 220V 0.4-1.5KW




b.3PH AC 380V 0.4-15KW & 1PH AC 220V 2.2-3.7KW




c.3PH AC 380V 18.5-37KW




2. Description of main circuit terminals

Terminal name	Description
	Earth(ground)
L1、L2、L3	Power input
U、V、W	Connect a three-phase AC motor.
+/B1、B2 or +、PB	Connect brake resistor
+/B1、- or +、-	DC bus terminal, can be connect to brake unit

3.Wiring example:



3. The basic wiring diagram



2-4 Control terminal



2-4-1 Control Terminal Description

Terminal	Function Description	Remarks
----------	----------------------	---------

name		
X1	Forward command input (multi-function input terminals)	Terminals X1 ~ X5 can be set through parameters P4.00~P4.04, set the terminal and COM closed effective
X2	Reverse command input (multi-function input terminals)	
X3	Fault reset	
X4	Multi-speed command 1	
X5	Multi-speed command 2 (High speed pulse input)	
COM	Digital input common	
FOV	Analog output terminal	0~10V/0~20mA
10V	Frequency setting power	
FIC	Analog input terminal	0~10V/0~20mA
24V	24V auxiliary power	
GND	Input signal common	
CME	Optically coupled output common	
YO	Multifunctional optical coupling output contacts	
YA	Relay output contacts (normally open)	
YB	Relay output contacts (normally closed)	
YC	Relay output contacts YA, YB common	

Control panel switch description:

Switch name	Switch description
J5	V, FOV short for voltage output; I, FOV short for current output
J3	V, FIC short for voltage input; I, FIC short for current input
J9	X4 is standard multi-function input terminal, Enable the STO function on the STO side(Note:The STO function do not need to set parameters. Just select STO with J9, short-circuit X4 and COM, and STO will be turned off; disconnect X4 and COM, and STO will be turned on.)
J4	RS485 communication terminal resistance selection switch, the ON side has RS+ and RS- connected in parallel with 120Ω resistors, and the OFF side of RS+ and RS- has no parallel terminal resistors.

J7,J8	Both jump to the BMQ side, select the LED keyboard, and both jump to the LCD side , select the LCD keyboard.
J1	NPN/PNP selection switch
J6	EMC interference to ground ON/OFF selection switch

Control loop distribution NOTES:

(1)Please let the control signal lines and the main lines, and other power lines, power lines separate traces.

(2)In order to prevent interference caused by malfunction, use stranded or double-stranded shielded wire line, specifications for 0.5 ~ 2mm²

(3)Make sure that each using terminal to allow conditions, such as: power supply, the maximum current.

(4)correct ground terminal E, grounding resistance is less than 100Ω.

(5)each terminal's wiring requirements, the correct selection of accessories such as potentiometer, voltmeter, input power supplies.


(6)After completing the wiring correctly and check to make sure it is correct and then the power can be on.

Chapter 3 Operation






3-1 Digital Operator Description





Digital Operator can also be called Panel

3-1-1 The picture of the panel



3-1-2 The descriptions of the key's function

Key	Name	Description
	Programming key	Entry or escape of first-level menu,delete shortcut parameters
	Data enter key	Progressively enter menu and confirm parameters.
	UP Increment Key	Progressively increase data or function codes
	DOWN Decrement Key	Progressive decrease data or function codes.
	Quick multifunction key	The function of this key is determined by the function code P7.01.

	Right shift key	In parameter setting mode, press this button to select the bit to be modified. In other modes, cyclically displays parameters by right shift
	Run key	Start to run the inverter in keypad control mode
	Stop key/Fault reset key	In running status, restricted by F7.04, can be used to stop the inverter. When fault alarm, can be used to reset the inverter without any restriction.。
	Encoder	When P0.03=4, when rotating the knob, can modify the set frequency; During standby, press the knob to switch the display screen by setting P7.03~P7.05, the output frequency, output current, output voltage, bus voltage, output speed can be displayed.

3-1-3 Indicator light description:



Indicator light name	Indicator light description
Hz	Frequency unit
A	Current unit
V	Voltage unit
F/R	Light off: forward operation. Light on: reverse operation.


3-2 Operational process

3-2-1Parameter Settings


Three-level menu :

1. The function code group (first menu);
2. The function code symbols (second menu);
3. The function code set value (third menu).

Explanation: The three-level menu operation, can press  or  to return to the secondary menu.The difference between the two is: press

 to set parameters in control panel, and then return to the secondary menu, and automatically move to the next function code;Press PRG directly to return to the secondary menu, don't store parameters, and keep staying in the current function code.

Example: Change the function code P2.05 from 10.00 Hz setting to 50.00 Hz.



In three-level state, if the parameter is not flashing, said the function code cannot be modified, possible reasons are:

- 1)The function code parameters can not be modified.Such as the actual testing parameters, operation records, etc.;
- 2)The function code in the running state cannot be modified, need to stop to modify;

3-2-2 Fault reset

After the failure of the inverter, the inverter will be prompted to related fault information.Users can press STOP key on the keyboard or terminal function to conduct the fault reset (P4), after fault reset,the inverter is in the standby state.If the inverter is in fault state, the user does not conduct on the fault reset, the inverter is in the running to protect state, inverter can't run.

3-2-3 Motor parameters auto-tuning

1:The dynamic parameter auto-tuning

Choosing no PG vector control operation mode, input motor nameplate parameters must be accurate, inverter will base on nameplate parameters

matching standard motor; In order to get better control performance, motor parameter auto-tuning is suggested and auto-tuning steps are as follows: First will run command channel choice (P0.02) choice for keyboard commands. Then the actual parameters according to the motor, please input the following parameters.

P1.01: the motor rated power;

P1.02: the motor rated voltage;

P1.03: the motor rated current;

P1.04: the motor rated frequency;

P1.05: the motor rated speed.

Note: in the process of auto-tuning ,motor and load should be released, otherwise, the motor parameters obtained from the auto-tuning may not be correct.

2: the static parameters of the auto-tuning

Motor static parameters auto-tuning , don't need to release motor with the load, motor parameter auto-tuning , must correct the input parameters of motor nameplates (P1.01 - P1.05), since auto-tuning will detect the motor stator resistance and rotor resistance and leakage inductance of the motor. And mutual inductance of the motor and no-load current will not be able to measure, the user can input the corresponding values according to the motor nameplates.

3-3 Running state

3-3-1 Power-on initialization

In the process of the Inverter's power-on, the system first initializes, and lights are all bright. After the initialization is complete, the drive is in the standby mode.

3-3-2 Standby status

In the stopping or running status, can display a variety of state parameters. select whether to display this parameter by Function Code P7.03 (operating parameters), P7.05 (stop parameter) binary bits , Various definitions can refer to P7.03 and P7.05 function code.

3-3-3 Motor parameters self-learning

Please refer to the detailed descriptions of P1.37 function code.


3-3-4 Running

In the running state, a total of 29 status parameters can choose whether to display the status parameters : operating frequency, set frequency, bus voltage, output voltage, output current, whether to display the function code is decided by P7.03 and P7.04 bit (converted into binary) choice, press the key to switch the display order of the selected parameters, press the Left/right shift key to switch in order to the selected display parameters.

3-3-5 Failure

T200series offers a variety of fault information, please refer T200 series inverter faults and their countermeasures.

3-4 Quick commissioning



Chapter 4 Detailed Function Description

Group P0: Basic ParametersP0

P0.00	G/P type display		Default	Model dependent
	Setting range	1	G type (constant torque load)	
		2	P type (variable torque load e.g. fan and pump)	

1: Applicable to constant torque load with rated parameters specified

2: Applicable to variable torque load (fan and pump) with rated parameters specified

P0.01	Control mode selection		Default	2
	Setting range	0	Sensorless flux vector control (SFVC)	
		1	Closed- loop vector control (CLVC)	
		2	V/F control	

0: Sensorless flux vector control (SFVC)

It indicates open-loop vector control, and is applicable to high-performance control application such as machine tool, centrifuge, wire drawing machine and injection moulding machine. One AC drive can operate only one motor.

1: Closed- loop vector control (CLVC)

It is applicable to high-accuracy speed control or torque control applications such as high-speed paper making machine, crane and elevator. Once AC drive can operate only one motor. An encoder must be installed at the motor side, and a PG card matching the encoder must be installed at the AC drive side.

2: V/F control

It is applicable to applications with low load requirements or applications where one AC drive operates multiple motors, such as fan and pump.

****Note:** If vector control is used, motor auto-tuning must be performed because the advantages of vector control can only be utilized after correct motor parameters are obtained.

P0.02	Command channel selection		Default	0
	Setting range	0	Operation panel control(LED off)	
		1	Terminal control(LED on)	
		2	Communication control(LED blink)	

It is used to determine the input channel of the AC drive control commands, such as run,stop, forward rotation, reverse rotation and jog operation. You can input the commands in the following three channels:

0: Operation of panel control(Light off)

Commands are given by pressing keys RUN and STOP/RESET on the operation panel.

1: Terminal control(Light on)

Commands are given by means of multifunctional input terminals with functions such as X1~X5.

2: Communication control (Light blink)

Commands are given from host computer.

P0.03	Main frequency source X selection		Default	0
	Setting range	0	Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost don't memory)	
		1	Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost memory)	
		2	FIV(Expansion card)	
		3	FIC	
		4	Operation panel potentiometer	
		5	Pulse setting	
		6	Multistage instruction	
		7	PLC	
		8	PID	
		9	Communications setting	

Choose inverter main input channel of a given frequency.

A total of 10 given frequency channels:

0: digital setting (power lost don't memory)

Set the initial value of frequency P0.08 (frequency preset) values. Can bring through a keyboard ▲ keys and ▼ keys (or multi-function input terminal of the UP and DOWN) to change the set frequency value of the inverter. Inverter after the power is off and the power is on again, set frequency values revert to P0.08 (digital frequency setting preset) values.

1: digital setting (power lost memory)

Set the initial value of frequency P0.08(frequency preset)values. Can be brought by a keyboard ,▲ ▼ keys (or multi-function input terminal of the UP and DOWN) to change the set frequency value of the inverter.

Inverter after the power is off and the power is on again, set frequency electric moment for the last set, through the keyboard bring ▲ ▼ keys or terminal correction by the memory of UP and DOWN.

What need to remind is, P0.23 set for "digital frequency setting down memory selection", P0.23 is used to select the inverter when the inverter stops, P0.23 is used to select whether inverter memorizes the freq or is reset during

stopping time,P0.23 is related to the stop,isn't related to the drop memory, pay attention in the application.

2: FIV(Expansion card)

3: FIC

4: Operation panel potentiometer

Frequency is depend on analog input terminal.T200 control panel provides two analog input terminal (FIV, FIC).Among them, the FIV is from 0V to 10V voltage input, FIV and FIC are both can be 0V to 10V voltage input, can also be used for 4 ~ 20 mA, can be selected by jump wire. T200 provide 5 set of corresponding relation curve, three groups of curve for linear relationship (2 point correspondence), two groups of curve for linear relationship (4 point correspondence), the user can set through the P4 group and C6 group function code .

P4.33 function code is used to set the FIV - the FIC two-way analog input, respectively select which of the five groups of curves, five specific corresponding relation curves, please refer to the descriptions of P4, C6 group function code.

5: Pulse frequency setting is given by terminal pulse. Pulse signal given specifications: voltage range of 9v~ 30v and frequent^ range of from 0 kHz to 100 kHz. Input pulse can only be given from multifunctional input terminals X5.

X5 terminal input pulse frequency and the corresponding set of relations, through the P4.28 ~ P4.31 setting, the corresponding relations between for 2 linear point correspondence .the linear relation between the corresponding set of input pulses 100.0%, refer to the relative maximum frequency P0.10 percentage.

6: When selecting the multi-segment instruction operation mode, you need to use different state combinations of digital input terminals to correspond to different set frequency values. T200 can set up 4 multispeed instruction terminals and select 16 state of those terminals. Through the function of the PC group code corresponding to any 16 Multistage instruction .The Multistage instruction is referred to the percentage of the maximum frequency P0.10

Digital input terminal function as multispeed selection terminal need to be done in group P4 corresponding settings, please refer to the specific content P4 group of related function parameters.

7: Simple PLC

When frequency source is in simple PLC mode, frequency source of inverter can run between any frequency source from 1 to 16 , the hold time from 1 to16 frequency instruction and their respective acc./dsc. time can also be set by the user. The specific content can refer to PC group.

8: PID

Select the process of PID control output as the operating frequency. Commonly used in the scene of the closed loop control technology, such as

constant pressure closed loop control, constant tension closed-loop control, etc. Application of PID as frequency source, you need to set up "PID" PA group related parameters.

9: Communication given

The main frequency source is given by the upper machine through the way of communication.

T200 support communication methods: RS - 485.

P0.04	Auxiliary frequency source Y selection		Default	0
	Setting range	0	Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost don't memory)	
		1	Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost memory)	
		2	FIV(expansion card)	
		3	FIC	
		4	Operation panel potentiometer	
		5	Pulse setting (X5)	
		6	Multistage instruction	
		7	PLC	
		8	PID	
		9	Communications given	

Auxiliary frequency source with the frequency for a given channel as an independent (i.e. frequency source selection of X to Y switch), its usage and the main frequency source with X, using the method can be refer to P0.03 related instructions.

When auxiliary frequency source used as a superposition of a given (i.e. frequency source selection of X + Y, X to X + Y switch or Y to X + Y), the need to pay attention to:

1) When the auxiliary frequency source for digital timing, preset frequency (P0.08) doesn't work, the user through the keyboard bring ▲, ▼ button (or multi-function input terminal of UP and DOWN) on the frequency of adjustment, directly in the main on the basis of a given frequency adjustment.

2) When the auxiliary frequency source for analog input given (FIV (expansion card) , FIC) or to the input pulse given, 100% of the input set corresponding auxiliary frequency source range, can be set by P0.05 and P0.06.

3) When Frequency source is pulse input given similar to analog given.

Tip: auxiliary frequency source selection and main frequency source X, Y can't

set to the same channel, namely P0.03 and P0.04 can't set to the same value, otherwise it will be easy to cause confusion.

P0.05	Auxiliary frequency source superposition Y range selection		Default	0
	Setting range	0	Relative to the maximum frequency	
		1	Relative to the main frequency source X	
P0.06	Auxiliary frequency source superposition Y		Default	0
	Setting range		0%~150%	

When selecting frequency source for the superposition of "frequency" (P0.07 set to 1,3, or 4), these two parameters are used to determine the adjusting range of auxiliary frequency source. P0.05 is used to determine the scope of the auxiliary frequency source of the object, the choice of relative to the maximum frequency, can also be relative to the rate of frequency source X, if choice is relative to the main frequency source,

P0.07	Frequency source superposition selection		Default	00
	Setting range	Unit's digit	Frequency source selection	
		0	Main frequency source X	
		1	X and Y operation(operation relationship determined by ten's digit)	
		2	Switchover between X and Y	
		3	Switchover between X and "X and Y" "operation"	
		4	Switchover between Y and "X and Y" "operation"	
		Ten's digit	X and Y operation	
		0	X+Y	
		1	X-Y	
		2	Maximum of X and Y	
		3	Minimum of X and Y	

It is used to select the frequency setting channel. Through the main frequency source X and auxiliary frequency source Y compound to achieve a given frequency. Unit's digit (Frequency source)

0:The main frequency X

The main frequency X as the target frequency.

1:Advocate complementary operation result as the target frequency, the operation relationship is decided by the function code "ten's digit".

2:Main frequency source X and auxiliary frequency source Y switch when the multifunctional input terminal 18 (frequency switch) is invalid, the main frequency X as the target frequency. When the multifunctional input terminals function 18 (frequency source switch) is valid, auxiliary frequency Y as the target frequency.

3:The main switch frequency source X and advocate complementary operation results When the multi-function input terminals function 18 (frequency switch) is invalid, the main frequency X as the target frequency. When the multi-function input terminals function 18 (frequency switch) is valid, advocate complementary computing results as the target frequency.

4:Auxiliary switch frequency source Y and advocate complementary operation results When the multi-function input terminals function 18 (frequency switch) is invalid, auxiliary frequency Y as the target frequency. When the multi-function input terminals function 18 (frequency switch) is valid, advocate main/auxiliary computing results as the target frequency.

Ten's digit : frequency source main/auxiliary relationship between operation:

0:The main frequency of X and Y auxiliary frequency and frequency as the target.

1:Main frequency X minus Y auxiliary frequency difference as the target frequency.

2:MAX (the main frequency source X, the auxiliary frequency source Y) take the main frequency absolute value of the largest in the X and Y auxiliary frequency as the target frequency.

3:MIN (the main frequency source X, the auxiliary frequency source Y) take the main frequency the least absolute value of X and Y auxiliary frequency as the target frequency. In addition, when the frequency source selection of the advocate complementary computing, offset frequency, can be set by P0.21 offset frequency, superimposed on the advocate complementary operation results in a flexible response to various needs.

P0.08	Frequency preset	Default	50.00Hz
	Setting range	0.00～maximum frequency（effect when frequency source selection as digital set）	

When frequency source selection set for "digital" or "terminal UP/ DOWN", the function code value is the frequency of the inverter digital set initial value.

P0.09	Rotation direction		Default	0
	Setting range	0	Same direction	
		1	Reverse direction	

By changing the function code, not need to change the motor wiring for the purpose of the motor's direction , its effect is equivalent to adjust electric machine (U, V, W) any two lines for motor direction of rotation transformation.

Tip: after initialization, parameters will restore the original state of the motor running direction. Pay attention to the good debugging system which is forbidden to change the motor's running direction.

P0.10	Maximum frequency	Default	50.00 Hz
	Setting range	50.00Hz～600.00Hz	

In T200 analog input and pulse input , period of instruction, etc., as a frequency source 100.0% of their relatively P0.10 calibration.

P0.11	Upper limit frequency source		Default	0
	Setting range	0	P0.12 setting	
		1	FIV (expansion card)	
		2	FIC	
		3	Reserved	
		4	PULSE setting	
		5	Communication setting	

Define the upper limit frequency source the upper limit frequency can be from digital set (P0.12), also can from the analog input. When was capped with analog input frequency, analog input corresponding set 100% is corresponding to P0.12.

For example at the scene of the winding control using torque control mode, in order to avoid material break appear "ride" phenomenon, can use analog frequency cap, when the inverter runs to the upper limit frequency value, the inverter is in a maximum frequency operation.

P0.12	Upper limit frequency	Default	50.00Hz
	Setting range	Frequency lower limit P0.14-Maximum frequency P0.10	

P0.13	Upper limit frequency offset	Default	0.00Hz
	Setting range	0.00Hz～ maximum frequency P0.10	

When the upper limit set for analog or PULSE frequency, P0.13 as the set point offset, superimpose the offset frequency and P0.12 setting upper limit frequency values, as the final limit frequency value.

P0.14	Frequency lower limit	Default	0.00Hz
	Setting range	0.00Hz～upper limit frequency P0.12	

Frequency instructions below P0.14 set the lower limit of frequency, inverter can stop and run at the lower frequency or a ship at zero speed line, what operation mode can be P8.14 (set frequency is lower than the lower limit frequency operation mode) Settings.

P0.15	Carrier frequency	Default	Model dependent
	Setting range	0.5kHz～16.0kHz	

This function adjusting carrier inverter. By adjusting the carrier frequency can reduce electrical noise, to avoid the resonance point of mechanical system, reduce the line of floor drain current and reducing interference caused by inverter.

When the carrier frequency is low, the output current of higher harmonic component increases, motor loss increases, the motor temperature increases. When the carrier frequency is higher, the motor loss is reduces, the motor temperature rise reduces, but the loss of the inverter increases, the temperature rise of the inverter increases, increased interference.

Adjusting the carrier frequency will affect the performance of the following:

Carrier frequency	low — high
The motor noise	large — small
The output current waveform	Bad- good
Temperature Rise in Electric Motors	High — low
The temperature rise of the inverter	Low--high
leak current	Small — large
Foreign raXated interference	Small --large

Different power inverter, the carrier frequency of the factory Settings is different. Although the user can according to need to modify, but need to pay attention: if

the carrier frequency set to a higher value than the factory, will lead to inverter radiator temperature increase, the user needs to use of inverter derating, otherwise the inverter is in danger of overheating alarm.

P0.16	Carrier frequency adjustment with temperature	Default	0
	Setting range	0: No 1: Yes	

Carrier frequency with the temperature adjustment, is refers to the inverter is detected its radiator at high temperature, reduce the carrier frequency automatically, for lowering the temperature rise of the inverter. When the radiator at low temperature, carrier frequency returning to the set value. This feature can reduce overheat alarm of inverter.

P0.17	Acceleration time 1	Default	Model dependent
	Setting range	0.00s～6500.0s	
P0.18	Deceleration time 1	Default	Model dependent
	Setting range	0.00s～6500.0s	

Acceleration time indicate the time of inverter accelerate from 0Hz to Acc/dec base frequency (P0.25) .

Deceleration time indicate the time of inverter decelerate from Acc/dec base frequency (P0.25) to 0Hz.

P0.19	Acceleration/Deceleration time unit		Default	1
	Setting range	0	1s	
		1	0.1s	
		2	0.01s	

To meet the needs of all kinds of scene, T200 provides three kinds of deceleration time units, 1 seconds, 0.1 seconds, respectively, and 0.01 seconds. Note: Modify the function parameters, four groups of decimal digits, as suggested by the deceleration time will change, the corresponding deceleration time changes, also pay special attention to in the course of application

P0.21	Frequency offset of auxiliary frequency source for X and Y operation	Default	0.00Hz
	Setting range	0.00Hz～ maximum frequency P0.12	

This function code is only valid at the time of frequency source selection of the advocate complementary computing.

When frequency source of the advocate complementary computing P0.21 as offset frequency, and advocate complementary computing results superposition frequency value, as the final frequency setting, make frequency setting be more flexible.

P0.22	Frequency command resolution		Default	2
	Setting range	2	0.01Hz	

This parameters used to determine the resolution of the function code associated with the frequency. It can not be modified.

P0.23	Retentive of digital setting frequency upon power off		Default	0
	Setting range	0	No memory	
		1	Memory	

The function of frequency source for digital only effective when setting.

"No memory" refers to the inverter after downtime, digital frequency values revert to P0.08(frequency preset value, the keyboard bring ▲ , ▼ button or terminal is UP and DOWN to correct the frequency is reset.

"Memory" refers to the inverter after downtime , digital set frequency keep set for the last moment of downtime, bring about keyboard ▲, ▼ button or terminal is UP and DOWN to correct the frequency of remain valid.

P0.25	Acceleration/deceleration time base frequency		Default	0
	Setting range	0	Maximum frequency (P0.10)	
		1	Setting frequency	
		2	100Hz	

Acceleration/deceleration time, indicate the Acceleration/deceleration time from 0 to the frequency set by P0.24.

When P0.25 set to 1, acceleration/deceleration time is relate to setting frequency, if setting frequency changes frequently, motor ‘s acceleration will changing accordingly.

P0.26	Base frequency for UP/DOWN modification during running		Default	0
	Setting range	0	Running frequency	
		1	Set frequency	

This parameter is only valid when frequency source for the digital setting. Used to determine the bring ▲▼ button or terminal of the keyboard UP/DOWN action, adopt what way set frequency correction, the target frequency is based on the operating frequency, increase or decrease or based on a set frequency increase or decrease. Two set of distinction, evident when inverter in the deceleration process, namely, if the operation of the inverter frequency and setting frequency is not at the same time, the parameter of the different selection difference is very big.

P0.27	Binding command source to frequency source		Default	000
	Setting range	Unit's digit	Binding operation panel command to frequency source	
		0	No binding	
		1	Frequency source by digital setting	
		2	FIV（expansion card）	
		3	FIC	
		4	Operation panel potentiometer	
		5	PULSE setting	
		6	Multi-reference	
		7	Simple PLC	
		8	PID	
		9	Communication setting	
		Ten's digit	Binding terminal command to frequency source(0-9, same as unit's digit)	
		Hundred's digit	Binding communication command to frequency source(0~9, same as units digit)	

It is used to bind the three running command sources with the nine frequency sources, facilitating to implement synchronous switchover. For details on the frequency sources, see the description of P0.03 (Main frequency source X selection).Different running command sources can be bound to the same frequency source.

If a command source has a bound frequency source, when the process of frequency source is effective,the command source set in P0.03 to P0.07 will no longer work.

Group P1 Motor Parameters

P1.00	Motor type selection	Default	0
	Setting range	0-Common asynchronous motor 1-Variable frequency asynchronous motor	
P1.01	Rated motor power	Default	Model dependent
	Setting range	0.1kW～450.0kW	
P1.02	Rated motor voltage	Default	Model dependent
	Setting range	1V～2000V	
P1.03	Rated motor current	Default	Model dependent
	Setting range	0.01A～655.35A (AC drive power ≤55kW) 0.1A～6553.5A (AC drive power >55kW)	
P1.04	Rated motor frequency	Default	Model dependent
	Setting range	0.01Hz～maximum frequency	
P1.05	Rated motor rotational speed	Default	Model dependent
	Setting range	1rpm～65535rpm	

Set the parameters according to the motor's nameplate no matter whether V/F control or vector control is adopted. To achieve better V/F or vector control performance, motor auto-tuning is required. The motor auto-tuning accuracy depends on the correct setting of motor nameplate parameters.

P1.06	Stator resistance (asynchronous motor)	Default	Model dependent
	Setting range	0.001Ω～65.535Ω (AC drive power ≤55kW) 0.0001Ω～6.5535Ω (AC drive power >55kW)	
P1.07	Rotor resistance (asynchronous motor)	Default	Model dependent
	Setting range	0.001Ω～65.535Ω (AC drive power ≤55kW) 0.0001Ω～6.5535Ω (AC drive power >55kW)	
P1.08	Leakage inductive reactance (asynchronous motor)	Default	Model dependent
	Setting range	0.01mH～655.35mH (AC drive power ≤55kW)	

		0.001mH～65.535mH（AC drive power>55kW）	
P1.09	Mutual inductive reactance (asynchronous motor)	Default	Model dependent
	Setting range	0.1mH～6553.5mH（AC drive power≤55kW） 0.01mH～655.35mH（AC drive power>55kW）	
P1.10	No-load current (asynchronous motor)	Default	Model dependent
	Setting range	0.01A～P1.03（AC drive power≤55kW） 0.1A～P1.03（AC drive power>55kW）	

The parameters in P1.06 to P1.10 are asynchronous motor parameters.

P1.06～P1.10 parameters are ordinary unavailable on the motor's nameplate and are obtained by means of inverter's auto-tuning .Asynchronous motor's stationary auto-tuning can obtain only P1.06 to P1.08. Asynchronous motor's dynamic autotuning can obtain besides all the parameters,and can also obtain encoder phase sequence and current loop PI.

Each time "Rated motor power (P1.01) or "Rated motor voltage" (P1.02) is changed, the AC drive automatically restores values of P1.06 to P1.10 to the parameter setting for the common standard asynchronous motor.

If it is impossible to perform asynchronous motor's stationary autotuning manually input the values of these parameters according to data provided by the motor manufacturer.

P1.11-P1.26 Reserved

P1.27	Encoder pulses per revolution	Default	1024
	Setting range	1～65535	

This parameter is used to set the pulses per revolution of ABZ or UVW incremental encoder. In CLVC mode, the motor can not run properly if this parameter is set incorrectly.

P1.28	Encoder type	Default	0
	Setting range	0	ABZ incremental encoder
		2	Resolver

T200 supports a variety of encoder type, different encoder needs matching PG card, please correct choose the type. Generally choose ABZ incremental encoder and resolver for asynchronous motor. After installed the PG card, please set P1.28

correctly, otherwise, inverter may not run properly.

P1.30	ABZ incremental encoder AB phase sequence		Default	0
	Setting range	0: Forward 1: Reverse		

This parameter only valid for ABZ incremental encoder, that is P1.28=0 valid. It is used to set AB phase sequence of ABZ incremental encoder. In auto tuning state, can get the AB phase sequence.

P1.34	Number of pole pairs of resolver		Default	1
	Setting range	1~65535		

If a resolver is applied, set the number of pole pairs properly.

P1.36	Encoder wire-break fault detection time		Default	0.0s
	Setting range	0.0s: No action 0.1s~10.0s		

This parameter is used to set the time that a wire-break fault lasts. If it is set to 0.0s, the AC drive do not detect the encoder wire-break fault. If the duration of the encoder wire-break fault detected by the AC drive exceeds P1.36 the time set in this parameter, the AC drive reports PG.

P1.37	Auto-tuning selection		Default	0
	Setting range	0	No operation	
		1	Static auto-tuning	
		2	Dynamic auto-tuning	
		3	Completely static self-learning	

0: No auto-tuning Auto-tuning is prohibited.

1: Asynchronous motor static auto-tuning

It is applicable to scenarios where complete auto-tuning cannot be performed because the asynchronous motor can't be easily disconnected to the load.Before performing static auto-tuning, properly set the motor type and motor nameplate parameters of P1.01 to P1.05 first. The AC drive will obtain three parameters of P1.06 to P1.08 by static autotuning.

Action description: Set this parameter to 1, and press RUN. Then, the AC drive starts static auto-tuning.

2: Asynchronous dynamic auto-tuning

To perform the dynamic control, when select the dynamic auto-tuning,

please make motor with no load state.

During the process of dynamic auto-tuning, AC drive first operate static auto-tuning, and then accelerate to 80% of rated motor frequency with acceleration time set by P0.17, hold for some time, stop and finish auto-tuning within the deceleration time set by P0.18.

Action description: Set the parameter to 2 and press RUN. Then the AC drive starts dynamic auto-tuning.

Note: When choosing vector control mode, you must correctly set the motor nameplate parameters and perform motor parameter self-learning. Only accurate motor parameters can take advantage of vector control.

Group P2 Vector Control Parameters

Group P2 function code applies only to the vector control, V/F control is invalid.

P2.00	Speed loop proportional gain 1	Default	30
	Setting range	1~100	
P2.01	Speed loop integral time 1	Default	0.50s
	Setting range	0.01s~10.00s	
P2.02	Switchover frequency 1	Default	5.00Hz
	Setting range	0.00~P3.05	
P2.03	Speed loop proportional gain 2	Default	20
	Setting range	0~100	
P2.04	Speed loop Integral time 2	Default	1.00s
	Setting range	0.01s~10.00s	
P2.05	Switchover frequency 2	Default	10.00Hz
	Setting range	P3.02~maximum output frequency	

Speed loop PI parameters vary with running frequencies of the AC drive.

If the running frequency is less than or equal to "Switchover frequency 1" (P2.02), the speed loop PI parameters are P2.00 and P2.01.

If the running frequency is equal to or greater than "Switchover frequency 2" (P2.05), the speed loop PI parameters are P2.03 and P2.04.

If the running frequency is between switching frequency 1 and switching

frequency 2, the speed loop PI parameters are obtained from the linear switchover between the two groups of PI parameters, as shown in Figure 4-1




Figure 4-1 PI parameter diagram

The speed dynamic response characteristics in vector control can be adjusted by setting the proportional gain and integral time of the speed regulator.

To achieve a faster system response, increase the proportional gain and reduce the integral time. Be aware that this may lead to system oscillation.

The recommended adjustment method is as follows:

If the factory setting cannot meet the requirements, make proper adjustment. Increase the proportional gain first to ensure that the system does not oscillate, and then reduce the integral time to ensure that the system has quick response and small overshoot.

Note: Improper PI parameter setting may cause too large speed overshoot, and over voltage fault may even occur when the overshoot drops.

P2.06	Vector control slip gain	Default	100%
	Setting range	50%~200%	

For SFVC, it is used to adjust speed stability accuracy of the motor. When the motor with load runs at a very low speed, increase the value of this parameter; when the motor with load runs at a very large speed, decrease the value of this parameter

P2.07	Time constant of speed loop filter	Default	0.05s
	Setting range	0.000s~1.000s	

In the vector control mode, the output of the speed loop regulator is torque current reference. This parameter is used to filter the torque references. It need not be adjusted generally and can be increased in the case of large speed fluctuation. In the case of motor oscillation, decrease the value of this parameter

properly. If the value of this parameter is small, the output torque of the AC drive may fluctuate greatly, but the response is quick.

P2.08	Vector control over-excitation gain	Default	64
	Setting range	0~200	

During deceleration of the AC drive, over-excitation control can restrain rise of the bus voltage to avoid the overvoltage fault. The larger the over-excitation gain is, the better the restraining effect is. Increase the over-excitation gain if the AC drive is liable to overvoltage error during deceleration. Too large over-excitation gain, however, may lead to an increase in output current. Therefore, set this parameter to a proper value in actual applications.

Set the over-excitation gain to 0 in applications of small inertia (the bus voltage will not rise during deceleration) or where there is a braking resistor.

P2.09	Torque upper limit source in speed control mode		Default	0
	Setting range	0	P2.10	
		1	FIV(expansion card)	
		2	FIC	
		3	Reserved	
		4	PULSE setting	
		5	Communication setting	
		6	MIN(FIV(expansion card),FIC)	
		7	MAX(FIV(expansion card),FIC)	
P2.10	Digital setting of torque upper limit in speed control mode		Default	150.0%
	Setting range		0.0%~200.0%	

In the speed control mode, the maximum output torque of the AC drive is restricted by P2.09. If the torque upper limit is analog, pulse or communication setting, 100% of the setting corresponds to the value of P2.10, and 100% of the value of P2.10 corresponds to the AC drive rated torque.

P2.13	Excitation adjustment proportional gain	Default	2000
	Setting range	0~20000	
	Excitation	Default	1300

P2.14	adjustment integral gain		
	Setting range	0~20000	
P2.15	Torque adjustment proportional gain	Default	2000
	Setting range	0~20000	
P2.16	Torque adjustment integral gain	Default	1300
	Setting range	0~20000	

These are current loop PI parameters for vector control. These parameters are automatically obtained through "Asynchronous motor complete auto-tuning", and commonly need not be modified. The dimension of the current loop integral regulator is integral gain rather than integral time.

Note that too large current loop PI gain may lead to oscillation of the entire control loop. Therefore, when current oscillation or torque fluctuation is great, manually decrease the proportional gain or integral gain here.

Group P3 V/F Control Parameters

The group of function codes is only valid for V/F control, not for vector control.

The V/F control mode is applicable to low load applications (fan or pump) or applications where one AC drive operates multiple motors or there is a large difference between the AC drive power and the motor power.

P3.00	V/F curve setting		Default	0
	Setting range	0	Linear V/F	
		1	Multi-point V/F	
		2	Square V/F	
		3	1.2-power V/F	
		4	1.4-power V/F	
		6	1.6-power V/F	
		8	1.8-power V/F	
		9	Reserved	
		10	VF complete separation	
		11	VF half separation	

0: Linear V/F

It is applicable to common constant torque load.

1: Multi-point V/F

It is applicable to special load such as dehydrator and centrifuge. Any such V/F curve can be obtained by setting parameters of P3.03 to P3.08.

2: Square V/F

It is applicable to centrifugal loads such as fan and pump.

3 to 8: V/F curve between linear V/F and square V/F

10: V/F complete separation mode

In this mode, the output frequency and output voltage of the AC drive are independent. The output frequency is determined by the frequency source, and the output voltage is determined by "Voltage source for V/F separation" (P3.13).

It is applicable to induction heating, inverse power supply and torque motor control.

11: V/F half separation mode

In this mode, V and F are proportional and the proportional relationship can be set in P3.13. The relationship between V and F is also related to the rated motor voltage and rated motor frequency in Group P1.

Assume that the voltage source input is X (0 to 100%), the relationship between V and F is: $V/F = 2 * X * (\text{Rated motor voltage}) / (\text{Rated motor frequency})$

P3.01	Torque boost	Default	Model dependent
	Setting range	0.0% ~ 30%	
P3.02	Cut-off frequency of torque boost	Default	50.00Hz
	Setting range	0.00Hz ~ maximum output frequency	

To compensate the low frequency torque characteristics of V/ F control, you can boost the output voltage of the AC drive. If the torque boost is set to too large, the motor may overheat, and the AC drive may suffer over current. If the load is large and the motor startup torque is insufficient, increase the value of P3.01. If the load is small, decrease the value of P3.01. If it is set to 0.0, the AC drive performs automatic torque boost. In this case, the AC drive automatically calculates the torque boost value based on motor parameters including the stator resistance.

P3.02 specifies the frequency under which torque boost is valid. Torque boost becomes invalid when this frequency is exceeded, as shown in the following figure.




Figure 4-2 Manual torque boost diagram

V1: Voltage of manual torque boost

Vb: Rated motor voltage

f1: Cutoff frequency of manual torque boost

fb: Rated motor frequency

P3.03	Multi-point V/F frequency F1	Default	0.00Hz
	Setting range	0.00Hz ~ P3.05	
P3.04	Multi-point V/F voltage V1	Default	0.0%
	Setting range	0.0% ~ 100.0%	
P3.05	Multi-point V/F frequency F2	Default	0.00Hz
	Setting range	P3.03 ~ P3.07	
P3.06	Multi-point V/F voltage V2	Default	0.0%
	Setting range	0.0% ~ 100.0%	
P3.07	Multi-point V/F frequency F3	Default	0.00Hz
	Setting range	P3.05 ~ rated motor frequency (P1.04)	
P3.08	Multi-point V/F voltage V3	Default	0.0%
	Setting range	0.0% ~ 100.0%	

(P3.03~P3.08) These six parameters are used to define the multi-point V/F curve. The multi-point V/F curve is set based on the motor's load characteristic. The relationship between voltages and frequencies must meet: $V1 < V2 < V3$, $F1 < F2 < F3$. At low frequency, higher voltage may cause overheat or even burnt out of the motor and overcurrent stall or overcurrent protection of the AC drive.




Figure 4-3 Multi-point V/F curve setting diagram

V1--V3: Multi-speed V/F 1-3 stage voltage percentage

F1--F3: Multi-speed V/F 1-3 stage frequency

Vb: Rated motor voltage

Fb: Rated motor frequency

P3.09	V/F slip compensation gain	Default	0.0%
	Setting range	0%~200.0%	

This parameter is valid only for the asynchronous motor.

It can compensate the rotational speed slip of the asynchronous motor when the load of the motor increases, stabilizing the motor speed in case of load changes.

If this parameter is set to 100%, it indicates that the compensation when the motor bears rated load is the rated motor slip. The rated motor slip is automatically obtained by the AC drive through calculation based on the rated motor frequency and rated motor rotational speed in group P1.

When adjust the V/F slip compensation gain, Generally, At rated load, if the motor rotational speed is different from the target speed, slightly adjust this Parameter.

P3.10	V/F over-excitation gain	Default	64
	Setting range	0~200	

During deceleration of the AC drive, over-excitation can restrain rise of the bus voltage, to prevent the overvoltage fault. The larger the over-excitation is, the better the restraining result is.

Increase the over-excitation gain if the AC drive is liable to overvoltage error during deceleration. However, too large overexcitation gain may lead to an increase in the output current. Set P3.09 to a proper value in actual applications.

Set the over-excitation gain to 0 in the applications where the inertia is small and the bus voltage will not rise during motor deceleration or where there is a braking resistor.

P3.11	V/F oscillation suppression gain	Default	Model dependent
	Setting range	0~100	

Set this parameter to a value as small as possible in the prerequisite of efficient oscillation suppression to avoid influence on V/F control. Set this parameter to 0 if the motor has no oscillation. Increase the value properly only when the motor has obvious oscillation. The larger the value is, the more obvious the oscillation suppression result will be.

When the oscillation suppression function is enabled, the rated motor current and no- load current must be correct. Otherwise, the V/F oscillation suppression effect will not be satisfactory.

P3.13	Voltage source for V/F separation		Default	0
	Setting range	0	Digital setting （P3.14）	
		1	FIV (expansion card)	
		2	FIC	
		3	Reserved	
		4	PULSE setting	
		5	Multi-reference	
		6	Simple PLC	
		7	PID	
		8	Communication setting	
		100.0% corresponds to the rated motor voltage(P1.02)		
P3.14	Voltage digital setting for V/F separation		Default	0V
	Setting range		0V～rated motor voltage	

V/F separation is generally applicable to the occasions, such as induction heating, inverse power supply and motor torque control.

If V/F separated control is enabled, the output voltage can be set by function code P3.14 or by means of analog, multi-reference, simple PLC, PID or communication. If you set the output voltage by means of non-digital setting, 100% of the setting corresponds to the rated motor voltage. If a negative percentage is set, its absolute value is used as the effective value.

0: digital setting (P3.14)

The output voltage is set directly by P3.14.

1:FIV (expansion card);

2:FIC

The output voltage is set by AI terminals.

4: Pulse setting

The output voltage is set by pulses of the terminal. Pulse setting specification: voltage range 9-30 V, frequency range 0kHz-100 kHz

5: Multi-reference

If the voltage source is multi-reference, parameters in group P4 and PC must be set to determine the corresponding relationship between setting signal and setting voltage.

6: Simple PLC

If the voltage source is simple PLC mode, parameters in group FC must be set to determine the setting output voltage.

7: PID

The output voltage generates based on PID closed loop. For details, see the descriptions of PID in group PA.

8: Communication setting

The output voltage is set by the host computer by the means of communication given. When the above voltage source is selected from 1 to 8, 0 to 100% corresponds to the output voltage 0V to the rated voltage of the motor.

P3.15	Voltage rise time of V/F separation	Default	0.0s
	Setting range	0.0s~1000.0s	
P3.16	Voltage decline time of V/F separation	Default	0.0s
	Setting range	0.0s~1000.0s	

P3.15 indicates the time required for the output voltage to rise from 0 V to the rated motor voltage shown as t1 in the following figure.




Figure 4-4 V/F Separation diagram

P3.17	Stop mode of V/F separation	Default	0
	Setting range	0: Frequency/voltage independently decrease to 0 1: After voltage decrease to 0, frequency decrease again	

0: V/F separation output voltage and decrease to 0V with the voltage deceleration time set by P3.15, at the same time output frequency and decrease to 0Hz with the deceleration time set by P0.18.

1: After V/F separation output voltage and decrease to 0V with the voltage deceleration time set by P3.15, output frequency and decrease to 0Hz with the deceleration time set by P0.18

P3.18	Action current of over current stall	Default	150%
	Setting range	50%~200%	
P3.19	Over current stall enable	Default	1
	Setting range	0: Disabled 1: Enabled	


During the process of acceleration, constant speed, deceleration, if the current exceeds the over current stall, over current stall will action, output frequency will decrease, until current back to lower than over current stall, frequency will accelerate to target frequency, actual acceleration time will lasts, if the

acceleration time can not meet require, add the value of P3.18 properly.

P3.20	Over current stall suppression gain	Default	20
	Setting range	0~100	
P3.21	Action current compensation coefficient of multiple over current stall	Default	50%
	Setting range	50%~200% 50% invalid	

In high frequency zone, motor drive current is small, For below rated frequency case, same stall current, the speed of motor will decrease too much, to improve the motor running performance, decrease stall action current of the rated frequency above, special good effect for the application of centrifuge that need run in high frequency and multiple rated motor frequency.

Transient stall action current exceeding rated frequency = $(f_s/f_n) * k * \text{LimitCur}$;
 f_s as running frequency, f_n as rated motor frequency, k as P3.21“Action current compensation coefficient of multiple over current stall”, LimitCur as P3.18“Action current of over current stall”;



P3.22	Action voltage of over current stall	Default	760.0V
	Setting range	200.0V~2000.0V	
P3.23	Over voltage stall enable	Default	1
	Setting range	0: Disabled 1: Enabled	
P3.24	Over voltage stall suppression gain	Default	30

	Setting range	0~100	
P3.25	Over voltage stall suppression voltage gain	Default	30
	Setting range	0~100	
P3.26	Maximum rising frequency limit of over voltage stall	Default	5Hz
	Setting range	0~50Hz	

Increase the value of P3.24 will improve the control of bus voltage, but output frequency will oscillate, decrease the value of P3.24 if output frequency oscillate is large. Increase the value of P3.25 will reduce the over shoot of bus voltage. The maximum rising frequency of over voltage stall is set by P3.26

Note: When use brake resistor or install brake unit, please set P3.11 to 0, otherwise, the running current may too large. Please set P3.23 to 0, otherwise, the deceleration time may too long.

Group P4 Input terminals

T200 series inverter are with 8 multi-function digital inputs (X5 can be used as a high-speed pulse input terminal), two analog input terminals.

P4.00	X1 function selection	Default	1 (Forward RUN)
P4.01	X2 function selection	Default	4 (Forward Jog)
P4.02	X3 function selection	Default	9 (Fault reset)
P4.03	X4 function selection	Default	12 (Multi-reference 1)
P4.04	X5 function selection	Default	13 (Multi-reference 2)
P4.05	X6 function selection (Expansion card)	Default	0
P4.06	X7 function selection (Expansion card)	Default	0
P4.07	Reserved	Default	0

The parameters of the functions available for the multi-function input terminals. Select the functions in the table as follows:

Value	Function	Description
0	No function	Set 0 for reserved terminals to avoid malfunction.
1	Forward run (FWD)	The terminal is used to control forward or reverse RUN of the AC drive.
2	Reverse run	

	(REV)	
3	Three-line control	The terminal determines three-line control of the AC drive. For details, see the descriptions of P4.11.
4	Forward JOG (FJOG)	FJOG indicates forward JOG running, while RJOG indicates reverse JOG running. The JOG frequency, acceleration time and deceleration time are described respectively in P8.00, P8.01 and P8.02.
5	Reverse JOG (RJOG)	
6	Terminal UP	If the frequency is determined by external terminals, the terminals with the two functions are used as increment and decrement commands for frequency modification. When the frequency source is digital setting, they are used to adjust the frequency.
7	Terminal DOWN	
8	Coast to stop	The AC drive blocks its output, the motor coasts to rest and is not controlled by the AC drive. It is the same as coast to stop described in P1.10.
9	Fault reset (RESET)	The terminal is used for fault reset function, the same as the function of RESET key on the operation panel. Remote fault reset can be implemented by this function.
10	RUN pause	The AC drive decelerates to stop, but the running parameters are all memorized, such as PLC, swing frequency and PID parameters. After this function is disabled, the AC drive resumes its status before stopping.
11	Normally open (NO) input of external fault	If this terminal becomes ON, the AC drive reports EF and performs the fault protection action. For more details, see the description of P9.47.
12	Multi-reference terminal 1	The setting of 16 speeds or 16 other references can be implemented through combinations of 16 states of these four terminals. Refer to table 1 for more details
13	Multi-reference terminal 2	
14	Multi-reference terminal 3	
15	Multi-reference terminal 4	
16	Acceleration/ deceleration time selection1	Totally four groups of acceleration/deceleration time can be selected through combinations of two states of these two terminals.
	Acceleration/	

17	deceleration time selection2	
18	Frequency source switchover	The terminal is used to switch and choose different frequency source. Choose function code P0.07 setting according to the frequency source .when set two kinds of frequency source switching as frequency source. the terminal is used to realize switching between the two frequency source.
19	UP and DOWN setting clear (terminal, operation panel)	If the frequency source is digital setting, the terminal is used to clear the modification by using the UP/DOWN function or the increment/decrement key on the operation panel, returning the set frequency to the value of P0.08.
20	Command source switchover terminal	If the command source is set to terminal control (P0.02 = 1), this terminal is used to perform switchover between terminal control and operation panel control. If the command source is set to communication control (P0.02 = 2), this terminal is used to perform switchover between communication control and operation panel control.
21	Acceleration/ Deceleration prohibited	It enables the AC drive to maintain the current frequency output without being affected by external signals (except the STOP command).
22	PID pause	PID is invalid temporarily. The AC drive maintains the current frequency output without supporting PID adjustment of frequency source.
23	PLC status reset	The terminal is used to restore the original status of PLC control for the AC drive when PLC control is started again after a pause.
24	Swing pause	The AC drive outputs the central frequency, and the swing frequency function pauses.
25	Counter input	This terminal is used to count pulses.
26	Counter reset	This terminal is used to clear the counter status.
27	Length counter input	This terminal is used to count the length.
28	Length reset	This terminal is used to clear the length.
29	Torque control prohibited	The AC drive is prohibited from torque control and enters the speed control mode.
	Pulse	

30	input(enabled only for X5)	X5 is used for pulse input.
31	Reserved	Reserved
32	Immediate DC braking	After this terminal becomes ON, the AC drive directly switches over to the DC braking state.
33	Normally closed (NC) input of external fault	After this terminal becomes ON, the AC drive reports EF and stops.
34	Frequency modification enabled	If this terminal becomes effective , the AC drive will not respond to any frequency modification until this terminal becomes invalid.
35	Reverse PID action direction	After this terminal becomes ON, the PID action direction is reversed to the direction set in PA.03.
36	External STOP terminal 1	In operation panel mode, this terminal can be used to stop the AC drive, equivalent to the function of the STOP key on the operation panel.
37	Command source switchover terminal 2	It is used to perform switchover between terminal control and communication control. If the command source is terminal control, the system will switch over to communication control after this terminal becomes effective.
38	PID integral pause	After this terminal becomes effective, the integral adjustment function pauses. However, the proportional and differentiation adjustment functions are still valid.
39	Switchover between main frequency source X and preset frequency	After this terminal becomes effective, the frequency source X is replaced by the preset frequency set in P0.08
40	Switchover between auxiliary frequency source Y and preset frequency	After this terminal is effective, the frequency source Y is replaced by the preset frequency set in P0.08

43	PID parameter switchover	If the PID parameters switchover performed by means of X terminal (PA.18 = 1), the PID parameters are PA.05 to PA.07 when the terminal becomes invalid.; the PID parameters PA.15 to PA.17 are used when this terminal becomes effective.
44	Reserved	
45	Reserved	
46	Speed control/Torque control switchover	This terminal enables the AC drive to switch over between speed control and torque control. When this terminal becomes invalid, the AC drive runs in the mode set in C0.00. When this terminal becomes effective, the AC drive switches over to another control mode.
47	Emergency stop	When this terminal becomes effective, the AC drive stops within the shortest time. During the stop process, the current remains at the set current upper limit. This function is used to satisfy the requirement of stopping the AC drive in emergency state.
48	External STOP terminal 2	In any control mode (operation panel, terminal or communication), it can be used to make the AC drive decelerate to stop. In this case, the deceleration time is deceleration time 4.
49	Deceleration DC braking	When this terminal becomes ON, the AC drive decelerates to the initial frequency of stop DC braking and then switches over to DC braking state.
50	Clear the current running Time	When this terminal becomes ON, the AC drive's current running time is cleared. This function must be supported by P8.42 and P8.53.

Additional table 1 :The descriptions of multi-reference

The four multi-reference terminals have 16 state combinations, corresponding to 16 reference values, as listed in the following table 1.

K4	K3	K2	K1	Reference Setting	CorresponXng Parameter
OFF	OFF	OFF	OFF	Multi- reference 0	PC.00
OFF	OFF	OFF	ON	Multi- reference 1	PC.01
OFF	OFF	ON	OFF	Multi- reference 2	PC.02
OFF	OFF	ON	ON	Multi- reference 3	PC.03
OFF	ON	OFF	OFF	Multi- reference 4	PC.04
OFF	ON	OFF	ON	Multi- reference 5	PC.05
OFF	ON	ON	OFF	Multi- reference 6	PC.06

OFF	ON	ON	ON	Multi- reference 7	PC.07
ON	OFF	OFF	OFF	Multi- reference 8	PC.08
ON	OFF	OFF	ON	Multi- reference 9	PC.09
ON	OFF	ON	OFF	Multi- reference 10	PC.10
ON	OFF	ON	ON	Multi- reference 11	PC.11
ON	ON	OFF	OFF	Multi- reference 12	PC.12
ON	ON	OFF	ON	Multi- reference 13	PC.13
ON	ON	ON	OFF	Multi- reference 14	PC.14
ON	ON	ON	ON	Multi- reference 15	PC.15

If the frequency source is multi-reference, the value 100% of PC.00 to PC.15 corresponds to the maximum frequency of P0.10.

Besides the multi-speed function, the multi-reference can be also used as the PID setting source or the voltage source for V/F separation, satisfying the requirement on switchover of different setting values.

Additional table 2:Terminal function descriptions of acceleration/deceleration time selection

Terminal2	Terminal1	Acceleration/Deceleration Time Selection	Corresponding Parameters
OFF	OFF	Acceleration/Deceleration time 1	P0.17、 P0.18
OFF	ON	Acceleration/Deceleration time 2	P8.03、 P8.04
ON	OFF	Acceleration/Deceleration time 3	P8.05、 P8.06
ON	ON	Acceleration/Deceleration time 4	P8.07、 P8.08

P4.10	S terminal filter time	Default	0.010s
	Setting range	0.000s～1.000s	

It is used to set the software filter time of input terminal status. If input terminals are liable to interference and may cause malfunction, increase the value of this parameter to enhance the anti-interference capability. However, increase of filter time will reduce the response of input terminals.

P4.11	Terminal command mode		Default	0
	Setting range	0	Two-line mode 1	
		1	Two-line mode 2	
		2	Three-line mode 1	
		3	Three-line mode 2	

This parameter defines the external terminal, control four different inverter

running ways.

0:Two-line mode 1: this pattern is the most commonly used two line mode. Positive and reverse operation of the motor is determined by terminal Xx, Xy, The parameters are set as below:

Terminal	Set value	Function Description
Xx	1	Forward RUN （FWD）
Xy	2	Reverse RUN （REV）

Among them, Xx, Xy is X1~X7 multi-function input terminals, level effectively.




Figure 4-6 Two-line mode 1

1:Two-line mode 2: use this pattern when Xx terminal functions for operation can make terminal, and Xy terminal function determined to run. The parameters are set as below:

Terminal	Set value	Function Description
Xx	1	Forward RUN （FWD）
Xy	2	Reverse RUN （REV）

Among them, Xx、Xy is X1~X7 multi-function input terminals, level effectively.




Figure 4-7 Two-line mode 2


2: Three-line mode 1

In this mode, Xn is RUN enabled terminal, and the direction is respectively decided by Xx and Xy. The parameters are set as below:

Terminal	Set value	Function Description
Xx	1	Forward RUN (FWD)
Xy	2	Reverse RUN (REV)
Xn	3	Three-line control

Xn terminal must be closed when it need to run, to realize the forward and reverse control system of the motor by Xx or Xy pulse rising.

When it need to stop, must be done by disconnecting Xn terminal signal. Among them, the Xx, Xy, Xn as ,X1~X7 multi-function input terminals,Xx, Xy is the pulse effective, Xn is the level effective.



Among them,KB1: stop button KB2:forward button KB3:Reverse button

3: Three-line mode 2


In this mode, Xn is RUN enabled terminal. The RUN command is given by Xx and the direction is decided by Xy.

The parameters are set as below:

Terminal	Set value	Function Description
Xx	1	Forward Run （FWD）
Xy	2	Reverse
Xn	3	Three-line control

Xn terminals must be closed when there is a need to run, Xn terminals, produced by Xx pulse rising along the motor running signal, the state of the Xy produce motor direction signals.

When there is a need to stop, by disconnecting Sn terminal signal to realize. Among them, the Xx, Xy, Xn is X1~X7 multi-function input terminals, Xx is the pulse effective, Xy, Xn are the level effective.



KB1: Stop button KB2: Run button

P4.12	Terminal UP/DOWN changing rate		Default	1.00Hz/s
	Setting range	0.01Hz/s~65.535Hz/s		

When it is used to set terminal UP/DOWN to adjust the set frequency .Frequency changing rate is the frequency variation per second

P4.13	FI curve 1 minimum input		Default	0.00V
	Setting range	0.00V~P4.15		
P4.14	Corresponding setting of FI		Default	0.0%



	curve 1 minimum input			
	Setting range	-100.00%~100.0%		
P4.15	FI curve 1 maximum input		Default	10.00V
	Setting range	P4.13~10.00V		
P4.16	Corresponding setting of FI curve 1 maximum input		Default	100.0%
	Setting range	-100.00%~100.0%		
P4.17	FI curve 1 filter time		Default	0.10s
	Setting range	0.00s~10.00s		

These parameters are used to define the relationship between the analog input voltage and the corresponding setting. When the analog input voltage exceeds the maximum value (P4.15), the analog voltage maximum value is calculated by “maximum input”.When the analog input voltage is less than the setting minimum input (P4.13), the value set in P4.14 (Setting for FI less than minimum input) is calculated by the minimum input or 0.0%

When the analog input is current input, 1mA current corresponds to 0.5V voltage. FI input filter time is used to set the software filter time of FI. If the analog input is liable to interference, increase the filter time value of this parameter to stabilize the detected analog input.However, increase of the FI filter time will slow down the response of analog detection. Set this parameter properly based on actual conditions.

In different applications, 100% of analog input corresponds to different nominal values. For details, refer to the description of different applications.

Two typical setting examples are shown in the following figure.



P4.18	FI curve 2 minimum input	Default	0.00V
	Setting range	0.00V ~ P4.20	
P4.19	Corresponding setting of FI curve 2 minimum input	Default	0.0%
	Setting range	-100.00% ~ 100.0%	
P4.20	FI curve 2 maximum input	Default	10.00V
	Setting range	P4.18 ~ 10.00V	

P4.21	Corresponding setting of FI curve 2 maximum input		Default	100.0%
	Setting range	-100.00%~100.0%		
P4.22	FI curve 2 filter time		Default	0.10s
	Setting range	0.00s~10.00s		

The method and functions of setting FI curve 2 are similar to that of setting FI curve 1 function.

P4.23	FI curve 3 minimum input		Default	0.00V
	Setting range	0.00s~P4.25		
P4.24	Corresponding setting of FI curve 3 minimum input		Default	0.0%
	Setting range	-100.00%~100.0%		
P4.25	FI curve 3 maximum input		Default	10.00V
	Setting range	P4.23~10.00V		
P4.26	Corresponding setting of FI curve 3 maximum input		Default	100.0%
	Setting range	-100.00%~100.0%		
P4.27	FI curve 3 filter time		Default	0.10s
	Setting range	0.00s~10.00s		

The method and functions of setting FI curve 3 are similar to that of setting FI curve 1 function.

P4.28	PULSE minimum input		Default	0.00kHz
	Setting range	0.00kHz~P4.30		
P4.29	Corresponding setting of pulse minimum input		Default	0.0%
	Setting range	-100.00%~100.0%		

P4.30	PULSE maximum input	Default	50.00kHz
	Setting range	P4.28～50.00kHz	
P4.31	Corresponding setting of pulse maximum input	Default	100.0%
	Setting range	-100.00%～100.0%	
P4.32	PULSE filter time	Default	0.10s
	Setting range	0.00s～10.00s	

These parameters are used to set the relationship between pulse frequency input and corresponding settings. The pulses can only be input by X5. The method of setting this function is similar to that of setting FI curve 1 ,Refer to the descriptions of FI curve 1

FI curve selection		Default	321
P4.33	Setting range	Unit's digit	FIV (expansion card) curve selection
		1	Curve 1 (2 points, refer to P4.13～P4.16)
		2	Curve 2 (2 points, refer to P4.18～P4.21)
		3	Curve 3 (2 points, refer to P4.23～P4.26)
		4	Curve 4 (4 points, refer to C6.00～C6.07)
		5	Curve 5 (4 points, refer to C6.08～C6.15)
	Hundred's digit	Ten's digit	FIC curve selection (1～6, same as FIV)
			Reserved

The unit's digit, ten's digit and hundred's digit of this parameter are respectively used to select the corresponding curve of FIV,FIC. Any one curve of the five curves can be selected for 2 analog inputs.

Curve 1, curve 2 and curve 3 are all 2-point curves, need to set in group P4. Curve 4 and curve 5 are both 4-point curves, set in group C6.

P4.34	Setting for FI less than minimum input		Default	000
	Setting range	Unit's digit	Setting for FIV (expansion card) less than minimum input	
		0	Corresponding to minimum input setting	
		1	0.0%	
		Ten's digit	Setting for FIC less than minimum input (0～1, same as FIV (expansion	

			card))
		Hundred's digit	Reserved

The function code is used to determine the corresponding setting when the analog input voltage is less than the minimum value.

The unit's digit, ten's digit and hundred's digit of this function code respectively correspond to the setting for FIV,FIC .If the value of a certain digit is selected to 0, when analog input voltage is less than the minimum input, the corresponding setting of the minimum input (P4.14, P4.19) is used.

If the value of a certain digit is selected to 1, when analog input voltage is less than the minimum input, the corresponding value of this analog input is 0.0%

P4.35	X1 delay time		Default	0.0s
	Setting range	0.0s～3600.0s		
P4.36	X2 delay time		Default	0.0s
	Setting range	0.0s～3600.0s		
P4.37	X3 delay time		Default	0.0s
	Setting range	0.0s～3600.0s		

These parameters are used to set the delay time of the AC drive when the status of the terminal changes.

Currently, only X1,X2 and X3 support the delay time function.

P4.38	X valid mode selection 1		Default	00000
	Setting range	Unit's digit	FWD valid mode	
		0	High level valid	
		1	Low level valid	
		Ten's digit	X2 valid mode (0～1, same as FWD)	
		Hundred's digit	X3 valid mode (0～1, same as FWD)	
		Thousand's digit	X4 valid mode (0～1, same as FWD)	
		Ten thousand's digit	X5 valid mode (0～1, same as FWD)	
P4.39	X valid mode selection 2		Default	00000
	Setting	Unit's digit	X6 (Expansion card)	

	range	0	High level valid
		1	Low level valid
		Ten's digit	X7 (Expansion card)
		Hundred's digit	Reserved
		Thousand's digit	Reserved
		Ten thousand's digit	Reserved

These parameters are used to set digital input terminals' valid mode .

The X terminal is valid when being connected with COM, and invalid when being disconnected from COM.

The X terminal is invalid when being connected with COM, and valid when being disconnected from COM.

Group P5 Output terminals

The T200 provides 1 multi-function analog output terminal FOV, 1 multi-function relay output terminal and a YO terminal.

P5.00	MO1 terminal output mode(Expansion card)		Default	0
	Setting range	0	Pulse output (MO1-COM)	
		1	Switch output (MOA-MOB-MOC)	

MO1 is programmable multiplex terminal, it can be used as high speed pulse output terminal(MO1-COM), also can be used as open collector switch output terminal (MOA-MOB-MOC). When it used as MO1-COM, the maximum frequency of output pulse is 100kHz. The function of MO1-COM, please refer to P5.06.

P5.01	MOA-MOB-MOC function selection (Expansion card)	Default	0
P5.02	Relay output function (YA-YB-YC)	Default	2
P5.03	Reserved	Default	0
P5.04	YO output function selection	Default	1

These parameters are used to select the functions of the 3 digital output terminals. The functions of the output terminals are described in the following table.

Value	Function	Description
0	No output	The terminal has no function.

1	AC drive running	When the AC drive is running and has output frequency(can be zero), the terminal outputs ON.
2	Fault output (stop)	When the AC drive stops due to a fault, the terminal outputs ON.
3	Frequency-level detection FDT1 output	Refer to the descriptions of P8.19 and P8.20.
4	Frequency reached	Refer to the descriptions of P8.21.
5	Zero-speed running (no output at stop)	If the AC drive runs with the output frequency of 0, the terminal outputs ON. If the AC drive is in the stop state, the terminal outputs OFF.
6	Motor overload pre-warning	The AC drive judges whether the motor load exceeds the overload pre-warning threshold before performing the protection action. If the pre-warning threshold is exceeded, the terminal outputs ON. For motor overload parameters, see the descriptions of P9.00 to P9.02.
7	AC drive overload pre-warning	The terminal outputs ON 10s before the AC drive overload protection action is performed.
8	Set count value reached	The terminal outputs ON when the count value reaches the value set in Pb.08.
9	Designated count value reached	The terminal outputs ON when the count value reaches the value set in Pb.09. Count function refer to group Pb.
10	Length reached	The terminal outputs ON when the detected actual length exceeds the value set in Pb.05.
11	PLC cycle complete	When simple PLC completes one cycle, the terminal outputs a pulse signal with width of 250 ms.
12	Accumulative running time reached	If the accumulative running time of the AC drive exceeds the time set in P8.17, the terminal outputs ON.
13	Frequency limited	If the set frequency exceeds the frequency upper limit or lower limit and the output frequency of the AC drive reaches the upper limit or lower limit, the terminal outputs ON.
14	Torque limited	In speed control mode, if the output torque reaches the torque limit, the AC drive enters the stall protection state and meanwhile the terminal outputs ON.

15	Ready for RUN	If the AC drive main circuit and control circuit become stable, and the AC drive detects no fault and is ready for RUN, the terminal outputs ON.
16	FIV (expansion card) >FIC	When the input of FIV is larger than the input of FIC, the terminal outputs ON.
17	Frequency upper limit reached	If the running frequency reaches the upper limit, the Terminal outputs ON.
18	Frequency lower limit reached (no output at stop)	If the running frequency reaches the lower limit, the terminal becomes ON. In the stop state, the terminal outputs OFF.
19	Under voltage state output	If the AC drive is in under voltage state, the terminal outputs ON.
20	Communication setting	Refer to the communication protocol.
21	Reserved	Reserved
22	Reserved	Reserved
23	Zero-speed running 2 (having output at stop)	If the output frequency of the AC drive is 0, the terminal becomes ON. In the state of stop, the signal is still ON.
24	Accumulative power-on time reached	If the AC drive accumulative power-on time (P7.13) exceeds the value set in P8.16, the terminal becomes ON.
25	Frequency level detection FDT2 output	Refer to the descriptions of P8.28 and P8.29.
26	Frequency 1 reached output	Refer to the descriptions of P8.30 and P8.31.
27	Frequency 2 reached output	Refer to the descriptions of P8.32 and P8.33.
28	Current 1 reached output	Refer to the descriptions of P8.38 and P8.39.
29	Current 2 reached output	Refer to the descriptions of P8.40 and P8.41.
30	Timing reached output	If the timing function (P8.42) is valid, the terminal becomes ON after the current running time of the AC drive reaches the set time.
	FIV (expansion	If FIV input is larger than the value of P8.46

31	card) input limit exceeded	(FIV(expansion card) input voltage upper limit) or lower than the value of P8.45 (FIV(expansion card) input voltage lower limit), the terminal outputs ON.
32	Load becoming 0	If the load becomes 0, the terminal outputs ON.
33	Reverse running	If the AC drive is in the reverse running state, the terminal outputs ON.
34	Zero current state	Refer to the descriptions of P8.28 and P8.29.
35	Module temperature reached	If the heatsink temperature of the inverter module (P7.07) reaches the set module temperature threshold (P8.47), the terminal outputs ON.
36	Software current limit exceeded	Refer to the descriptions of P8.36 and P8.37.
37	Frequency lower limit reached (having output at stop)	If the running frequency reaches the lower limit, the terminal becomes ON. In the stop state, the signal is still ON.
38	Alarm output	If a fault occurs on the AC drive and the AC drive continues to run, the terminal outputs the alarm signal.
39	Reserved	Reserved
40	Current running time reached	If the current running time of AC drive exceeds the value of P8.53, the terminal outputs ON.

P5.06	MO1 output function selection	Default	0
P5.07	FOV output function selection	Default	0
P5.08	FOC(Expansion card) output function selection	Default	1

Output pulse frequency range of MO1 is 0.01kHz~ P5.09 (Maximum output frequency of MO1) , P5.09 can be set by 0.01kHz~100.00kHz.

Analog output range of FOV and FOC is 0V~10V , or 0mA~20mA. The relationship between pulse and analog output ranges and corresponding functions is listed in the following table.

Value	Function	Range (Corresponding to Pulse or Analog Output Range 0.0%~100.0%)
0	Running frequency	0~maximum output frequency
1	Set frequency	0~maximum output frequency

2	Output current	0~2 times of rated motor current
3	Output torque	0~2 times of rated motor torque
4	Output power	0~2 times of rated power
5	Output voltage	0~1.2 times of rated AC drive voltage
6	Pulse input	0.01kHz~100.00kHz
7	FIV (expansion card)	0V~10V
8	FIC	0V~10V (or 0~20mA)
9	Reserved	
10	Length	0~maximum set length
11	Count value	0~maximum count value
12	Communication setting	0.0%~100.0%
13	Motor rotational speed	0~rotational speed corresponding to maximum output frequency
14	Output current	0.0A~1000.0A
15	Output voltage	0.0V~1000.0V

P5.09	MO1 output maximum frequency	Default	50.00kHz
	Setting range	0.01kHz~100.00kHz	

When MO1 terminal used as pulse output, the function code is used to select maximum frequency of output pulse.

P5.10	FOV zero offset coefficient	Default	0.0%
	Setting range	-100.0%~+100.0%	
P5.11	FOV gain	Default	1.00
	Setting range	-10.00~+10.00	
P5.12	FOC zero offset coefficient	Default	0.00%
	Setting range	-100.0%~+100.0%	
P5.13	FOC gain	Default	1.00
	Setting range	-10.00~+10.00	

These function codes are used to correct the zero drift of analog output and the output amplitude deviation. They can also be used to define the desired FOV ,FOC curve.

If "b" represents zero offset, "k" represents gain, "Y" represents actual output, and "X" represents standard output, the actual output is: $Y = kX + b$. Among them, the zero offset coefficient 100% of FOV corresponds to 10 V (or 20mA). The standard output refers to the value corresponding to the analog output of 0 to 10 V (or 0 to 20mA) with no zero offset or gain adjustment. For example, if the analog output is used as the running frequency, and it is expected that the output is 8 V when the frequency at the maximum frequency is 3V, the gain shall be set to -0.50, and the zero offset shall be set to 80%.

P5.17	MOA-MOB-MOC output delay time	Default	0.0s
	Setting range	0.0s~3600.0s	
P5.18	YA-YB-YC output delay time	Default	0.0s
	Setting range	0.0s~3600.0s	

These parameters are used to set the delay time of output terminals relay from status change to actual output.

P5.22	Output terminal valid mode selection		Default	00000
	Setting range	Unit's digit	MOA-MOB-MOC valid mode	
		0	Positive logic	
		1	Negative logic	
		Ten's digit	YA-YB-YC valid mode (0~1, Same as MOA-MOB-MOC)	
		Hundred's digit	Reserved	

It is used to definite the logic of output terminals relay.

0: Positive logic

The output terminal is valid when it is connected with corresponding common terminal, and invalid when it is disconnected from corresponding common terminal.

1: Negative logic

The output terminal is invalid when it is connected with corresponding common terminal, and valid when it is disconnected from corresponding common terminal.

Group P6 Start /stop control

P6.00	Start mode		Default	0
	Setting range	0	Direct start	
		1	Rotational speed tracking restart	

		2	Pre-excited start (asynchronous motor)
--	--	---	--

0: Direct start

If the DC braking time is set to 0, the AC drive starts to run at the startup frequency. If the DC braking time is not 0, the AC drive performs DC braking first and then starts to run at the startup frequency. It is applicable to small-inertia load application where the motor is likely to rotate at startup time.

1: Rotational speed tracking restart

The AC drive judges the rotational speed and direction of the motor first and then starts at the tracked frequency. Such smooth start has no impact on the rotating motor. It is applicable to the restart upon instantaneous power failure of large-inertia load. To ensure the performance of rotational speed tracking restart, set the motor parameters in group P1 correctly.

2: Pre-excited start (asynchronous motor)

It is valid only for asynchronous motor and used for building the magnetic field before the motor runs. For pre-excited current and pre-excited time, see parameters of P6.05 and P6.06. If the pre-excited time is 0, the AC drive cancels pre-excitation and starts to run at startup frequency. If the pre-excited time is not 0, the AC drive pre-excites first before starting, improving the dynamic response of the motor.

P6.01	Rotational speed tracking mode		Default	0
	Setting range	0	Start from stop frequency	
		1	From zero speed start	
		2	From maximum frequency start	

To complete the rotational speed tracking process within the shortest time, select the proper mode in which the AC drive tracks the motor rotational speed.

0: From frequency at stop to track down.

It is the commonly selected mode.

1: From zero frequency to track down.

It is applicable to restart after a long time of power failure.

2: From the maximum frequency to track down.

It is applicable to the power-generating load.

P6.02	Rotational speed tracking speed		Default	20
	Setting range	1~100		

In the rotational speed tracking restart mode, select the rotational speed tracking speed. The larger the value is, the faster the tracking is. However, too large setting value may cause unreliable tracking.

P6.03	Startup frequency	Default	0.00Hz
	Setting range	0.00Hz～10.00Hz	
P6.04	Startup frequency holding time	Default	0.0s
	Setting range	0.0s～100.0s	

To ensure the motor torque at AC drive startup, set a proper startup frequency. In addition, to build excitation when the motor starts up, the startup frequency must be held for a certain time.

The startup frequency (P6.03) is not restricted by the frequency lower limit. If the set target frequency is lower than the startup frequency, the AC drive will not start and stays in the standby state.

During switchover between forward rotation and reverse rotation, the startup frequency holding time is disabled. The holding time is not included in the acceleration time but in the running time of simple PLC.

Example 1:

P0.04=0 The frequency source is digital setting.

P0.10=2.00Hz The digital setting frequency is 2.00 Hz.

P6.03=5.00Hz The startup frequency is 5.00 Hz.

P6.04=2.0s The startup frequency holding time is 2.0s.

In this example, the AC drive stays in the standby state and the output frequency is 0.00 Hz.

Example 2:

P0.04=0 The frequency source is digital setting.

P0.10=2.00Hz The digital setting frequency is 2.00 Hz.

P6.03=5.00Hz The startup frequency is 5.00 Hz.

P6.04=2.0s The startup frequency holding time is 2.0s.

In this example, the AC drive accelerates to 5.00 Hz, and then accelerates to the set frequency 10.00 Hz after 2s.

P6.05	Startup DC braking current/Pre-excited current	Default	0%
	Setting range	0%～100%	
P6.06	Startup DC braking time/Pre-excited time	Default	0.0s
	Setting range	0.0s～100.0s	

Startup DC braking is generally used during restart of the AC drive after the

rotating motor stops. Pre-excitation is used to make the AC drive build magnetic field for the asynchronous motor before startup to improve the responsiveness.

Startup DC braking is valid only for direct start. In this case, the AC drive performs DC braking at the set startup DC braking current. After the startup DC braking time, the AC drive starts to run. If the startup DC braking time is 0, the AC drive starts directly without DC braking. The larger the startup DC braking current is, the larger the braking force is.

If the startup mode is pre-excited start, the AC drive builds magnetic field based on the set pre-excited current. After the pre-excited time, the AC drive starts to run. If the pre-excited time is 0, the AC drive starts directly without pre-excitation. The startup DC braking current or pre-excited current is a percentage relative to the base Value.

P6.07	Acceleration/ Deceleration mode		Default	0
	Setting range	0	Linear acceleration/deceleration	
		1	S-curve acceleration/deceleration A	
		2	S-curve acceleration/deceleration B	

It is used to set the frequency change mode during the AC drive start and stop process.

0: Linear acceleration/deceleration


The output frequency increases or decreases in linear mode. The Z2000 provides four group of acceleration/deceleration time, which can be selected by using P4.00 to P4.07.

1: S-curve acceleration/deceleration A

The output frequency is increasing or decreasing as S-curve. S-curve is required to use in the occasion where smoothly start or stop, such as the elevator, conveyer belt, etc. Function code P6.08 and P6.09 respectively defines S-curve the start and end of the acceleration/deceleration time rate.

2: S-curve acceleration/deceleration B

In this curve, the rated motor frequency is always the inflexion point. This mode is f_b usually used in applications where acceleration/deceleration is required at the speed higher than the rated frequency.



When the set frequency is higher than the rated frequency, the acceleration/deceleration time is:

$$t = \left(\frac{4}{9} * \left(\frac{f}{f_b} \right) + \frac{5}{9} \right) * T$$

In the formula, “f” is the set frequency, “fb” is the rated motor frequency and T is the acceleration time from 0 Hz to the rated frequency fb.

S-curve acceleration/deceleration B

P6.08	Time proportion of S-curve start segment	Default	30.0%
	Setting range	0.0% ~ (100.0%-P6.09)	
P6.09	Time proportion of S-curve end segment	Default	30.0%
	Setting range	0.0% ~ (100.0%-P6.08)	

These two parameters respectively define the time proportions of the start segment and the end segment of S-curve acceleration/deceleration A. They must satisfy the requirement:

$$P6.08 + P6.09 \leq 100.0\%.$$

In Figure 4-2, t1 is the time defined in P6.08, within which the slope of the output frequency change increases gradually. t2 is the time defined in P6.09, within which the slope of the output frequency change gradually decreases to 0. Within the time between t1 and t2, the slope of the output frequency

change remains unchanged, that is, linear acceleration/deceleration.




Figure 4-11 S-curve acceleration/deceleration A

P6.10	Stop mode		Default	0
	Setting	0	Decelerate to stop	
		1	Coast to stop	

0: Decelerate to stop

After the stop command is enabled, the AC drive decreases the output frequency according to the deceleration time and stops when the frequency decreases to zero.

1: Coast to stop

After the stop command is enabled, the AC drive immediately stops the output. The motor will coast to stop based on the mechanical inertia.。

P6.11	Initial frequency of stop DC braking		Default	0.00Hz
	Setting range	0.00Hz～maximum frequency		
P6.12	Waiting time of stop DC braking		Default	0.0s
	Setting range	0.0s～100.0s		
P6.13	Stop DC braking current Setting Range		Default	0%
	Setting	0%～100%		

	range	
P6.14	Stop DC braking time	Default 0.0s
	Setting range	0.0s~100.0s

Initial frequency of stop DC braking

During the process of decelerating to stop, the AC drive starts DC braking when the running frequency is lower than the value set in P6.11.

Waiting time of stop DC braking

When the running frequency decreases to the initial frequency of stop DC braking, the AC drive stops output for a certain period and then starts DC braking. This prevents faults such as over-current caused due to DC braking at high speed.

Stop DC braking current

This parameter specifies the output current at DC braking and is a percentage relative to the base value. If the rated motor current is less than or equal to 80% of the rated AC drive current, the base value is the rated motor current. If the rated motor current is greater than 80% of the rated AC drive current, the base value is 80% of the rated AC drive current.

Stop DC braking time

This parameter specifies the holding time of DC braking. If it is set to 0, DC braking is canceled. The stop DC braking process is shown in the following figure.




Figure 4-12 Stop DC braking process

P6.15	Brake use ratio	Default	100%
	Setting	0%~100%	

It is valid only for the AC drive with internal braking unit and used to adjust the

duty ratio of the braking unit. The larger the value of this parameter is, the better the braking result will be. However, too larger value causes great fluctuation of the AC drive bus voltage during the braking process.

Group P7 Operation Panel and Display

P7.02	STOP/RESET function		Default	1
	Setting	0	Only valid in operation panel mode	
	range	1	Valid in any operation mode	

P7.03	LED display running parameters 1		Default	1F
	Setting Range	0000 ~ FFFF	Bit00: Operating frequency 1 (Hz) Bit01: Set frequency (Hz) Bit02: DC bus voltage (V) Bit03: output voltage (V) Bit04: Output current (A) Bit05: Output power (kW) Bit06: output torque (%) Bit07: Input terminal status Bit08: Output terminal status Bit09: FIV (expansion card) voltage (V) Bit10: FIC voltage (V) Bit11: Reserved Bit12: count value Bit13: length value Bit14: Display load speed Bit15: PID setting If a parameter needs to be displayed during the running, set the corresponding bit to 1, and set P7.03 to the hexadecimal equivalent of this binary number.	

P7.04	LED display running parameters 2		Default	0
	Setting Range	0000 ~ FFFF	Bit00: PID feedback Bit01: PLC stage Bit02: PULSE input pulse frequency (kHz) Bit03: Operating speed (rpm) Bit04: remaining running time Bit05: FIV (extension card) voltage before calibration (V) Bit06: Voltage before FIC correction (V) Bit07: Reserved Bit08: Motor speed Bit09: Current power-on time (Hour) Bit10: Current running time (Min) Bit11: PULSE input pulse frequency (Hz) Bit12: Communication set value Bit13: encoder feedback speed (Hz) Bit14: Display of main frequency X (Hz) Bit15: Display of auxiliary frequency Y (Hz) If a parameter needs to be displayed during the running, set the corresponding bit to 1, and set P7.04 to the hexadecimal equivalent of this binary number.	

Run the display parameters,used to set the parameters that can be viewed when the AC drive is in any running state. Available view 32 parameters, according to the binary number of P7.03,P7.04 to select display parameters state, display order start from P7.03 lower digit.

P7.05	LED display stop parameters		Default	33
	Setting Range	0000 ~ FFFF	Bit00: Set frequency (Hz) Bit01: DC bus voltage (V) Bit02: Input terminal status Bit03: Output terminal status Bit04: FIV (expansion card) voltage (V) Bit05: FIC voltage (V) Bit06: Reserved Bit07: count value Bit08: length value Bit09: PLC stage Bit10: Load speed Bit11: PID setting	

			Bit12: PULSE input pulse frequency (kHz) If a parameter needs to be displayed during the running, set the corresponding bit to 1, and set P7.05 to the hexadecimal equivalent of this binary number.
--	--	--	---

P7.06	Load speed display coefficient		Default	1.0000
	Setting range	0.0001 ~ 6.5000		

This parameter is used to adjust the relationship between the output frequency of the AC drive and the load speed. For details, see the description of P7.12.

P7.07	Heatsink temperature of inverter	0
	Setting Range	0.0℃ ~ 100.0℃

It is used to display the insulated gate bipolar transistor (IGBT) temperature of the inverter module, and the IGBT overheat protection value of the inverter module depends on the model.

P7.08	Rectifier module heatsink temperature	Default	0
	Setting Range	0.0℃ ~ 100.0℃	

It is used to display the temporary of rectifier module. Different module over temperature protection value is different.

P7.09	Accumulative running time	Default	0h
	Default	0h ~ 65535h	

It is used to display the accumulative running time of the AC drive. After the accumulative running time reaches the value set in P8.17, the terminal with the digital output function 12 outputs ON.

P7.10	Reserved		Default	
P7.11	Software version		Default	read-only
	Setting Range	Software version of control board		
P7.12	Number of decimal places for load speed display		Default	21
	Setting Range	Unit's digit	0	0 decimal place
			1	1 decimal place
			2	2 decimal places
			3	3 decimal places
		Ten's	1	1 decimal place

		digit	2	2 decimal place
--	--	-------	---	-----------------

Unit's digit

P7.12 is used to set the number of decimal places for load speed display. The following gives an example to explain how to calculate the load speed:

Assume that P7.06 (Load speed display coefficient) is 2.000 and P7.12 is 2 (2 decimal places). When the running frequency of the AC drive is 40.00 Hz, the load speed is $40.00 \times 2.000 = 80.00$ (display of 2 decimal places).

If the AC drive is in the stop state, the load speed is the speed corresponding to the set frequency, namely, "set load speed". If the set frequency is 50.00 Hz, the load speed in the stop state is $50.00 \times 2.000 = 100.00$ (display of 2 decimal places).

Ten's digit

D0.19/D0.29 are displayed with 1 decimal point respectively.

D0.19/D0.29 are displayed with 2 decimal point respectively.

P7.13	Accumulative power-on time	Default	0h
	Setting Range	0h~65535h	

It is used to display the accumulative power-on time of the AC drive since the delivery. If the time reaches the set power-on time (P8.17), the terminal with the digital output function 24 outputs ON.

P7.14	Accumulative power consumption	Default	-
	Setting Range	0~65535kWh	

It is used to display the accumulative power consumption of the AC drive until now.

Group P8: Auxiliary Functions

P8.00	JOG running frequency	Default	2.00Hz
	Setting Range	0.00Hz~maximum frequency	
P8.01	JOG acceleration time	Default	20.0s
	Setting Range	0.0s~6500.0s	
P8.02	JOG deceleration time	Default	20.0s
	Setting Range	0.0s~6500.0s	

These parameters are used to define the set frequency and acceleration/deceleration time of the AC drive when jogging. The startup mode is "Direct start" (P6.00 = 0) and the stop mode is "Decelerate to stop" (P6.10 = 0) during jogging.

P8.03	Acceleration time 2	Default	20.0s
-------	---------------------	---------	-------


	Setting Range	0. 0s～6500.0s	
P8.04	Deceleration time 2	Default	20.0s
	Setting Range	0. 0s～6500.0s	
P8.05	Acceleration time 3	Default	20.0s
	Setting Range	0. 0s～6500.0s	
P8.06	Deceleration time 3	Default	20.0s
	Setting Range	0. 0s～6500.0s	
P8.07	Acceleration time 4	Default	20.0s
	Setting Range	0. 0s～6500.0s	
P8.08	Deceleration time 4	Default	20.0s
	Setting Range	0. 0s～6500.0s	

The T200 provides a total of four groups of acceleration/deceleration time, that is, the preceding three groups and the group defined by P0.17 and P0.18. Definitions of four groups are completely the same. You can switch over between the four groups of acceleration/deceleration time through different state combinations of S terminals. For more details, see the descriptions of P4.00 to P4.07.

P8.09	Jump frequency 1	Default	0.00Hz
	Setting Range	0.00Hz～maximum frequency	
P8.10	Jump frequency 2	Default	0.00Hz
	Setting Range	0.00 Hz～maximum frequency	
P8.11	Frequency jump amplitude	Default	0.00Hz
	Setting Range	0.00～maximum frequency	

If the set frequency is within the frequency jump range, the actual running frequency is the jump frequency close to the set frequency. Setting the jump frequency helps to avoid the mechanical resonance point of the load. The T200 supports two jump frequencies. If both are set to 0, the frequency jump function is disabled. The principle of the jump frequencies and jump amplitude is shown in the following figure.


Figure 4-13 Principle of the jump frequencies and jump amplitude



P8.12	Forward/Reverse rotation dead-zone time	Default	0.0s
	Setting Range	0.00s~3000.0s	

It is used to set the time when the output is 0 Hz at transition of the AC drive forward rotation and reverse rotation, as shown in the following figure.

Figure 4-14 Forward/Reverse rotation dead-zone time



P8.13	Reverse control		Default	0
	Setting Range	0	permitted	
		1	prohibited	

It is used to set whether the AC drive allows reverse rotation. In the applications where reverse rotation is prohibited, set P8.13= 1.

P8.14	Running mode when set frequency lower than frequency lower limit		Default	0
	Setting Range	0	Run at frequency lower limit	
		1	Stop	
		2	Run at zero speed	

It is used to set the AC drive running mode when the set frequency is lower than the frequency lower limit. The T200 provides three running modes to satisfy requirements of various applications.

P8.15	Droop control		Default	0.00Hz
	Setting Range		0.00Hz ~ 10.00Hz	

This function is used for balancing the workload allocation when multiple motors are used to drive the same load. The output frequency of the AC drives decreases as the load increases. You can reduce the workload of the motor under load by decreasing the output frequency for this motor, implementing workload balancing between multiple motors.

P8.16	Accumulative power-on time threshold		Default	0h
	Setting Range		0h ~ 65000h	

If the accumulative power-on time (P7.13) reaches the value set in P8.16 , the corresponding YO terminal outputs ON(P5.01=24).

P8.17	Accumulative running time threshold		Default	0h
	Setting Range		0h ~ 65000h	

It is used to set the accumulative running time threshold of the AC drive. If the accumulative running time (P7.09) reaches the value set in this parameter, the corresponding YO terminal outputs ON(P5.04=40).


P8.18	Startup protection		Default	0
	Setting Range	0	No	
		1	Yes	

This parameter is used to set whether to enable the safety protection. If it is set to 1, the AC drive does not respond to the running command valid upon AC drive power-on (for example, an input terminal is ON before power-on). The AC drive responds only after the running command is canceled and becomes valid again. In addition, the AC drive does not respond to the running command valid upon fault reset of the AC drive. The run protection can be disabled only after the

running command is canceled.
 In this way, this parameter is set to 1, the motor can be protected from responding to run commands upon power-on or fault reset in unexpected conditions.

P8.19	Frequency detection value(FDT1)	Default	50.00Hz
	Setting Range	0.00Hz～maximum frequency	
P8.20	Frequency detection hysteresis (FDT1)	Default	5.0%
	Setting Range	0.0%～100.0% (FDT1 level)	

If the running frequency is higher than the value of frequency detection the corresponding YO terminal becomes ON. If the running frequency is lower than detection value , that the YO terminal outputs on is canceled. (P5.04=37)
 These two parameters are respectively used to set the detection value of output frequency and hysteresis value upon cancellation of the output. The value of P8.20 is a percentage of the hysteresis frequency to the frequency detection value (P8.19).The FDT function is shown in the following figure.
 Figure 4-15 FDT level




P8.21	Detection range of frequency reached	Default	0.0%
	Setting Range	0.00～100% (maximum frequency)	

If the AC drive’s running frequency is within the certain range of the set frequency, the corresponding YO terminal becomes ON.(P5.04=3)
 This parameter is used to set the range within which the output frequency is

detected to reach the set frequency. The value of this parameter is a percentage relative to the maximum frequency. The detection range of frequency reached is shown in the following figure.

Figure 4-16 Detection range of frequency reached




P8.22	Jump frequency during the process of acceleration/deceleration	Default	1
	Setting Range	0: Disabled 1: Enabled	

It is used to set whether the jump frequency is valid during the process of acceleration/deceleration.

When the jump frequency is valid during acceleration/deceleration, and the

running frequency is within the frequency jump range, the actual running frequency will jump over the set frequency jump amplitude (rise directly from the lowest jump frequency to the highest jump frequency). The following figure shows the diagram when the jump frequency is valid during acceleration/deceleration.


Figure 4-17 Diagram when the jump frequency is valid during the process of acceleration/deceleration



P8.25	Frequency switchover point between acceleration time 1 and acceleration time 2	Default	0.00Hz
	Setting Range	0.00Hz～maximum frequency	
P8.26	Frequency switchover point between deceleration time 1 and deceleration time 2	Default	0.00Hz
	Setting Range	0.00Hz～maximum frequency	

This function is valid when the motor selects acceleration/deceleration time that is not performed by means of X terminal’s switchover. It is used to select different groups of acceleration/deceleration time based on the running frequency range rather than X terminal during the running process of the AC drive.

Figure 4-17 Acceleration/deceleration time switchover



During the process of acceleration, if the running frequency is smaller than the value of P8.25, acceleration time 2 is selected. If the running frequency is larger than the value of P8.25, acceleration time 1 is selected.

During the process of deceleration, if the running frequency is larger than the value of P8.26, deceleration time 1 is selected. If the running frequency is smaller than the value of P8.26, deceleration time 2 is selected.

P8.27	Terminal JOG preferred	Default	0
	Setting Range	0: Disabled 1: Enabled	

It is used to set whether terminal JOG is the highest priority.

If terminal JOG is preferred, the AC drive switches to terminal JOG running state when there is a terminal JOG command during the running process of the AC drive.

P8.28	Frequency detection value (FDT2)	Default	50.00Hz
	Setting Range	0.00Hz~maximum frequency	
P8.29	Frequency detection hysteresis (FDT2)	Default	5.0%

	Setting Range	0.0%~100.0% (FDT2 level)
--	---------------	--------------------------


The frequency detection function is the same as FDT1 function. For details, refer to the descriptions of P8.19 and P8.20.

P8.30	Any frequency reaching detection value 1	Default	50.00Hz
	Setting Range	0.00 Hz ~ maximum frequency	
P8.31	Any frequency reaching detection amplitude 1	Default	0.0%
	Setting Range	0.0%~100.0% (maximum frequency)	
P8.32	Any frequency reaching detection value 2	Default	50.00Hz
	Setting Range	0.00Hz~maximum frequency	
P8.33	Any frequency reaching detection amplitude 2	Default	0.0%
	Setting Range	0.0%~100.0% (maximum frequency)	

If the output frequency of the AC drive is within the positive and negative amplitudes of the any frequency reaching detection value, the corresponding YO outputs ON(P5.04=26/27)

The T200 provides two groups of any frequency reaching detection parameters, including frequency detection value and detection amplitude, as shown in the following figure.


Figure 4-19 Any frequency reaching detection



P8.34	Zero current detection level		Default	5.0%
	Setting Range	0.0%~300.0% (rated motor current)		
P8.35	Zero current detection delay time		Default	0.10s
	Setting Range	0.00s~600.00s		

If the output current of the AC drive is equal to or less than the zero current detection level and the duration exceeds the zero current detection delay time, the corresponding YO becomes ON(P5.04=34). The zero current detection is shown in the following figure.

Figure 4-20 Zero current detection




P8.36	Output over-current threshold	Default	200.0%
	Setting Range	0.0% (no detection) 0.1%~300.0% (rated motor current)	
P8.37	Output over-current detection delay time	Default	0.00s
	Setting Range	0.00s~600.00s	

If the output current of the AC drive is equal to or higher than the over-current threshold and the duration exceeds the detection delay time, the corresponding YO becomes ON(P5.04=36). The output over-current detection function is shown

in the following figure.

Figure 4-21 Output over-current detection




P8.38	Any current reaching 1	Default	100.0%
	Setting Range	0.0%～300.0%（rated motor current）	
P8.39	Any current reaching 1 Amplitude	Default	0.0%
	Setting Range	0.0%～300.0%（rated motor current）	
P8.40	Any current reaching 2	Default	100.0%
	Setting Range	0.0%～300.0%（rated motor current）	
P8.41	Any current reaching 2 amplitude	Default	0.0%
	Setting Range	0.0%～300.0%（rated motor current）	

If the output current of the AC drive is within the positive and negative amplitudes of any current reaching detection value, the corresponding YO becomes ON.（P5.04=28/29）

The T200 provides two groups of any current reaching detection parameters, including current detection value and detection amplitudes, as shown in the following figure.

Figure 4-22 Any current reaching detection



P8.42	Timing function selection			Default	0
	Setting Range	0	Disabled		
		1	Enabled		
P8.43	Timing duration selection			Default	0
	Setting Range	0	P8.44		
		1	FIV(expansion card)		
		2	FIC		
		3	Reserved		
		100% of analog input corresponds to the value of P8.44			
P8.44	Timing duration			Default	0.0Min
	Setting Range	0.0Min～6500.0Min			

These parameters are used to implement the AC drive timing function.

If P8.42 is set to 1, the AC drive starts to time at startup. When the set timing duration is reached, the AC drive stops automatically and meanwhile the corresponding YO outputs ON.(P5.04=30)

The AC drive starts timing from 0 each time it starts up and the remaining timing duration can be queried by D0.20.The timing duration is set in P8.43 and P8.44, in the unit of minute.

P8.45	FIV input voltage lower limit		Default	3.10V
	Setting Range	0.00V~P8.46		

P8.46	FIV input voltage upper limit		Default	6.80V
	Setting Range	P8.45～11.00V		

These two parameters are used to set the limits of the input voltage to provide protection on the AC drive. When the FIV input is larger than the value of P8.46 or smaller than the value of P8.47, the corresponding YO becomes ON, indicating that whether FIV input exceeds the limit.(P5.04=31)

P8.47	Module temperature		Default	75℃
	Setting Range	0.~P8.46		

When the heat sink temperature of the AC drive reaches the value of this parameter, the corresponding YO becomes ON (P5.04=35)

p8.48	Cooling fan control		Default	0
	Setting Range	0: Fan working during running 1: Fan working continuously		

It is used to set the working mode of the cooling fan. If this parameter is set to 0, the fan works when the AC drive is in running state. When the AC drive stops, the cooling fan works if the heat sink temperature is higher than 40℃, and stops working if the heat sink temperature is lower than 40℃.

If this parameter is set to 1, the cooling fan keeps working after power-on.

P8.49	Wake up frequency		Default	0.00Hz
	Setting Range	Dormant frequency (P8.51) ~maximum frequency (P0.10)		
P8.50	Wake up delay time		Default	0.0s
	Setting Range	0.0s～6500.0s		
P8.51	Sleep frequency		Default	0.00Hz
	Setting Range	0.00Hz～wakeup frequency (P8.49)		
P8.52	Sleep delay time		Default	0.0s
	Setting Range	0.0s～6500.0s		

These parameters are used to implement the sleep and wake up functions in the water supply application.

When the AC drive is in running state, the AC drive enters the sleep state and stops automatically after the sleep delay time (P8.52) if the set frequency is lower than or equal to the sleep frequency (P8.51).

When the AC drive is in sleep state and the current running command is effective, the AC drive starts up after the wake up delay time (P8.50) if the set frequency is higher than or equal to the wake up frequency (P8.49).

Generally, set the wake up frequency equal to or higher than the sleep frequency. If the wake up frequency and sleep frequency are set to 0, the sleep and wake up functions are disabled.

When the sleep function is enabled, if the frequency source is PID, whether PID operation is performed in the sleep state is determined by PA.28. In this case, select PID operation enabled in the stop state (PA.28 = 1).

P8.53	Current running time reached	Default	0.0Min
	Setting Range	0.0Min~6500.0Min	

If the current running time reaches the value set in this parameter, the corresponding YO becomes ON, indicating that the current running time is reached.

P8.54	Output power correct coefficient	Default	100.0%
	Setting range	0.0~200.0%	

When output power(D0.05) is not the one needed, output the value to correct.

Group P9: Fault and Protection

P9.00	Motor overload protection selection		Default	1
	Setting Range	0	Disabled	
		1	Enabled	
P9.01	Motor overload protection gain		Default	1.00
	Setting Range		0.20～10.00	

P9.00 = 0

The motor overload protective function is disabled. The motor is exposed to potential damage due to overheating. A thermal relay is suggested to be installed between the AC drive and the motor.

P9.00 = 1

The AC drive judges whether the motor is overloaded according to the inverse time-lag curve of the motor overload protection.

The inverse time-lag curve of the motor overload protection is:

$195\% \times P9.01 \times \text{rated motor current}$ (if the load remains at this value for one minute, the AC drive reports motor overload fault), or $150\% \times P9.01 \times \text{rated motor}$

current (if the load remains at this value for 5x (P9.01), the AC drive reports motor overload fault).

Set P9.01 properly based on the actual overload capacity. If the value of P9.01 is set too large, the damage to the motor may result when the motor overheats but the AC drive does not report the alarm.

P9.02	Motor overload warning coefficient	Default	80%
	Setting Range	50%～100%	

This function is used to give a warning signal to the control system via YO before motor overload protection. This parameter is used to determine the percentage, at which pre-warning is performed before motor overload. The larger the value is, the less advanced the pre-warning will be.

When the accumulative output current of the AC drive is greater than the value of the overload inverse time-lag curve multiplied by P9.02, the multifunction digital YO terminal on the AC drive (Motor overload pre-warning) outputs ON.

P9.03	Over-voltage stall gain	Default	0
	Setting Range	0（no stall over-voltage）～100	
P9.04	Over-voltage stall protective voltage	Default	760.0V
	Setting Range	200.0V～2000.0V（Three phase）	

When the DC bus voltage exceeds the value of P9.04 (Over-voltage stall protective voltage) during deceleration of the AC drive, the AC drive stops deceleration and keeps the present running frequency. After the bus voltage declines, the AC drive continues to decelerate. P9.03 (Over-voltage stall gain) is used to adjust the over-voltage suppression capacity of the AC drive. The larger the value is, the greater the over-voltage suppression capacity will be. In the prerequisite of no over-voltage occurrence, set P9.03 to a small value. For small-inertia load, the value should be small. Otherwise, the system dynamic response will be slow. For large-inertia load, the value should be large. Otherwise, the suppression result will be poor and an over-voltage fault may occur. If the over-voltage stall gain is set to 0, the over-voltage stall function is disabled.

P9.07	Short-circuit to ground upon power-on		Default	1
	Setting Range	0	Disabled	
		1	Enabled	

It is used to determine whether to check the motor is short-circuited to ground at power-on of the AC drive. If this function is enabled, the AC drive's UVW will have voltage output a while after power-on.

P9.09	Fault auto reset times		Default	0
	Setting Range	0~20		

It is used to set the times of fault auto resets if this function is used. After the value is exceeded, the AC drive will remain in the fault state.

P9.10	MOA-MOB-MOC action during fault auto reset		Default	1
	Setting Range	0: No action 1: Action		

It is used to decide whether the MOA-MOB-MOC acts during the fault auto reset by set of P9.10

P9.11	Time interval of fault auto reset		Default	1.1s
	Setting Range	0.1s~100.0s		

It is used to set the waiting time from the alarm of the AC drive to fault auto reset.

P9.12	Input phase loss/contactors pull-in protection selection		Default	11
	Setting range	Unit's digit: Input phase loss protection selection Ten's digit: Contactor pull-in protection selection 0: Disabled 1: Enabled		

Select whether to protect contactor pull-in protection.

T200 inverter 11KW G machine and above power, only the input phase loss protection function, 11KW G machine below the power, no matter the P9.12 bit set to 0 or 1 there is no input phase loss protection function.

P9.13	Output phase loss protection selection		Default	1
	Setting Range	Unit's digit: Output phase loss protection selection Ten's digit: Output phase loss protection before running 0: Prohibited 1: Permitted		

It is used to determine whether to perform output phase loss protection.

P9.14	1st fault type	0~99
P9.15	2nd fault type	
P9.16	3rd (latest) fault type	

It is used to record the types of the recent three faults of the AC drive. 0 indicates no fault. For possible causes and solution of each fault, refer to Chapter

5.

P9.17	Frequency upon 3rd fault	It displays the frequency when the latest fault occurs.						
P9.18	Current upon 3rd fault	It displays the current when the latest fault occurs.						
P9.19	Bus voltage upon 3rd fault	It displays the bus voltage when the latest fault occurs.						
P9.20	Input terminal status upon 3rd fault	It displays the status of all input terminals when the latest fault occurs.The sequence is as follows:						
		Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
		X7	X6	X5	X4	X3	X2	X1
		If an input terminal is ON, the setting is 1, the OFF is 0, the setting is 0. The value is the equivalent decimal number converted from the X status.						
P9.21	Output terminal status upon 3rd fault	It displays the status of all output terminals when the latest fault occurs.The sequence is as follows:						
		Bit3	Bit2	Bit1		Bit0		
		YO	-	YA-YB-YC		MOA-MOB-MOC		
		If an output terminal is ON, the setting is 1,the OFF is 0,.If the output terminal is OFF, the setting is 0. All output status turn to decimal system .						
P9.22	AC drive status upon 3rd fault	Reserved						
P9.23	Power-on time upon 3rd fault	It displays the present power-on time when the latest fault occurs.						
P9.24	Running time upon 3rd fault	It displays the present running time when the latest fault occurs.						
P9.27	Frequency upon 2nd fault							
P9.28	Current upon 2nd fault							
P9.29	Bus voltage upon 2nd fault							
P9.30	Input terminal status upon 2nd fault							
P9.31	Output terminal status upon 2nd fault							

P9.32	AC drive status upon 2nd fault	The same as P9.17～P9.24	
P9.33	power-on time upon 2nd fault		
P9.34	Running time upon 2nd fault		
P9.37	Frequency upon 1st fault		
P9.38	Current upon 1st fault		
P9.39	Bus voltage upon 1st fault		
P9.40	input terminal status upon 1st fault		
P9.41	output terminal status upon 1st fault		
P9.42	AC drive status 1st fault		
P9.43	power-on time upon 1st fault		
P9.44	Running time upon 1st fault		
P9.47	Fault protection action selection 1		Default 00000
	Setting Range	Unit's digit	Motor overload (OL1)
		0	Coast to stop
		1	Stop according to the stop mode
		2	Continue to run
		Ten's digit	Reserved
		Hundred's digit	Power output phase loss (LO) (the same as unit's digit)
		Thousand's digit	External equipment fault (EF) (the same as unit's digit)
		Ten thousand's digit	Communication fault (CE) (the same as unit's digit)
P9.48	Fault protection action selection 2		Default 00000
	Setting Range	Unit's digit	Encoder fault (PG)
		0	Coast to stop
		1	Switch over to V/F control, stop according to the stop mode
		2	Switch over to V/F control, continue to run
		Ten's digit	function code read-write abnormal (EEP)
		0	Coast to stop

		1	Stop according to the stop mode	
		Hundred's digit	Reserved	
		Thousand's digit	Reserved	
		Ten thousand's digit	Accumulative running time reached （END1）（the same as unit's digit in P9.47）	
P9.49	Fault protection action selection 3		Default	00000
	Setting Range	Unit's digit	Reserved	
		Ten's digit	Reserved	
		Hundred's digit	Accumulative power-on time reached （END2）（the same as unit's digit in P9.47）	
		Thousand's digit	Load becoming 0（LOAD）	
		0	Coast to stop	
		1	Stop according to the stop mode	
		2	Continue to run at 7% of rated motor frequency and resume to the set frequency if the load recovers	
		Ten thousand's digit	PID feedback lost during running（PIDE） （the same as unit's digit in P9.47）	

P9.50	Fault protection action selection 4		Default	00000
	Setting range	Unit's digit	Speed deviation too large (ESP) (Same as P9.47 unit's digit)	
		Ten's digit	Motor over speed (OSP) (Same as P9.47 unit's digit)	
		Hundred's digit	Initial position error (INI) (Same as P9.47 unit's digit)	
		Thousand's digit	Reserved	
		Ten thousand's digit	Reserved	

If "Coast to stop" is selected, the AC drive displays error code and directly stops.
If "Stop according to the stop mode" is selected, the AC drive displays alarm code and stops according to the stop mode. After stopping, the AC drive displays error code.

If "Continue to run" is selected, the AC drive continues to run and displays alarm code . The running frequency is set in P9.54.

P9.54	Frequency selection for continuing to run		Default	0
	Setting Range	0	Current running frequency	
		1	Set frequency	
		2	Frequency upper limit	
		3	Frequency lower limit	
P9.55	Backup frequency upon abnormality		Default	100.0%
	Setting Range	0.0%～100.0%		

If a fault occurs during the running of the AC drive and the handling of fault is set to "Continue to run", the AC drive displays alarm code and continues to run at the frequency set in P9.54.

The setting of P9.55 is a percentage relative to the maximum frequency.

P9.59	Action selection at instantaneous power failure		Default	0
	Setting Range	0	Invalid	
		1	Decelerate	
P9.60	Action pause judging voltage at instantaneous power failure		Default	85.0%
	Setting Range	P9.62～100.0%		
P9.61	Voltage rally judging time at instantaneous power failure		Default	0.50s
	Setting Range	0.00s～100.00s		
P9.62	Action judging voltage at instantaneous power failure		Default	80.0%
	Setting Range	60.0%～100.0% (standard bus voltage)		


Upon instantaneous power failure or sudden voltage dip, the DC bus voltage of the AC drive reduces. This function enables the AC drive to compensate the DC bus voltage reduction with the load feedback energy by reducing the output frequency so as to keep the AC drive running continuously.

If P9.59 = 1, upon instantaneous power failure or sudden voltage dip, the AC drive decelerates. Once the bus voltage resumes to normal, the AC drive accelerates to the set frequency. If the bus voltage remains normal for the time exceeding the value set in P9.61, it is considered that the bus voltage resumes to

normal.

If $P9.59 = 2$, upon instantaneous power failure or sudden voltage dip, the AC drive decelerates to stop.

Figure 4-23 AC drive action diagram upon instantaneous power failure



P9.63	Protection upon load becoming 0		Default	0
	Setting Range	0	Disabled	
		1	Enabled	

P9.64	Detection level of load becoming 0	Default	10.0%
	Setting Range	0.0%~100.0% (rated motor current)	
P9.65	Detection time of load becoming 0	Default	1.0s
	Setting Range	0.0s~60.0s	

If protection upon load becoming 0 is enabled, when the output current of the AC drive is lower than the detection level (P9.64) and the lasting time exceeds the detection time (P9.65), the output frequency of the AC drive automatically declines to 7% of the rated frequency. During the protection, the AC drive automatically accelerates to the set frequency if the load resumes to be normal.

P9.67	Over speed detection value	Default	15.0%
	Setting range	0.0%~50.0% (maximum frequency)	
P9.68	Over speed detection time	Default	1.0s
	Setting range	0.0s~60.0s	

This function is only valid in CLVC control. When AC drive detect the motor actual speed is over the set frequency by P9.67, and lasting time exceed P9.68, it will report OSP, and action as the protection mode.

P9.69	Detection value of too large speed deviation	Default	20.0%
	Setting range	0.0%~50.0% (maximum frequency)	
P9.70	Deviation time of too large speed deviation	Default	5.0s
	Setting range	0.0s~60.0s	

This function only valid in CLVC control. If the AC drive detects the deviation between the actual motor rotational speed detected by the AC drive and the set frequency is greater than the value of P9.69 and the lasting time exceeds the value of P9.70, the AC drive reports ESP and according to the selected fault protection action. If P9.70 is 0.0s, the function is disabled.

Group PA: Process Control PID Function

PID control is a general process control method. By performing proportional, integral and differential operations on the difference between the feedback signal and the target signal, it adjusts the output frequency and constitutes a feedback system to stabilize the controlled counter around the target value.

It is applied to process control such as flow control, pressure control and temperature control. The following figure shows the principle block diagram of PID control.




Figure 4-23 Principle block diagram of PID control

PA.00	PID setting source		Default	0
	Setting Range	0	PA.01	
		1	FIV（expansion card）	
		2	FIC	
		3	Reserved	
		4	PULSE setting（X5）	
		5	Communication setting	
		6	Multi-reference	
PA.01	PID digital setting		Default	50.0%
	Setting Range		0.0%～100.0%	

PA.00 is used to select the channel of target process PID setting. The PID setting is a relative value and ranges from 0.0% to 100.0%. The PID feedback is also a relative value. The purpose of PID control is to make the PID setting and PID feedback the same.

PA.02	PID feedback source			Default	0
	Setting Range	0	FIV (expansion card)		
		1	FIC		
		2	Reserved		
		3	FIV(expansion card)－FIC		
		4	PULSE setting		
		5	Communication setting		
		6	FIV(expansion card)+FIC		
		7	MAX（ FIV(expansion card) , FIC ）		
		8	MIN（ FIV(expansion card) , FIC ）		

This parameter is used to select the feedback signal channel of process PID. The PID feedback is a relative value and ranges from 0.0% to 100.0%.

PA.03	PID action direction		Default	0
	Setting	0	Forward action	
	Range	1	Reverse action	

0: Forward action

When the feedback value is smaller than the PID setting, the AC drive's output frequency rises. For example, the winding tension control requires forward PID action.

1: Reverse action

When the feedback value is smaller than the PID setting, the AC drive's output frequency reduces. For example, the unwinding tension control requires reverse PID action. Note that this function is influenced by reversing the multifunction terminal PID action. Pay attention in the application.

PA.04	PID setting feedback range	Default	1000
	Setting Range	0~65535	

This parameter is a non-dimensional unit. It is used for PID setting display (D0.15) and PID feedback display (D0.16).

Relative value 100% of PID setting feedback corresponds to the value of PA.04. If PA.04 is set to 2000 and PID setting is 100.0%, the PID setting display (D0.15) is 2000.

PA.05	Proportional gain Kp1	Default	20.0
	Setting Range	0.0~100.0	
PA.06	Integral time Ti1	Default	2.00s
	Setting Range	0.01s~10.00s	
PA.07	Differential time Td1	Default	0.000s
	Setting Range	0.00~10.000	

PA.05 (Proportional gain Kp1)

It decides the regulating intensity of the PID regulator. The higher the Kp1 is, the larger the regulating intensity is. The value 100.0 indicates when the deviation between PID feedback and PID setting is 100.0%, the adjustment amplitude of the PID regulator on the output frequency reference is the maximum frequency.

PA.06 (Integral time Ti1)

It decides the integral regulating intensity. The shorter the integral time is, the larger the regulating intensity is. When the deviation between PID feedback and PID setting is 100.0%, the integral regulator performs continuous adjustment for the time set in PA.06. Then the adjustment amplitude reaches the maximum frequency.

PA.07 (Differential time Td1)

It decides the regulating intensity of the PID regulator on the deviation change.

The longer the differential time is, the larger the regulating intensity is. Differential time is the time within which the feedback value change reaches 100.0%, and then the adjustment amplitude reaches the maximum frequency.

PA.08	Cut-off frequency of PID reverse rotation	Default	0.00Hz
	Setting Range	0. 00～maximum frequency	

In some situations, only when the PID output frequency is a negative value (AC drive reverse rotation), PID setting and PID feedback can be equal. However, too high reverse rotation frequency is prohibited in some applications, and PA.08 is used to determine the reverse rotation frequency upper limit.

PA.09	PID deviation limit	Default	0.01%
	Setting Range	0. 0%～100.0%	

If the deviation between PID feedback and PID setting is smaller than the value of PA.09, PID control stops. The small deviation between PID feedback and PID setting will make the output frequency stable and unchanging, especially effective for some closed-loop control applications.

PA.10	PID differential limit	Default	0.10%
	Setting Range	0. 00%～100.00%	

It is used to set the PID differential output range. In PID control, the differential operation may easily cause system oscillation. Thus, the PID differential regulation is restricted to a small range. PA.10 is used to set the range of PID differential output.

PA.11	PID setting changing time	Default	0.00s
	Setting Range	0.00s～650.00s	

The PID setting changing time indicates the time required for PID setting changing from 0.0% to 100.0%. The PID setting changes linearly according to the changing time, reducing the impact caused by sudden setting change on the system.

PA.12	PID feedback filter time	Default	0.00s
	Setting Range	0.00s～60.00s	
PA.13	PID output filter time	Default	0.00s
	Setting Range	0.00s～60.00s	

PA.12 is used to filter the PID feedback, helping to reduce interference on the feedback but slowing down the response of the process closed-loop system. PA.13 is used to filter the PID output frequency, helping to weaken sudden change of the AC drive output frequency but slowing down the response of the process closed-loop system.

PA.15	Proportional gain Kp2	Default	20.0
	Setting Range	0.0～100.0	

PA.16	Integral time Ti2		Default	2.00s
	Setting Range		0.01s~10.00s	
PA.17	Differential time Td2		Default	0.000s
	Setting Range		0.00~10.000	
PA.18	PID parameter switchover condition		Default	0
	Setting Range	0	No switchover	
		1	Switchover via S	
		2	Automatic switchover based on deviation	
PA.19	PID parameter switchover deviation 1		Default	20.0%
	Setting Range		0.0%~PA.20	
PA.20	PID parameter switchover deviation 2		Default	80.0%
	Setting Range		PA.19~100.0%	

In some applications, PID parameters switchover is required when one group of PID parameters cannot satisfy the requirement of the whole running process. These parameters are used for switchover between two groups of PID parameters.

Regulator parameters PA.15 to PA.17 are set in the similar way as PA.05 to PA.07. The switchover can be implemented either via S terminal or automatically implemented based on the deviation.

If you select switchover via X terminal, the X must be allocated with function 43 "PID parameter switchover". If the X is OFF, group 1 (PA.05 to PA.07) is selected. If the X is ON, group 2 (PA.15 to PA.17) is selected.

If you select automatic switchover, when the absolute value of the deviation between PID feedback and PID setting is smaller than the value of PA.19, PID parameter selects group 1. When the absolute value of the deviation between PID feedback and PID setting is higher than the value of PA.20, PID parameter selects group 2. When the deviation is between PA.19 and PA.20, the PID parameters are the linear interpolated value of the two groups of parameter values.





Figure 4-25 PID parameters switchover

PA.21	PID initial value	Default	0.0%
	Setting Range	0.0%~100.0%	
PA.22	PID initial value holding time	Default	0.00s
	Setting Range	0.00s~650.00s	

When the AC drive starts up, the PID starts closed-loop algorithm only after the PID output is fixed to the PID initial value (PA.21) and lasts the time set in PA.22.

Figure 4-26 PID initial value function



PA.23	Maximum deviation between two PID outputs in forward direction	Default	1.00%
-------	--	---------	-------

	Setting Range	0.00%～100.00%		
PA.24	Maximum deviation between two PID outputs in reverse direction	Default	1.00%	
	Setting Range	0.00%～100.00%		

This function is used to limit the deviation between two PID outputs (2 ms per PID output) to suppress the rapid change of PID output and stabilize the running of the AC drive.

PA.23 and PA.24 respectively correspond to the maximum absolute value of the output deviation in forward direction and in reverse direction.

PA.25	PID integral property		Default	00
	Setting Range	Unit's digit	Integral separated	
		0	Invalid	
		1	Valid	
		Ten's digit	Whether to stop integral operation when the	
		0	Continue integral operation	
		1	Stop integral operation	

Integral separated

If set the integral separated valid , the PID integral operation stops when the X allocated with function 22 "PID integral pause" is effective .In this case, only proportional and differential operations take effect.

If it is set invalid, the integral separated remains invalid no matter whether the X allocated with function "PID integral pause" is ON or not.

Whether to stop integral operation when the output reaches the limit.

If "Stop integral operation" is selected, the PID integral operation stops, which may help to reduce the PID overshoot.

PA.26	Detection value of PID feedback loss	Default	0.0%
	Setting Range	0.0%: Not judging feedback loss 0.1%～100.0%	
PA.27	Detection time of PID feedback loss	Default	1.0s
	Setting Range	0.0s～20.0s	

These parameters are used to judge whether PID feedback is lost.

If the PID feedback is smaller than the value of PA.26 and the continuous time exceeds the value of PA.27, the AC drive reports PIDE and acts according to the selected fault protection action.

PA.28	PID operation at stop		Default	0
	Setting Range	0	No PID operation at stop	
		1	PID operation at stop	

It is used to select whether to continue PID operation in the state of stop.
Generally, the PID operation stops when the AC drive stops.

Group PC: Multi-Reference and Simple PLC Function

The T200 multi-reference has more rich functions than multi-speed. Besides multi-speed, it can be used as the setting source of the V/F separated voltage source and setting source of process PID. In addition, the multi-reference is relative value.

The simple PLC function is different from the T200 user programmable function. Simple PLC can only complete simple combination of multi-reference, while the user programmable function is richer and more practical. For details, see the descriptions of group PC.

PC.00	multi-reference 0	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.01	multi-reference 1	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.02	multi-reference 2	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.03	multi-reference 3	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.04	multi-reference 4	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.05	multi-reference 5	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.06	multi-reference 6	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.07	multi-reference 7	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.08	multi-reference 8	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.09	multi-reference 9	Default	0.0%
	Setting Range	-100.0%~100.0%	
PC.10	multi-reference 10	Default	0.0Hz
	Setting Range	-100.0%~100.0%	

PC.11	multi-reference 11	Default	0.0%
	Setting Range	-100.0%～100.0%	
PC.12	multi-reference 12	Default	0.0%
	Setting Range	-100.0%～100.0%	
PC.13	multi-reference 13	Default	0.0%
	Setting Range	-100.0%～100.0%	
PC.14	multi-reference 14	Default	0.0%
	Setting Range	-100.0%～100.0%	
PC.15	multi-reference 15	Default	0.0%
	Setting Range	-100.0%～100.0%	

Multi-reference can be used in three occasions : as the source of frequency, V/F separated voltage source and the setting source of process PID. The multi-reference is relative value and ranges from -100.0% to 100.0%.

As frequency source, it is a percentage relative to the maximum frequency. As V/F separated voltage source, it is a percentage relative to the rated motor voltage.

As process PID setting source, it does not require conversion.

Multi-reference can be switched over based on different states of multifunction digital S terminal. For details, see the descriptions of group P4.

PC.16	Simple PLC running mode		Default	0
	Setting	0	Stop after the AC drive runs one cycle	
	Range	1	Keep final values after the AC drive runs one cycle	
		2	Repeat after the AC drive runs one cycle	

Simple PLC function has two effects: the frequency source or V/F separated voltage source.

When simple PLC is used as the frequency source, whether parameter values of PC. 00 to PC. 15 are positive or negative determines the running direction. If the parameter values are negative, it indicates that the AC drive runs in reverse direction.




Figure 4-29 Simple PLC when used as frequency source

As the frequency source, PLC has three running modes, as V/F separated voltage source, it doesn't have the three modes. Among them,

0: Stop after the AC drive runs one cycle

The AC drive stops after running one cycle, and will not start up until receiving another command.

1: Keep final values after the AC drive runs one cycle. The AC drive keeps the final running frequency and direction after running one cycle.

2: Repeat after the AC drive runs one cycle

The AC drive automatically starts another cycle after running one cycle, and will not stop until receiving the stopping command.

PC.17	Simple PLC retentive selection		Default	00
	Setting Range	Unit's digit	Retentive upon power failure	
		0	No	
		1	Yes	

		Ten's digit	Retentive upon stop
		0	No
		1	Yes

PLC retentive upon power failure indicates that the AC drive memorizes the PLC running moment and running frequency before power failure and will continue to run from the memorized moment after it is powered on again. If the unit's digit is set to 0, the AC drive restarts the PLC process after it is powered on again.

PLC retentive upon stopping indicates that the AC drive records the PLC running moment and running frequency upon stopping and will continue to run from the recorded moment after it starts up again. If the ten's digit is set to 0, the AC drive restarts the PLC process after it starts up again.

PC.18	Running time of simple PLC reference 0	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.19	Acceleration/deceleration time of simple PLC reference 0	Default	0
	Setting Range	0~3	
PC.20	Running time of simple PLC reference 1	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.21	Acceleration/deceleration time of simple PLC reference 1	Default	0
	Setting Range	0~3	
PC.22	Running time of simple PLC reference 2	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.23	Acceleration/deceleration time of simple PLC reference 2	Default	0

	Setting Range	0~3	
PC.24	Running time of simple PLC reference 3	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.25	Acceleration/deceleration time of simple PLC reference 3	Default	0
	Setting Range	0~3	
PC.26	Running time of simple PLC reference 4	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.27	Acceleration/deceleration time of simple PLC reference 4	Default	0
	Setting Range	0~3	
PC.28	Running time of simple PLC reference 5	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.29	Acceleration/deceleration time of simple PLC reference 5	Default	0
	Setting Range	0~3	
PC.30	Running time of simple PLC reference 6	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.31	Acceleration/deceleration time of simple PLC reference 6	Default	0
	Setting Range	0~3	
PC.32	Running time of simple PLC reference 7	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	

PC.33	Acceleration/deceleration time of simple PLC reference 7	Default	0
	Setting Range	0~3	
PC.34	Running time of simple PLC reference 8	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.35	Acceleration/deceleration time of simple PLC reference 8	Default	0
	Setting Range	0~3	
PC.36	Running time of simple PLC reference 9	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.37	Acceleration/deceleration time of simple PLC reference 9	Default	0
	Setting Range	0~3	
PC.38	Running time of simple PLC reference 10	Default	0.0s (h)
	Setting Range	0.0 s (h) ~ 6553.5s (h)	
PC.39	Acceleration/deceleration time of simple PLC reference 10	Default	0
	Setting Range	0~3	
PC.40	Running time of simple PLC reference 11	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	
PC.41	Acceleration/deceleration time of simple PLC reference 11	Default	0
	Setting Range	0~3	
PC.42	Running time of simple PLC reference 12	Default	0.0s (h)
	Setting Range	0.0s (h) ~ 6553.5s (h)	

PC.43	Acceleration/deceleration time of simple PLC reference 12		Default	0
	Setting Range		0~3	
PC.44	Running time of simple PLC reference 13		Default	0.0s (h)
	Setting Range		0.0s (h) ~ 6553.5s (h)	
PC.45	Acceleration/deceleration time of simple PLC reference 13		Default	0
	Setting Range		0~3	
PC.46	Running time of simple PLC reference 14		Default	0.0s (h)
	Setting Range		0.0s (h) ~ 6553.5s (h)	
PC.47	Acceleration/deceleration time of simple PLC		Default	0
	Setting Range		0~3	
PC.48	Running time of simple PLC reference 15		Default	0.0s (h)
	Setting Range		0.0s (h) ~ 6553.5s (h)	
PC.49	Acceleration/deceleration time of simple PLC		Default	0
	Setting Range		0~3	
PC.50	Time unit of simple PLC		Default	0
	Setting	0	S (second)	
		1	h (hour)	
PC.51	Reference 0 source		Default	0
	Setting Range	0	Set by PC.00	
		1	FIV (expansion card)	
		2	FIC	
		3	Reserved	
		4	PULSE setting	
		5	PID	
		6	Set by preset frequency (P0.08), modified via terminal UP/DOWN	

It determines the setting channel of reference 0. You can perform convenient switchover between the setting channels. When multi-reference or simple PLC is used as frequency source, the switchover between two frequency sources can be realized easily.

Group PD: Communication Parameters

Please refer to the "T200 communication protocol"

Group PP: User-Defined Function Codes

PP.00	User password	Default	0
	Setting Range	0~65535	

If it is set to any non-zero number, the password protection function is enabled. After a password has been set and taken effect, you must input the correct password in order to enter the menu. If the password is incorrect you cannot view or modify parameters. If PP.00 is set to 00000, the previously set user password is cleared, and the password protection function is disabled.

PP.01	Restore default settings		Default	0
	Setting Range	0	No operation	
		1	Restore factory settings except motor parameters	

1: Restore default settings except motor parameters

If PP.01 is set to 1, most function codes are restored to the default settings except motor parameters, frequency reference decimal point(P0.22, fault records, accumulative running time (P7.09), accumulative power-on time (P7.13) and accumulative power consumption (P7.14).

Group C0: Torque Control and Restricting Parameters

C0.00	Speed/Torque control		Default	0
	Setting	0	Speed control	
		1	Torque control	

It is used to select the AC drive's control mode: speed control or torque control. The T200 provides multi-function terminals with two torque related functions, Torque control prohibited (function 29)and Speed control/Torque control switchover(function 46).The two terminals need to be used together with C0.00 to implement speed control/torque control switchover.

If the terminal allocated with function 46 (Speed control/Torque control switchover) is OFF, the control mode is determined by C0.00. If the S terminal allocated with function 46 is ON, the control mode is to reverse the value of C0.00. However, if the torque control prohibited terminal is ON, the AC drive is fixed to run in the speed control mode.

	Torque setting source in torque control		Default	0
		0	Digital setting (C0.03)	

C0.01	Setting Range	1	FIV（expansion card）		
		2	FIC		
		3	Reserved		
		4	PULSE setting		
		5	Communication setting		
		6	MIN（FIV（expansion card）,FIC）		
		7	MAX（FIV（expansion card）,FIC）		
C0.03	Torque digital setting in torque control		Default	150%	
	Setting Range	-200.0%～200.0%			

C0.01 is used to set the torque setting source. There are a total of eight torque setting sources. The torque setting is a relative value. 100.0% corresponds to the AC drive's rated torque. The setting range is -200.0% to 200.0%, indicating the AC drive's maximum torque is twice of the AC drive's rated torque. When the torque setting using 1 ~ 7, communication, analog input and pulse input. The data format is -100.00% to 100.00%. 100% corresponds to the value of C0.03.

C0.05	Forward maximum frequency in torque control	Default	50.00Hz
	Setting Range	0.00Hz~maximum frequency	
C0.06	Reverse maximum frequency in torque control	Default	50.00Hz
	Setting Range	0.00Hz~maximum frequency(P0.10)	

This two parameters are used to set the maximum frequency in forward or reverse rotation in torque control mode.

In torque control, if the load torque is smaller than the motor output torque, the motor's rotational speed will rise continuously. To avoid runaway of the mechanical system, the motor maximum rotating speed must be limited in torque control.

You can implement continuous change of the maximum frequency in torque control dynamically by controlling the frequency upper limit.

C0.07	Acceleration time in torque control	Default	0.00s
	Setting Range	0.00s~6500.0s	

C0.08	Deceleration time in torque control	Default	0.00s
	Setting Range	0.00s～6500.0s	

In torque control, the difference between the motor output torque and the load torque determines the speed change rate of the motor and load. The motor rotational speed may change quickly and this will result in noise or too large mechanical stress. The setting of acceleration/deceleration time in torque control makes the motor rotational speed change smoothly.

However, in applications requiring rapid torque response, set the acceleration/deceleration time in torque control to 0.00s. For example, two AC drives are connected to drive the same load. To balance the load allocation, set one AC drive as master in speed control and the other as slave in torque control. The slave receives the master's output torque as the torque command and must follow the master rapidly. In this case, the acceleration/deceleration time of the slave in torque control is set to 0.00s.

Group C5: Control Optimization Parameters

C5.00	PWM switchover frequency upper limit	Default	8.00Hz
	Setting Range	0.00Hz～15.00Hz	

This parameter is valid only for V/F control.

It is used to determine the wave modulation mode in V/F control of asynchronous motor.

If the frequency is lower than the value of this parameter, the waveform is 7-segment continuous modulation. If the frequency is higher than the value of this parameter, the waveform is 5-segment intermittent modulation.

The 7-segment continuous modulation causes more loss to switches of the AC drive but smaller current ripple. The 5-segment intermittent modulation causes less loss to switches of the AC drive but larger current ripple. This may lead to motor running instability at high frequency. Do not modify this parameter generally.

C5.01	PWM modulation	Default	0
	Setting Range	0	Asynchronous modulation
		1	Synchronous modulation

Only V/F control is effective. asynchronous modulation is used when the output frequency is high(over 100HZ),conductive to the quality of the output voltage

C5.02	Dead compensation way	Default	1
	Setting Range	0	No compensation
		1	compensation mode 1

		2	compensation mode 2
--	--	---	---------------------

It doesn't have to modify generally.

C5.03	Random PWM depth	Default		0
	Setting Range	0	Random PWM is invalid	
		1-10	PWM carrier frequency random depth	

Random PWM depth is set to improve the motor's noise,reduce electromagnetic interference

C5.04	Fast current limiting open	Default		1
	Setting Range	0	Not open	
		1	Open	

Opening fast current limiting can reduce over current fault,make the inverter work normally. Opening fast current limiting for a long time ,can make the inverter overheat,Report a fault CBC.CBC represents fast current limiting fault and need to stop.

C5.05	Current detection compensation	Default	105
	Setting Range	100-110	

Used to set current detection compensation, don't recommend to modify

C5.06	Undervoltage setting	Default	机型确定
	Setting Range	200.0V-2000.0V	

Used to set the voltage of inverter's lack voltage fault LU,Different voltage levels of inverter's 100%,corresponding to different voltages, Respectively single-phase 220V or three-phase 220V: three-phase 380V:350;three-phase 690V:650V

C5.07	SFVC optimization mode selection		Default	1
	Setting Range	0	No optimization	
		1	Optimization mode 1	
		2	Optimization mode 2	

1: Optimization mode 1

It is used when the requirement on torque control linearity is high.

2: Optimization mode 2

It is used for the requirement on speed stability is high.

C5.08	Dead time adjustment	Default	150%
	Setting range	100%~200%	

Adjusting the value to improve the effective voltage usage. Adjust the value too small will lead to unstable system operation. User modification is not recommended.

C5.09	Over voltage point setting	Default	Model dependent
	Setting range	200.0V~2200.0V	

It is used to set the voltage value for over voltage fault of the AC drive. The factory values for different voltage levels are:

Single-phase 220V or three-phase 220V: 400V Three-phase 380V: 810V.

Group D0: Monitoring Parameters

Group D0 is used to monitor the AC drive's running state. You can view the parameter values by using operation panel, convenient for on-site commissioning, or from the host computer by means of communication . D0.00 to D0.31 are the monitoring parameters in the running and stopping state defined by P7.03 and P7.04.

For more details, see Table as follow.

Function Code	Parameter Name	Unit
D0.00	Running frequency (Hz)	0.01Hz
D0.01	Set frequency (Hz)	0.01Hz
D0.02	Bus voltage (V)	0.1V
D0.03	Output voltage (V)	1V
D0.04	Output current (A)	0.01A
D0.05	Output power (kW)	0.1kW
D0.06	Output torque (%)	0.1%
D0.07	Input terminal state	1
D0.08	Output terminal state	1
D0.09	FIV voltage (V)	0.01V
D0.10	FIC voltage (V)	0.01V
D0.11	Reserved	
D0.12	Count value	1
D0.13	Length value	1
D0.14	Load speed display	1
D0.15	PID setting	1
D0.16	PID feedback	1
D0.17	PLC stage	1
D0.18	Input pulse frequency(kHz)	0.01kHz
D0.19	Motor speed	1rpm

D0.20	Remaining running time	0.1Min
D0.21	FIV(Expansion card) voltage before correction	0.001V
D0.22	FIC voltage before correction	0.001V
D0.24	Linear speed	1m/Min
D0.25	The current power-on time	1Min
D0.26	The current running time	0.1Min
D0.27	Pulse input frequency	1Hz
D0.28	Communication setting value	0.01%
D0.31	Auxiliary frequency Y	0.01Hz
D0.32	View any memory address values	1
D0.34	Motor temperature value	1℃
D0.35	Target torque(%)	0.1%
D0.36	Resolver position	1
D0.37	Power factor angle	0.1°
D0.38	ABZ position	1
D0.39	Target voltage upon V/F separation	1V
D0.40	Output voltage upon V/F	1V
D0.45	Fault information	0
D0.58	Z signal counter	1
D0.59	Set frequency (%)	0.01%
D0.60	Run frequency (%)	0.01%
D0.61	AC drive state	1
D0.74	AC drive output torque	0.1

Chapter 5 Fault checking and ruled out

5-1 Fault alarm and countermeasures

T200 inverter with kinds of warning information and the protection function, once the failure, protection function action, inverter will stop output, and fault relay contact action, and display the fault code shown on the panel. The user can check according to the tips before seeking service, analyze the cause of the problem, find out the solution. If it is belong to the dotted line frame stated reason, please seek service ,with your purchased inverter agents or direct contact with our company.

Warning information OUOC is over current or over voltage signals for hardware, in most cases the hardware over voltage fault cause OUOC alarm.

Fault Name	Display of Panel	Possible Causes	Solutions
Inverter unit protection	OC	1: The output circuit short circuited. 2: The connecting cable of the motor is too long. 3: The module overheats. 4: The internal connections become loose. 5:The main control board is faulty. 6: The drive board is faulty. 7: The inverter module is faulty	1:Eliminate external faults. 2: Install a reactor or an output filter. 3:Check the air filter and the cooling fan. 4:Connect all cables properly. 5:Looking for technical support 6:Looking for technical support 7:Looking for technical support

Over-current during acceleration	OC1	<p>1: The output circuit is grounded or short circuited.</p> <p>2: Control mode is vector control, Motor auto-tuning is not performed.</p> <p>3: The acceleration time is too short.</p> <p>4: Manual torque boost or V/F curve is not appropriate.</p> <p>5: The voltage is too low.</p> <p>6: The startup operation is performed on the rotating motor.</p> <p>7: A sudden load is added during acceleration.</p> <p>8: The AC drive model is of too small power class.</p>	<p>1: Eliminate external faults.</p> <p>2: Perform the motor auto-tuning .</p> <p>3: Increase the acceleration time.</p> <p>4: Adjust the manual torque boost or V/F curve.</p> <p>5: Adjust the voltage to normal range.</p> <p>6: Select rotational speed tracking restart or start the motor after it stops.</p> <p>7: Remove the added load.</p> <p>8: Select an AC drive of higher power class.</p>
Over-current during acceleration	OC2	<p>1: The output circuit is grounded or short circuited.</p> <p>2: Motor auto-tuning is not performed.</p> <p>3: The deceleration time is too short.</p> <p>4: The voltage is too low.</p> <p>5: A sudden load is added during deceleration.</p> <p>6: The braking unit and braking resistor are not installed.</p>	<p>1: Eliminate external faults.</p> <p>2: Perform the motor auto- tuning.</p> <p>3: Increase the deceleration time.</p> <p>4: Adjust the voltage to normal range.</p> <p>5: Remove the added load.</p> <p>6: Install the braking unit and braking resistor.</p>

Over-current at constant speed	OC3	<p>1: The output circuit is grounded or short circuited.</p> <p>2: Motor auto-tuning is not performed.</p> <p>3: The voltage is too low.</p> <p>4: A sudden load is added during operation.</p> <p>5: The AC drive model is of too small power class.</p>	<p>1: Eliminate external faults.</p> <p>2: Perform the motor auto-tuning.</p> <p>3: Adjust the voltage to normal range.</p> <p>4: Remove the added load.</p> <p>5: Select an AC drive of higher power class.</p>
Over-voltage during acceleration	OU1	<p>1: The input voltage is too high.</p> <p>2: An external force drives the motor during acceleration.</p> <p>3: The acceleration time is too short.</p> <p>4: The braking unit and braking resistor are not installed.</p>	<p>1: Adjust the voltage to normal range.</p> <p>2: Cancel the external force or install a braking resistor.</p> <p>3: Increase the acceleration time.</p> <p>4: Install the braking unit and braking resistor.</p>
Over-voltage during deceleration	OU2	<p>1: The input voltage is too high.</p> <p>2: An external force drives the motor during deceleration.</p> <p>3: The deceleration time is too short.</p> <p>4: The braking unit and braking resistor are not installed.</p>	<p>1: Adjust the voltage to normal range.</p> <p>2: Cancel the external force or install the braking resistor.</p> <p>4: Install the braking unit and braking resistor.</p>
Over-voltage at constant speed	OU3	<p>1: The input voltage is too high.</p> <p>2: An external force drives the</p>	<p>1: Adjust the voltage to normal range.</p> <p>2: Cancel the</p>

		motor during deceleration.	external force or install the braking resistor.
Control power supply fault	POF	The input voltage is not within the allowable range.	Adjust the input voltage to the allowable range.
Lack of voltage	LU	1: Instantaneous power failure occurs on the input power supply. 2: The AC drive's input voltage is not within the allowable range. 3: The bus voltage is abnormal. 4: The rectifier bridge and buffer resistor are abnormal. 5: The drive board is abnormal. 6: The main control board is abnormal.	1: Reset the fault. 2: Adjust the voltage to normal range. 3,4,5,6: Looking for technical support
AC drive overload	OL2	1: The load is too heavy or motor-stalled occurs on the motor. 2: The AC drive model is of too small power class.	1: Reduce the load and check the motor and mechanical condition. 2: Select an AC drive of higher power class.
Motor overload	OL1	1: P9.01 is set improperly. 2: The load is too heavy or motor-stalled occurs on the motor. 3: The AC drive model is of too small power class.	1: Set P9.01 correctly. 2: Reduce the load and check the motor and the mechanical condition. 3: Select an AC drive of higher power class.

Input phase loss	LI	1. Three phase input power is abnormal 2. Drive board is abnormal 3. Lightning protection board is abnormal 4. Main control board is abnormal	1:Check the wiring 2,3,4 Looking for technical support
Power output phase loss	LO	1: The cable connecting the AC drive and the motor is faulty. 2: The AC drive's three-phase output is unbalanced when the motor is running. 3: The drive board is faulty. 4: The module is faulty.	1:Eliminate external faults. 2:Check whether the motor three-phase winding is normal. 3:Looking for technical support .
Module overheat	OH	1: The ambient temperature is too high.. 2: The air filter is blocked. 3: The fan is damaged. 4:The thermally sensitive resistor of the module is damaged. 5:The inverter module is damaged.	1:Lower the ambient temperature. 2:Clean the air filter. 3:Replace the damaged fan. 4:Replace the damaged thermally sensitive resistor. 5:Replace the inverter module.
External equipment fault	EF	1: External fault signal is input via S.	Reset the operation.

Communication fault	CE	<p>1: The host computer is in abnormal state.</p> <p>2: The communication cable is faulty.</p> <p>3: The communication parameters in group PD are set improperly.</p>	<p>1: Check the cabling of host computer.</p> <p>2: Check the communication cabling.</p> <p>3: Set the communication parameters properly.</p>
Contactor fault	Ray	<p>1: The drive board and power supply are faulty.</p> <p>2: The contactor is faulty.</p>	<p>1: Replace the faulty drive board or power supply board.</p> <p>2: Replace the faulty Contactor.</p>
Current detection fault	IE	<p>1: The HALL device is faulty.</p> <p>2: The drive board is faulty.</p>	<p>1: Replace the faulty HALL device.</p> <p>2: Replace the faulty drive board.</p>
Motor auto-tuning fault	TE	<p>1: The motor parameters are not set according to the nameplate.</p> <p>2: The motor auto-tuning times out.</p>	<p>1: Set the motor parameters according to the nameplate properly.</p> <p>2: Check the cable connecting the AC drive and the motor.</p>
EEPROM read-write fault	EEP	The EEPROM chip is damaged.	Replace the main control board.
AC drive hardware fault	OUOC	<p>1: Over-voltage exists.</p> <p>2: Over-current exists.</p>	<p>1: Handle based on over-voltage.</p> <p>2: Handle based on over-current.</p>

Short circuit to ground fault	GND	The motor is short circuited to the ground.	Replace the cable or motor.
Accumulative running time reached	END1	The accumulative running time reaches the setting value.	Clear the record through The parameter initialization function.
Accumulative power-on time reached	END2	The accumulative power-on time reaches the setting value.	Clear the record through the parameter initialization function.
Load becoming 0	LOAD	The AC drive running current is lower than P9.64.	Check that the load is disconnected or the setting of P9.64 and P9.65 is correct.
PID feedback lost during running fault	PIDE	The PID feedback is lower than the setting of PA.26.	Check the PID feedback signal or set PA.26 to a proper value.
Pulse-by-pulse current limit fault	CBC	1: The load is too heavy or locked-rotor occurs on the motor. 2: The AC drive model is of too small power class.	1: Reduce the load and check the motor and mechanical condition. 2: Select an AC drive of higher power class.
Too large speed deviation fault	ESP	1: No parameters identification 2:Parameters of too large speed deviation P9.69 and P9.70 are set incorrectly.	1: Motor parameters identify

Motor over-speed fault	OSP	1: No parameters identification	1: Motor parameters identify
------------------------	-----	---------------------------------	------------------------------

5-2 Common Faults and Solutions

You may come across the following faults during the use of the AC drive. Refer to the following table for simple fault analysis.

Troubleshooting to common faults of the AC drive

SN	Fault	Possible Causes	Solutions
1	There is no display when the power is on	1: There is no power supply to the AC drive or the power input to the AC drive is too low. 2: The power supply of the switch on the drive board of the AC drive is Faulty. 3: The rectifier bridge is damaged. 4: The control board or the operation panel is faulty. 5: The cable connecting the control board and the drive board and the operation panel breaks.	1: Check the power supply. 2: Check the bus voltage. 3: Looking for technical support
2	"2000" is displayed when the power is on	1: The cable between the drive board and the control board is in poor contact. 2: Related components on the control board are damaged. 3: The motor or the motor cable is short circuited to the ground. 4: The HALL device is faulty. 5: The power input to the AC drive is too low.	Looking for technical support

3	"GND" is displayed when power on	1: The motor or the motor output cable is short-circuited to the ground. 2: The AC drive is damaged.	1: Measure the insulation of the motor and the output cable with a meter. 2: Looking for technical support
4	The AC drive display is normal when the power is on. But "2000" is displayed after running and stops immediately.	1: The cooling fan is damaged or locked-rotor occurs. 2: The external control terminal cable is short circuited.	1: Replace the damaged fan. 2: Eliminate external faults.
5	OH (module overheat) fault is reported frequently.	1: The setting of carrier frequency is too high. 2: The cooling fan is damaged, or the air filter is blocked. 3: Components inside the AC drive are damaged (thermal coupler or others).	1: Reduce the carrier frequency (P0.17). 2: Replace the fan and clean the air filter. 3: Looking for technical support
6	The motor does not rotate after the AC drive runs.	1: Check the motor and the motor Cables. 2: The AC drive parameters are set improperly (motor parameters). 3: The cable between the drive board and the control board is in poor contact. 4: The drive board is faulty.	1: Ensure the cable between the AC drive and the motor is normal. 2: Replace the motor or clear mechanical faults. 3: Check and reset motor parameters.

7	The S terminals are disabled.	1: The parameters are set incorrectly. 2: The external signal is incorrect 3: The jumper bar across OP and +24 V becomes loose. 4: The control board is faulty.	1: Check and reset the parameters in group P5. 2: Re-connect the external signal cables. 3: Re-confirm the jumper bar across OP and +24 V. 4: Looking for technical support
8	Reserved		
9	The AC drive reports Over-current and over-voltage frequently.	1: The motor parameters are set improperly. 2: The acceleration/deceleration time is improper. 3: The load fluctuates.	1: Reset motor parameters or re-perform the motor auto-tuning . 2: Set proper acceleration/ deceleration time. 3: Looking for technical support
10	RAY is reported when the power is or the AC drive is running.	The soft startup contactor is not picked up.	1: Check whether the contactor cable is loose. 2: Check whether the contactor is faulty. 3: Check whether 24 V power supply of the contactor is faulty. 4: Looking for technical support

Appendix A List of Function Parameters

If PP.00 is set to a non-zero number, parameter protection is enabled. You must enter the correct user password to enter the menu. To cancel the password protection function, enter with password and set PP.00 to 0. Parameters menu the user customizes are not protected by password. Group P,C is the basic function parameters , Group D is to monitor the function parameters.The symbols in the function code table are described as follows:

“☆”: The parameter can be modified when the AC drive is in either stop or running state.

“★”: The parameter cannot be modified when the AC drive is in the running state.

“●”: The parameter is the actually measured value and cannot be modified.

“*”: The parameter is factory parameter and can be set only by the manufacturer.

Standard Function Parameters:

Function code	Name	Setting range	Default	Property
Group P0 Basic function				
P0.00	G/P type display	1:G type (constant torque load) 2: P type (variable torque load e.g. fan and pump)	Model dependent	●
P0.01	Control mode selection	0: Sensorless flux vector control 1: Closed-loop vector control 2: V/F control	2	★
P0.02	Command source selection	0: Operation panel control (LED off) 1: Terminal control (LED on) 2: Communication control (LED linking)	0	☆
P0.03	Main frequency source X selection	0: Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost don't memory)	0	★

		1: Digital setting (P0.08 preset frequency, can modify the UP/DOWN, power lost memory) 2: FIV (expansion card) 3: FIC 4: Reserved 5: Pulse setting 6: Multistage instruction 7: Simple PLC 8: PID 9: Communications given		
P0.04	Auxiliary frequency source Y selection	The same as P0.03 (Main frequency source X selection)	0	★
P0.05	Auxiliary frequency source superposition Y range selection	0: Relative to the maximum frequency 1: Relative to the main frequency source X	0	☆
P0.06	Auxiliary frequency source superposition Y range	0%～150%	100%	☆
P0.07	Frequency source superposition selection	Unit's digit (Frequency source) 0: Main frequency source X 1: X and Y operation(operation relationship determined by ten's digit) 2: Switchover between X and Y 3: Switchover between X and "X and Y operation" 4: Switchover between Y and "X and Y operation" Ten's digit (X and Y operation) 0: X+Y 1: X-Y	00	☆

		2: Both the maximum 3: Both the minimum		
P0.08	Frequency preset	0.00Hz～maximum frequency (P0.10)	50.00Hz	☆
P0.09	Rotation direction	0: Same direction 1: Reverse direction	0	☆
P0.10	Maximum frequency	50.00Hz～600.00Hz	50.00Hz	★
P0.11	Upper limit frequency source	0: P012 setting 1: FIV (expansion card) 2: FIC 3: Reserved 4: PULSE settings 5: Communication settings	0	★
P0.12	Upper limit frequency	Frequency lower limit P0.14～Maximum frequency P0.10	50.00Hz	☆
P0.13	Upper limit frequency offset	0.00Hz～Maximum frequency P0.10	0.00Hz	☆
P0.14	Frequency lower limit	0.00Hz～Upper limit frequency P0.12	0.00Hz	☆
P0.15	Carrier frequency	0.5kHz～16.0kHz	Model dependent	☆
P0.16	Carrier frequency adjustment with temperature	0: No 1: Yes	1	☆
P0.17	Acceleration time 1	0.00s～65000s	Model dependent	☆
P0.18	Deceleration time1	0.00s～65000s	Model dependent	☆
P0.19	Acceleration/ Deceleration time unit	0: 1s 1: 0.1s 2: 0.01s	1	★
P0.21	Frequency offset of auxiliary frequency source for X and Y operation	0.00Hz～Maximum frequencyP0.10	0.00Hz	☆
P0.22	Frequency command resolution	2: 0.01Hz	2	★

P0.23	Retentive of digital setting frequency upon power	0: Not retentive 1: Retentive	0	☆
P0.25	Acceleration/ Deceleration time base frequency	0: Maximum frequency (P0.10) 1: Set frequency 2: 100Hz	0	★
P0.26	Base frequency for UP/DOWN modification during running	0: Running frequency 1: Set frequency	0	★
P0.27	Binding command source to frequency source	Unit's digit:Binding operation panel command to frequency source 0:No binding 1:Frequency source by digital setting 2:FIV (expansion card) 3:FIC 4:Reserved 5:Pulse setting 6:Multi-Reference 7:Simple PLC 8:PID 9:Communication setting Ten's digit:Binding terminal command to frequency source Hundred's digit:Binding communication command to frequency source	0000	☆
Group P1 Motor parameters				
P1.00	Motor type	0: Common asynchronous motor 1: Variable frequency asynchronous motor	0	★
P1.01	Rated motor power	0.1kW～1000.0kW	Model dependent	★
P1.02	Rated motor voltage	1V～2000V	Model dependent	★
P1.03	Rated motor current	0.01A～655.35A	Model dependent	★

		(AC drive power≤55kW) 0.1A～6553.5A (AC drive power>55kW)		
P1.04	Rated motor frequency	0.01Hz～Maximum frequency	Model dependent	★
P1.05	Rated motor rotational speed	1rpm～65535rpm	Model dependent	★
P1.06	Stator resistance (asynchronous motor)	0.001Ω～65.535Ω (AC drive power≤55kW) 0.0001Ω～6.5535Ω (AC drive power>55kW)	Auto- tuning	★
P1.07	Rotor resistance (asynchronous motor)	0.001Ω～65.535Ω (AC drive power≤55kW) 0.0001Ω～6.5535Ω (AC drive power>55kW)	Auto- tuning	★
P1.08	Leakage inductive reactance (asynchronous motor)	0.01mH～655.35mH (AC drive power≤55kW) 0.001mH～65.535mH (AC drive power>55kW)	Auto- tuning	★
P1.09	Mutual inductive reactance (asynchronous motor)	0.1mH～6553.5mH (AC drive power≤55kW) 0.01mH～655.35mH (AC drive power>55kW)	Auto- tuning	★
P1.10	No-load current (synchronous motor)	0.01A～P1.03 (AC drive power≤55kW) 0.1A～P1.03 (AC drive power>55kW)	Auto- tuning	★
P1.27	Encoder resolution	1～65535	1024	★
P1.28	Encoder type	0: ABZ incremental encoder 2: Resolver	0	★
P1.30	AB phase sequence of ABZ incremental encoder	0: Forward 1: Reverse	0	★

P1.31	Encoder angle offset	0.0~359.9°	0.0°	★
P1.34	Number of pole pairs of resolver	1~65535	1	★
P1.36	Speed feedback PG disconnection detection time	0.0: No action 0.1s~10.0s	0.0	★
P1.37	Auto-tuning selection	0: No operation 1:Static auto-tuning 2:Dynamic auto-tuning 3:Complete static auto-tuning	0	★
Group P2 Motor vector control parameters				
P2.00	Speed loop proportional gain1	1~100	30	☆
P2.01	Speed loop integral time1	0.01s~10.00s	0.50s	☆
P2.02	Switchover frequency 1	0.00~P2.05	5.00Hz	☆
P2.03	Speed loop proportional gain2	1~100	20	☆
P2.04	Speed loop integral time2	0.01s~10.00s	1.00s	☆
P2.05	Switchover frequency 2	P2.02~Maximum frequency	10.00Hz	☆
P2.06	Vector control slip gain	50%~200%	100%	☆
P2.07	Time constant of speed loop filter	0.000s~1.000s	0.05s	☆
P2.09	Torque upper limit source in speed control mode	0: Function code P2.10 setting 1: FIV (expansion card) 2: FIC 3: Reserved 4: Pulse setting 5: Communication setting 6: MIN (FIV (expansion card) , FIC) 7: MAX (FIV (expansion card) ,FIC) 1-7's Full Scale to P2.10	0	☆
P2.10	Digital setting of torque upper limit in speed control mode(electrical)	0.0%~200.0%	150.0%	☆

P2.13	Excitation adjustment proportional gain	0~60000	2000	☆
P2.14	Excitation adjustment integral gain	0~60000	1300	☆
P2.15	Torque adjustment proportional gain	0~60000	2000	☆
P2.16	Torque adjustment integral gain	0~60000	1300	☆
P2.17	Speed loop integral property	Unit's digit: integral separation 0: Disabled 1: Enabled	0	☆
P2.21	Maximum torque coefficient of field weakening area	50%~200%	100%	☆
P2.22	Generation power limit enable	0: Disabled 1: Full effect	0	☆
Group P3 V/F control parameters				
P3.00	V/F curve setting	0: Linear V/F 1: Multi-point V/F 2: Square V/F 3: 1.2-power V/F 4: 1.4-power V/F 6: 1.6-power V/F 8: 1.8-power V/F 9: Reserved 10: V/F complete separation 11: V/F half separation	0	★
P3.01	Torque boost	0.0%: (Automatic torque boost) 0.1%~30.0%	Model dependent	☆
P3.02	Cut-off frequency of torque boost	0.00Hz~Maximum frequency	50.00Hz	★
P3.03	Multi-point V/F frequency 1	0.00Hz~P3.05	0.00Hz	★
P3.04	Multi-point V/F voltage 1	0.0%~100.0%	0.0%	★
P3.05	Multi-point V/F frequency 2	P3.03~P3.07	0.00Hz	★

P3.06	Multi-point V/F voltage 2	0.0%~100.0%	0.0%	★
P3.07	Multi-point V/F frequency 3	P3.05~rated motor frequency (P1.04)	0.00Hz	★
P3.08	Multi-point V/F voltage 3	0.0%~100.0%	0.0%	★
P3.09	VF slip compensation gain	0.0%~200.0%	0.0%	☆
P3.10	VF over-excitation gain	0~200	64	☆
P3.11	VF oscillation suppression gain	0~100	Model dependent	☆
P3.13	Voltage source for V/F separation	0: digital setting (P3.14) 1: FIV (expansion card) 2: FIC 3: Reserved 4: PULSE setting 5: Multi-Reference 6: Simple PLC 7: PID 8: Communication setting Note: 100% corresponding to rated motor voltage	0	☆
P3.14	Voltage digital setting for V/F separation	0V~rated motor voltage	0V	☆
P3.15	Voltage acceleration time of V/F separation	0.0s~1000.0s It indicates the time for the voltage accelerate from 0V to rated motor voltage	0.0s	☆
P3.16	Voltage deceleration time of V/F separation	0.0s~1000.0s .It indicates the time for the voltage decelerate from rated motor voltage to 0V	0.0s	☆
P3.17	Stop mode of V/F separation	0: Frequency/voltage independently decrease to 0 1: After voltage decrease to 0, frequency decrease again	0	☆
P3.18	Action current of over	50%~200%	150%	★

	current stall			
P3.19	Over current stall enable	0: Disabled 1: Enabled	1	★
P3.20	Over current stall suppression gain	0~100	20	☆
P3.21	Action current compensation coefficient of multiple over current stall	50%~200%	50%	★
P3.22	Action voltage of over current stall	200.0V~2000.0V	760.0V	★
P3.23	Over voltage stall enable	0: Disabled 1: Enabled	1	★
P3.24	Over voltage stall suppression gain	0~100	30	☆
P3.25	Over voltage stall suppression voltage gain	0~100	30	☆
P3.26	Maximum rising frequency limit of over voltage stall	0~50Hz	5Hz	★
Group P4 Input terminals				
P4.00	X1 function selection	0: No function	1	★
P4.01	X2 function selection	1: Forward RUN (FWD)	2	★
P4.02	X3 function selection	2: Reverse RUN (REV)	9	★
P4.03	X4 function selection	3: Three-line control	12	★
P4.04	X5 function selection	4: Forward JOG (JOG-F)	13	★
P4.05	X6 function selection(Expansion card)	5: Reverse JOG (JOG-R) 6: Terminal UP	0	★
P4.06	X7 function selection(Expansion card)	7: Terminal DOWN 8: Coast to stop	0	★
P4.07	Reserved	9: Fault reset (RESET) 10: RUN pause 11: Normally open (NO) input of external fault 12: Multi-Reference terminal 1 13: Multi-Reference terminal 2 14: Multi-Reference terminal 3 15: Multi-Reference terminal 4	0	★

		<p>16: Terminal 1 for acceleration/ deceleration time selection</p> <p>17: Terminal 2 for acceleration/ deceleration time selection</p> <p>18: Frequency source Switchover</p> <p>19: UP and DOWN setting clear (terminal, operation panel)</p> <p>20: Command source switchover terminal</p> <p>21: Acceleration/Deceleration Prohibited</p> <p>22: PID pause</p> <p>23: PLC status reset</p> <p>24: Swing pause</p> <p>25: Counter input</p> <p>26: Counter reset</p> <p>27: Length count input</p> <p>28: Length reset</p> <p>29: Torque control prohibited</p> <p>30: Pulse frequency input (enabled onlyfor S3)</p> <p>31: Reserved</p> <p>32: Immediate DC braking</p> <p>33: Normally closed (NC) input of external fault</p> <p>34: Frequency modification forbidden</p> <p>35: Reverse PID action direction</p> <p>36: External STOP terminal 1</p> <p>37: Command source switchover terminal 2</p>		
--	--	--	--	--

		38: PID integral pause 39: Switchover between main frequency source X and preset frequency 40: Switchover between auxiliary frequency source Y and preset frequency 41: Reserved 42: Reserved 43: PID parameter switchover 44: Reserved 45: Reserved 46: Speed control/Torque control switchover 47: Emergency stop 48: External STOP terminal 2 49: Deceleration DC braking 50: Clear the current running time 51-59:Reserved		
P4.10	Filter time	0.000s~1.000s	0.010s	☆
P4.11	Terminal command mode	0: Two-line mode 1 1: Two-line mode 2 2: Three-line mode 1 3: Three-line mode 2	0	★
P4.12	Terminal UP/DOWN rate	0.001Hz/s~65.535Hz/s	1.00Hz/s	☆
P4.13	Fl curve 1 minimum input	0.00V~P4.15	0.00V	☆
P4.14	Corresponding setting of Fl curve 1 minimum input	-100.0%~+100.0%	0.0%	☆
P4.15	Fl curve 1 maximum input	P4.13~+10.00V	10.00V	☆
P4.16	Corresponding setting of Fl curve 1 maximum input	-100.0%~+100.0%	100.0%	☆
P4.17	Fl curve 1 filter time	0.00s~10.00s	0.10s	☆
P4.18	Fl curve 2 minimum input	0.00V~P4.20	0.00V	☆
P4.19	Corresponding setting of Fl	-100.0%~+100.0%	0.0%	☆

	curve 2 minimum input			
P4.20	FI curve 2 maximum input	P4.18～+10.00V	10.00V	☆
P4.21	Corresponding setting of FI curve 2 maximum input	-100.0%～+100.0%	100.0%	☆
P4.22	FI curve 2 filter time	0.00s～10.00s	0.10s	☆
P4.23	FI curve 3 minimum input	-10.00V～P4.25	-10.00V	☆
P4.24	Corresponding setting of FI curve 3 minimum input	-100.0%～+100.0%	0.0%	☆
P4.25	FI curve 3 maximum input	P4.23～+10.00V	10.00V	☆
P4.26	Corresponding setting of FI curve 3 maximum input	-100.0%～+100.0%	100.0%	☆
P4.27	FI curve 3 filter time	0.00s～10.00s	0.10s	☆
P4.28	PULSE minimum input	0.00kHz～P4.30	0.00kHz	☆
P4.29	Corresponding setting of pulse minimum input	-100.0%～100.0%	0.0%	☆
P4.30	PULSE maximum input	P4.28～100.00kHz	50.00kHz	☆
P4.31	Corresponding setting of pulse maximum input	-100.0%～100.0%	100.0%	☆
P4.32	PULSE filter time	0.00s～10.00s	0.10s	☆
P4.33	FI curve selection	Unit's digit: FIV (expansion card) curve selection 1: Curve 1 (2 points, see P4.13～P4.16) 2: Curve 2 (2 points, see P4.18～P4.21) 3: Curve 3 (2 points, see P4.23～P4.26) 4: Curve 4 (4 points, see C6.00～C6.07) 5: Curve 5 (4 points, see C6.08～C6.15) Ten's digit: FIC curve selection (1～5, same as FIV) Hundred's digit: Reserved	321	☆
P4.34	Setting selection for FI less than minimum input	Unit's digit: Setting for FIV (expansion card) less than minimum input	000	☆

		0: Corresponds to the minimum input settings 1:0.0% Ten's digit: Setting selection for FIC less than minimum input (0~1, same as FIV)		
P4.35	X1 delay time	0.0s~3600.0s	0.0s	★
P4.36	X2 delay time	0.0s~3600.0s	0.0s	★
P4.37	X3 delay time	0.0s~3600.0s	0.0s	★
P4.38	X valid mode selection 1	0: High level valid 1: Low level valid Unit's digit: X1 Ten's digit: X2 Hundred's digit: X3 Thousand's digit: X4 Ten thousand's digit: X5	00000	★
P4.39	X valid mode selection 2	0: High level valid 1: Low level valid Unit's digit: X6(Expansion card) Ten's digit: X7(Expansion card) Hundred's digit: Reserved Thousand's digit: Reserved Ten thousand's digit:Reserved	00000	★
Group P5 Output terminals				
P5.00	MO1 terminal output mode selection(Expansion card)	0: Pulse output (MO1-COM) 1: Switch signal output (MOA-MOB-MOC)	0	☆
P5.01	MOA-MOB-MOC output function selection (Expansion card)	0: No output 1: AC drive running 2: Fault output	0	☆
P5.02	Control board relay function selection (YA-YB-	3: Frequency-level	2	☆

	YC)	detection FDT1 output		
P5.03	Reserved	4: Frequency reached	0	☆
P5.04	YO terminal output function selection	5: Zero-speed running(no output at stop)	1	☆
P5.05	Reserved	6: Motor overload pre- warning 7: AC drive overload pre- warning 8: Setting count value Reached 9: Designated count value reached 10: Length reached 11: PLC cycle complete 12: Accumulative running time reached 13: Frequency limited 14: Torque limited 15: Ready for RUN 16: FIV (expansion card) >FIC 17: Frequency upper limit reached 18: Frequency lower limit reached (relate to run) 19: Under voltage state output 20: Communication setting 21: (Reserved) 22: (Reserved) 23: Zero-speed running 2 (having output at stop) 24: Accumulative power- on time reached 25: Frequency level detection FDT2 output 26: Frequency 1 reached output	4	☆

		27: Frequency 2 reached output 28: Current 1 reached output 29: Current 2 reached output 30: Timing reached output 31: FIV (expansion card) input limit exceeded 32: Load becoming 0 33: Reverse running 34: Zero current state 35: Module temperature reached 36: Output current limit exceeded 37: Frequency lower limit reached (having output at stop) 38: Alarm output(Keep running) 39: Motor overheat pre-warning 40: Current running time reached 41: Fault output(No output at under voltage)		
P5.06	MO1 output function selection	0: Running frequency	0	☆
P5.07	FOV output function selection	1: Setting frequency		
		2: Output current	0	☆
		3: Output torque		
P5.08	FOC (expansion card) output function selection	4: Output power		
		5: Output voltage		
		6: Pulse input (100.0% for 100.0kHz)	1	☆
		7: FIV (expansion card)		
		8: FIC		
		9: Reserved		

		10: Length 11: Count value 12: Communication setting 13: Motor rotational speed 14: Output current (100.0% for 1000.0A) 15: Output voltage (100.0% for 1000.0V) 16: Output torque (Actual value, corresponding to motor percentage)		
P5.09	MO1 output Maximum frequency	0.01kHz～100.00kHz	50.00kHz	☆
P5.10	FOV bias coefficient	-100.0%～+100.0%	0.0%	☆
P5.11	FOV gain	-10.00～+10.00	1.00	☆
P5.12	FOC (Expansion card) bias coefficient	-100.0%～+100.0%	0.0%	☆
P5.13	FOC (Expansion card) gain	-10.00～+10.00	1.00	☆
P5.17	MOA-MOB-MOC output delay time	0.0s～3600.0s	0.0s	☆
P5.18	YA-YB-YC output delay time	0.0s～3600.0s	0.0s	☆
P5.22	Output terminal valid mode selection	0: Positive logic 1: Negative logic Unit's digit: MOA-MOB-MOC Ten's digit: YA-YB-YC Hundred's digit: Reserved	00000	☆
Group P6 Start/Stop				
P6.00	Start mode	0: Direct start 1: Rotational speed tracking restart 2: Pre-excited start (asynchronous motor)	0	☆
P6.01	Rotational speed tracking mode	0: From frequency at stop 1: From zero speed 2: From maximum	0	★

		frequency		
P6.02	Rotational speed tracking speed	1~100	20	☆
P6.03	Startup frequency	0.00Hz~10.00Hz	0.00Hz	☆
P6.04	Startup frequency holding time	0.0s~100.0s	0.0s	★
P6.05	Startup DC braking current/ Pre-excited current	0%~100%	0%	★
P6.06	Startup DC braking time/Pre-excited time	0.0s~100.0s	0.0s	★
P6.07	Acceleration/ Deceleration mode	0: Linear acceleration/deceleration 1: S-curve acceleration/deceleration A 2: Dynamic S-curve acceleration/deceleration B	0	★
P6.08	Time proportion of S-curve start	0.0%~ (100.0%-P6.09)	30.0%	★
P6.09	Time proportion of S-curve end	0.0%~ (100.0%-P6.08)	30.0%	★
P6.10	Stop mode	0: Decelerate to stop 1: Coast to stop	0	☆
P6.11	Initial frequency of stop DC braking	0.00Hz~Maximum frequency	0.00Hz	☆
P6.12	Waiting time of stop DC braking	0.0s~100.0s	0.0s	☆
P6.13	Stop DC braking current	0%~100%	0%	☆
P6.14	Stop DC braking time	0.0s~100.0s	0.0s	☆
P6.15	Brake use ratio	0%~100%	100%	☆
P6.18	Speed tracking current	30%~200%	Model dependent	★
P6.21	Demagnetization time (SVC valid)	0.00~5.00s	Model dependent	☆
Group P7: Operation Panel and Display				
P7.02	STOP/RESET function	0:STOP/RESET key enabled only in operation panel control 1:STOP/RESET key enabled	1	☆

		in any operation mode		
P7.03	LED display running parameters 1	0000—FFFF Bit00: Operating frequency 1 (Hz) Bit01: Set frequency (Hz) Bit02: DC bus voltage (V) Bit03: output voltage (V) Bit04: Output current (A) Bit05: Output power (kW) Bit06: output torque (%) Bit07: Input terminal status Bit08: Output terminal status Bit09: FIV (expansion card) voltage (V) Bit10: FIC voltage (V) Bit11: Reserved Bit12: count value Bit13: length value Bit14: Display load speed Bit15: PID setting	1F	☆
P7.04	LED display running parameters 2	0000—FFFF Bit00: PID feedback Bit01: PLC stage Bit02: PULSE input pulse frequency (kHz) Bit03: Motor speed (rpm) Bit04: remaining running time Bit05: FIV (extension card) voltage before calibration (V) Bit06: Voltage before FIC correction (V) Bit07: Reserved Bit08: Motor speed Bit09: Current power-on time (Hour) Bit10: Current running time (Min)	0	☆

		Bit11: PULSE input pulse frequency (Hz) Bit12: Communication set value Bit13: encoder feedback speed (Hz) Bit14: Display of main frequency X (Hz) Bit15: Display of auxiliary frequency Y (Hz)		
P7.05	LED display stop parameters	0000–FFFF Bit00: Set frequency (Hz) Bit01: DC bus voltage (V) Bit02: DI input status Bit03: DO output status Bit04: FIV (expansion card) voltage (V) Bit05: FIC voltage (V) Bit06: Reserved Bit07: Count value Bit08: Length value Bit09: PLC stage Bit10: Load speed Bit11: PID setting Bit12: Pulse setting frequency (kHz)	33	☆
P7.06	Load speed display coefficient	0.0001～6.5000	1.0000	☆
P7.07	Heatsink temperature of inverter	0.0℃～120.0℃	-	●
P7.08	Rectifier bridge radiator temperature	0.0℃～120.0℃	-	●
P7.09	Accumulative running time	0h～65535h	-	●
P7.10	Performance software version number	-	-	●
P7.11	Function software version	-	-	●
P7.12	Load speed display decimal point	Unit's dgit: D0.14 Number of decimal points 0: 0 decimal place 1: 1 decimal place	21	☆

		2: 2 decimal places 3: 3 decimal places Ten's dgit: D0.19/D0.29 Number of decimal points 1: 1 decimal place 2: 2 decimal place		
P7.13	Accumulative power on time	0h~65535h	-	●
P7.14	Accumulative power consumption	0kW~65535 kWh	-	●
Group P8: Auxiliary Functions				
P8.00	JOG running frequency	0.00Hz~Maximum frequency	2.00Hz	☆
P8.01	JOG acceleration time	0.0s~6500.0s	20.0s	☆
P8.02	JOG deceleration time	0.0s~6500.0s	20.0s	☆
P8.03	Acceleration time 2	0.00s~65000s	Model dependent	☆
P8.04	Deceleration time 2	0.0s~65000s	Model dependent	☆
P8.05	Acceleration time 3	0.0s~65000s	Model dependent	☆
P8.06	Deceleration time 3	0.0s~65000s	Model dependent	☆
P8.07	Acceleration time 4	0.0s~65000s	Model dependent	☆
P8.08	Deceleration time 4	0.0s~65000s	Model dependent	☆
P8.09	Jump frequency 1	0.00Hz~Maximum frequency	0.00Hz	☆
P8.10	Jump frequency 2	0.00Hz~Maximum frequency	0.00Hz	☆
P8.11	Frequency jump amplitude	0.00Hz~Maximum frequency	0.00Hz	☆
P8.12	Forward/Reverse rotation dead-zone time	0.0s~3000.0s	0.0s	☆
P8.13	Reverse control	0: Enabled 1: Disabled	0	☆
P8.14	Running mode when set frequency lower than frequency lower limit	0: Run at frequency lower limit 1: Stop	0	☆

		2: Run at zero speed		
P8.15	Droop control	0.00Hz～10.00Hz	0.00Hz	☆
P8.16	Accumulative power-on time threshold	0h～65000h	0h	☆
P8.17	Accumulative running time threshold	0h～65000h	0h	☆
P8.18	Startup protection	0: No 1: Yes	0	☆
P8.19	Frequency detection value (FDT1)	0.00Hz～Maximum frequency	50.00Hz	☆
P8.20	Frequency detection hysteresis (FDT1)	0.0%～100.0% (FDT1 level)	5.0%	☆
P8.21	Detection range of frequency reached	0.0%～100.0% (Maximum frequency)	0.0%	☆
P8.22	Jump frequency during acceleration/Deceleration	0: Disabled 1: Enabled	0	☆
P8.25	Frequency switchover point between acceleration time 1 and acceleration time 2	0.00Hz～Maximum frequency	0.00Hz	☆
P8.26	Frequency switchover point between deceleration time 1 and deceleration time 2	0.00Hz～Maximum frequency	0.00Hz	☆
P8.27	Terminal JOG preferred	0: Disabled 1: Enabled	0	☆
P8.28	Frequency detection value (FDT2)	0.00Hz～Maximum frequency	50.00Hz	☆
P8.29	Frequency detection hysteresis (FDT2)	0.0%～100.0% (FDT2 level)	5.0%	☆
P8.30	Any frequency reaching detection value 1	0.00Hz～Maximum frequency	50.00Hz	☆
P8.31	Any frequency reaching detection amplitude 1	0.0%～100.0% (Maximum frequency)	0.0%	☆
P8.32	Any frequency reaching detection value 2	0.00Hz～Maximum frequency	50.00Hz	☆
P8.33	Any frequency reaching detection amplitude 2	0.0%～100.0% (Maximum frequency)	0.0%	☆

P8.34	Zero current detection level	0.0%~300.0% 100.0% for rated motor current	5.0%	☆
P8.35	Zero current detection delay tim	0.01s~600.00s	0.10s	☆
P8.36	Output over-current threshold	0.0% (No detection) 0.1%~300.0% (rated motor current)	200.0%	☆
P8.37	Output over-current detection delay time	0.00s~600.00s	0.00s	☆
P8.38	Any current reaching 1	0.0%~300.0% (rated motor current)	100.0%	☆
P8.39	Any current reaching 1 amplitude	0.0%~300.0% (rated motor current)	0.0%	☆
P8.40	Any current reaching 2	0.0%~300.0% (rated motor current)	100.0%	☆
P8.41	Any current reaching 2 amplitude	0.0%~300.0% (rated motor current)	0.0%	☆
P8.42	Timing function selection	0:Disabled 1:Enabled	0	☆
P8.43	Timing duration source	0: P8.44 setting 1: FIV (expansion card) 2: FIC 3: Reserved 100% of analog input corresponds to the value of P8.44	0	☆
P8.44	Timing duration source	0.0Min~6500.0Min	0.0Min	☆
P8.45	FIV input voltage lower limit	0.00V~P8.46	3.10V	☆
P8.46	FIV input voltage upper limit protection value	P8.45~11.00V	6.80V	☆
P8.47	Module temperature threshold	0℃~100℃	75℃	☆
P8.48	Cooling fan control	0: Fan working during running 1: Fan working continuously	0	☆
P8.49	Wake up frequency	Dormant frequency	0.00Hz	☆

		(P8.51) ~ Maximum frequency (P0.10)		
P8.50	Wake up delay time	0.0s~6500.0s	0.0s	☆
P8.51	Dormant frequency	0.00Hz~ wake up frequency (P8.49)	0.00Hz	☆
P8.52	Dormant delay time	0.0s~6500.0s	0.0s	☆
P8.53	Current running time reached setting	0.0Min~6500.0Min	0.0Min	☆
P8.54	Output power correction coefficient	0~200%	100%	☆
Group P9 Fault and Protection				
P9.00	Motor overload protection selection	0: Disabled 1: Enabled	1	☆
P9.01	Motor overload protection gain	0.20~10.00	1.00	☆
P9.02	Motor overload warning coefficient	50%~100%	80%	☆
P9.03	Over-voltage stall gain	0~100	0	☆
P9.04	Over-voltage stall protective voltage	200.0V ~ 2000.0V	760.0V	☆
P9.07	Short-circuit to ground upon power-on	0: Disabled 1: Enabled	1	☆
P9.09	Fault auto reset times	0~20	0	☆
P9.10	MOA-MOB-MOC action during fault auto reset	0: No action 1: Action	0	☆
P9.11	Time interval of fault auto reset	0.1s~100.0s	1.1s	☆
P9.12	Input phase loss/contactorsuction protection selection	Unit's digit: Input phase loss protection selection Unit's digit: Contactor suction protection selection 0: Disabled 1: Enabled	11	☆
P9.13	Output phase loss protection selection	0: Disabled 1: Enabled	1	☆
P9.14	1st fault type	0: No fault	—	●
P9.15	2nd fault type	1: Reserved	—	●
P9.16	3rd (latest) fault type	2: Over-current during acceleration 3: Over-current during	—	●

		<p>deceleration</p> <p>4: Over-current at constant speed</p> <p>5: Over-voltage during acceleration</p> <p>6: Over-voltage during deceleration</p> <p>7: Over-voltage at constant speed</p> <p>8: Snubber resistor overload</p> <p>9: Undervoltage</p> <p>10: AC drive overload</p> <p>11: Motor overload</p> <p>12: Input phase loss</p> <p>13: Output phase loss</p> <p>14: Module overheat</p> <p>15: External equipment fault</p> <p>16: Communication fault</p> <p>17: Contactor fault</p> <p>18: Current detection fault</p> <p>19: Motor auto-tuning fault</p> <p>20: Encoder/PG card fault</p> <p>21: Parameters read-write fault</p> <p>22: AC drive hardware fault</p> <p>23: Short circuit to ground</p> <p>24: Reserved</p> <p>25: Reserved</p> <p>26: Accumulative running time reached</p> <p>27: Reserved</p> <p>28: Reserved</p> <p>29: Accumulative power-on time reached</p> <p>30: Load becoming 0</p> <p>31: PID feedback lost during running</p> <p>40: Rapid limit overtime</p>		
--	--	---	--	--

		41: Switch motor during running 42: Speed deviation too large 43: Motor over speed 45: Reserved		
P9.17	Frequency upon 3rd(latest) fault	—	—	●
P9.18	Current upon 3rd (latest) fault	—	—	●
P9.19	Bus voltage upon 3rd(latest) fault	—	—	●
P9.20	Input terminal status upon 3rd(latest) fault	—	—	●
P9.21	Output terminal status upon 3rd (latest) fault	—	—	●
P9.22	AC drive status upon 3rd(latest) fault	—	—	●
P9.23	Power-on time upon 3rd (latest) fault	—	—	●
P9.24	Running time upon 3rd (latest) fault	—	—	●
P9.27	Frequency upon 2nd fault	—	—	●
P9.28	Current upon 2nd fault	—	—	●
P9.29	Bus voltage upon 2nd fault	—	—	●
P9.30	Input terminal status upon 2nd fault	—	—	●
P9.31	Output terminal status upon 2nd fault	—	—	●
P9.32	Frequency status upon 2nd fault	—	—	●
P9.33	Power-on time upon 2nd fault	—	—	●
P9.34	Running time upon 2nd fault	—	—	●
P9.37	Frequency upon 1st fault	—	—	●
P9.38	Current upon 1st fault	—	—	●
P9.39	Bus voltage upon 1st fault	—	—	●
P9.40	Input terminal status upon	—	—	●

	1st fault			
P9.41	Output terminal status upon 1st fault	—	—	●
P9.42	Frequency status upon 1st fault	—	—	●
P9.43	Power-on time upon 1st fault	—	—	●
P9.44	Running time upon 1st fault	—	—	●
P9.47	Fault protection action selection 1	Unit's digit: Motor overload (OL1) 0: Coast to stop 1: Stop according to the stop mode 2: Continue to run Ten's digit: Reserved Hundred's digit: Power output phase loss (LO) Thousand's digit: External equipment fault (EF) Ten thousand's digit: Communication fault (CE)	00000	☆
P9.48	Fault protection action selection 2	Unit's digit: Reserved 0: Coast to stop Ten's digit: Function code read-write fault (EEP) 0: Coast to stop 1: Stop according to the stop mode Hundred's digit: Reserved Thousand's digit: Reserved Ten thousand's digit: Accumulative running time reached (END1)	00000	☆
P9.49	Fault protection action selection 3	Unit's digit: Reserved 0: Coast to stop 1: Stop according to the	00000	☆

		<p>stop mode</p> <p>2: Continue to run</p> <p>Ten's digit: Reserved</p> <p>0: Coast to stop</p> <p>1: Stop according to the stop mode</p> <p>2: Continue to run</p> <p>Hundred's digit:</p> <p>Accumulative power-on time reached (END2)</p> <p>0: Coast to stop</p> <p>1: Stop according to the stop mode</p> <p>2: Continue to run</p> <p>Thousand's digit: Load becoming 0 (LOAD)</p> <p>0: Coast to stop</p> <p>1: Stop according to the stop mode</p> <p>2: Continue to run at 7% of rated motor frequency and resume to the set frequency if the load recovers</p> <p>Ten thousand's digit: PID feedback loss of running(PIDE)</p> <p>0: Coast to stop</p> <p>1: Stop according to the stop mode</p> <p>2: Continue to run</p>		
P9.50	Fault protection action selection 4	<p>Unit's digit: Speed deviation is too large(42)</p> <p>0: Coast to stop</p> <p>1: Stop according to the stop mode</p> <p>2: Continue to run</p> <p>Ten's digit: Reserved</p>	00000	☆

		Hundred's digit: Reserved		
P9.54	Frequency selection for continuing to run	0: Current running frequency 1: Set frequency 2: Frequency upper limit 3: Frequency lower limit 4: Backup frequency upon abnormality	0	☆
P9.55	Backup frequency upon abnormality	0.0%~100.0% (100.0% corresponds to the maximum frequency P0.10)	100.0%	☆
P9.59	Action selection at instantaneous power failure	0: Invalid 1: Decelerate 2: Decelerate to stop	0	☆
P9.60	Action pause judging voltage at instantaneous power failure	P9.62~100.0%	85.0%	☆
P9.61	Voltage rally judging time at instantaneous power failure	0.00s~100.00s	0.50s	☆
P9.62	Action judging voltage at instantaneous power failure	60.0%~100.0% (standard bus voltage)	80.0%	☆
P9.63	Protection upon load becoming 0	0: Disabled 1: Enabled	0	☆
P9.64	Detection level of load becoming 0	0.0~100.0%	10.0%	☆
P9.65	Detection time of load becoming 0	0.0~60.0s	1.0s	☆
P9.67	Over speed detection value	0.0%~50.0% (Maximum frequency)	20.0%	☆
P9.68	Over speed detection time	0.0s~60.0s	1.0s	☆
P9.69	Detection value of speed deviation too large	0.0%~50.0% (Maximum frequency)	20.0%	☆
P9.70	Detection time of speed deviation too large	0.0s~60.0s	0.0s	☆
P9.71	Instantaneous power failure gain	0~100	40	☆

P9.72	Instantaneous power failure integral coefficient	0~100	30	☆
P9.73	Instantaneous power failure action deceleration time	0~300.0s	20.0s	★
Group PA PID function				
PA.00	PID setting source	0: PA.01 1: FIV (expansion card) 2: FIC 3: Reserved 4: PULSE setting 5: Communication setting 6: Multi-reference	0	☆
PA.01	PID digital setting	0.0%~100.0%	50.0%	☆
PA.02	PID feedback source	0: FIV (expansion card) 1: FIC 2: Reserved 3: FIV (expansion card)-FIC 4: PULSE setting 5: Communication setting 6: FIV (expansion card)+FIC 7: MAX (FIV (expansion card) , FIC) 8: MIN (FIV (expansion card) , FIC)	0	☆
PA.03	PID action direction	0: Forward action 1: Reverse action	0	☆
PA.04	PID setting feedback range	0~65535	1000	☆
PA.05	Proportional gain Kp1	0.0~100.0	20.0	☆
PA.06	Integral time Ti1	0.01s~10.00s	2.00s	☆
PA.07	Differential time Td1	0.000s~10.000s	0.000s	☆
PA.08	Cut-off frequency of PID reverse	0.00~Maximum frequency	2.00Hz	☆
PA.09	PID deviation limit	0.0%~100.0%	0.0%	☆
PA.10	PID differential limit	0.00%~100.00%	0.10%	☆
PA.11	PID setting change time	0.00~650.00s	0.00s	☆
PA.12	PID feedback filter time	0.00~60.00s	0.00s	☆

PA.13	PID output filter time	0.00~60.00s	0.00s	☆
PA.15	Proportional gain KP1	0.0~100.0	20.0	☆
PA.16	Integral time Ti2	0.01s~10.00s	2.00s	☆
PA.17	Differential time Td2	0.000s~10.000s	0.000s	☆
PA.18	PID parameter switchover condition	0: No switchover 1: Switchover via X 2: Automatic switchover based on deviation 3: Automatic switchover based on running frequency	0	☆
PA.19	PID parameter switchover deviation 1	0.0%~PA.20	20.0%	☆
PA.20	PID parameter switchover deviation 2	PA.19~100.0%	80.0%	☆
PA.21	PID initial value	0.0%~100.0%	0.0%	☆
PA.22	PID initial value holding time	0.00~650.00s	0.00s	☆
PA.25	PID integral property	Unit's digit: Integral separated 0: Invalid 1: Valid Ten's digit: Whether to stop integral operation when the output reaches 0: Continue integral operation 1: Stop integral operation	00	☆
PA.26	Detection value of PID feedback loss	0.0%: Not judging feedback loss 0.1%~100.0%	0.0%	☆
PA.27	Detection time of PID feedback loss	0.0s~20.0s	0.0s	☆
PA.28	PID stop operation	0: No PID operation at stop 1: PID operation at stop	0	☆
Group PC Multi-Reference and Simple PLC Function				
PC.00	Multi-Reference0	-100.0%~100.0%	0.0%	☆

PC.01	Multi-Reference1	-100.0%～100.0%	0.0%	☆
PC.02	Multi-Reference2	-100.0%～100.0%	0.0%	☆
PC.03	Multi-Reference3	-100.0%～100.0%	0.0%	☆
PC.04	Multi-Reference4	-100.0%～100.0%	0.0%	☆
PC.05	Multi-Reference5	-100.0%～100.0%	0.0%	☆
PC.06	Multi-Reference6	-100.0%～100.0%	0.0%	☆
PC.07	Multi-Reference7	-100.0%～100.0%	0.0%	☆
PC.08	Multi-Reference8	-100.0%～100.0%	0.0%	☆
PC.09	Multi-Reference9	-100.0%～100.0%	0.0%	☆
PC.10	Multi-Reference10	-100.0%～100.0%	0.0%	☆
PC.11	Multi-Reference11	-100.0%～100.0%	0.0%	☆
PC.12	Multi-Reference12	-100.0%～100.0%	0.0%	☆
PC.13	Multi-Reference13	-100.0%～100.0%	0.0%	☆
PC.14	Multi-Reference14	-100.0%～100.0%	0.0%	☆
PC.15	Multi-Reference15	-100.0%～100.0%	0.0%	☆
PC.16	Simple PLC running mode	0: Stop after the AC drive runs one cycle 1: Keep final values after the AC drive runs one cycle 2: Repeat after the AC drive runs one cycle	0	☆
PC.17	Simple PLC retentive selection	Unit's digit: Retentive upon power failure selection 0: No 1: Yes Ten's digit: Retentive upon stop selection 0: No 1: Yes	00	☆
PC.18	Running time of simple PLC reference 0	0.0s (h) ～6500.0s (h)	0.0s (h)	☆
PC.19	Acceleration/deceleration time of simple PLC reference 0	0～3	0	☆
PC.20	Running time of simple PLC reference 1	0.0s (h) ～6500.0s (h)	0.0s (h)	☆
PC.21	Acceleration/deceleration	0～3	0	☆

	time of simple PLC reference 1			
PC.22	Running time of simple PLC reference	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.23	Acceleration/deceleration time of simple PLC reference 2	0~3	0	☆
PC.24	Running time of simple PLC reference 3	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.25	Acceleration/deceleration time of simple PLC reference 3	0~3	0	☆
PC.26	Running time of simple PLC reference 4	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.27	Acceleration/deceleration time of simple PLC reference 4	0~3	0	☆
PC.28	Running time of simple PLC reference 5	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.29	Acceleration/deceleration time of simple PLC reference 5	0~3	0	☆
PC.30	Running time of simple PLC reference 6	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.31	Acceleration/deceleration time of simple PLC reference 6	0~3	0	☆
PC.32	Running time of simple PLC reference 7	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.33	Acceleration/deceleration time of simple PLC reference 7	0~3	0	☆
PC.34	Running time of simple PLC reference 8	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.35	Acceleration/deceleration time of simple PLC reference 8	0~3	0	☆
PC.36	Running time of simple PLC reference 9	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.37	Acceleration/deceleration	0~3	0	☆

	time of simple PLC reference 9			
PC.38	Running time of simple PLC reference 10	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.39	Acceleration/deceleration time of simple PLC reference 10	0~3	0	☆
PC.40	PLC Running time of simple PLC reference 11	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.41	Acceleration/deceleration time of simple PLC reference 11	0~3	0	☆
PC.42	Running time of simple PLC reference 12	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.43	Acceleration/deceleration time of simple PLC reference 12	0~3	0	☆
PC.44	Running time of simple PLC reference 13	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.45	Acceleration/deceleration time of simple PLC reference 13	0~3	0	☆
PC.46	Running time of simple PLC reference 14	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.47	Acceleration/deceleration time of simple PLC reference 14	0~3	0	☆
PC.48	Running time of simple PLC reference 15	0.0s (h) ~6500.0s (h)	0.0s (h)	☆
PC.49	Acceleration/deceleration time of simple PLC reference 15	0~3	0	☆
PC.50	Time unit of simple PLC running	0: s (second) 1: h (hour)	0	☆
PC.51	Multi-Reference 0 setting mode	0: Set by PC.00 1: FIV (expansion card) 2: FIC 3: Reserved 4: PULSE	0	☆

		5: PID 6: Preset frequency (P0.08) setting, UP/DOWN can be modified		
Group Pd Communication parameters				
PD.00	Baud rate	个位: MODBUS 0: 300BPS 1: 600BPS 2: 1200BPS 3: 2400BPS 4: 4800BPS 5: 9600BPS 6: 19200BPS 7: 38400BPS 8: 57600BPS 9: 115200BPS Ten's digit: Reserved Hundred's digit: Reserved Thousand's digit: CAN 0: 20 1: 50 2: 100 3: 125 4: 250 5: 500 6: 1M	5005	☆
PD.01	Data format	0: No check (8-N-2) 1: Even parity check (8-E-1) 2: Odd Parity check (8-O-1) 3: 8-N-1	3	☆
PD.02	Local address	1~247	1	☆
PD.03	Response delay	0ms~20ms	2	☆
PD.04	Communication timeout	0.0 (invalid) , 0.1s~60.0s	0.0	☆
PD.05	Data transfer format selection	Unit's digit: MODBUS 0: Non-standard MODBUS	1	☆

		protocol 1: Standard MODBUS protocol Ten's digit: Reserved		
PD.06	Communication reading current resolution	0: 0.01A 1: 0.1A	0	☆
Group PP User-Defined Function Codes				
PP.00	User password	0~65535	0	☆
PP.01	Parameter Initialization	00: No operation 01: Restore factory settings except motor parameters	0	★
Group C0 Torque Control and Restricting Parameters				
C0.00	Speed/Torque control selection	0: Speed control 1: Torque control	0	★
C0.01	Torque setting source selection in torque control	0: Digital setting (C0.03) 1: FIV (expansion card) 2: FIC 3: Reserved 4: PULSE 5: Communication setting 6: MIN (FIV (expansion card),FIC) 7: MAX (FIV (expansion card),FIC) (Full Scale 1-7 options, corresponding C0.03 digital set)	0	★
C0.03	Torque digital setting in torque control	-200.0%~200.0%	150.0%	☆
C0.05	Forward maximum frequency in torque control	0.00Hz~Maximum frequency	50.00Hz	☆
C0.06	Reverse maximum frequency in torque control	0.00Hz~Maximum frequency	50.00Hz	☆
C0.07	Acceleration time in torque control	0.00s~65000s	0.00s	☆
C0.08	Deceleration time in	0.00s~65000s	0.00s	☆

	torque control			
Group C5 Control Optimization Parameters				
C5.00	DPWM switchover frequency upper limit	5.00Hz～Maximum frequency	8.00Hz	☆
C5.01	PWM modulation mode	0: Asynchronous modulation 1: Synchronous modulation	0	☆
C5.02	Dead zone compensation mode selection	0: No compensation 1: Compensation mode 1	1	☆
C5.03	Random PWM depth	0: Random PWM invalid 1～10: PWM carrier frequency random depth	0	☆
C5.04	Rapid current limit enable	0: Disabled 1: Enabled	1	☆
C5.05	Voltage overmodulation coefficient	100～110	105	☆
C5.06	Under voltage threshold setting	200.0V～2000.0V	Model dependent	☆
C5.08	Dead zone time adjustment	100%～200%	150%	☆
C5.09	Over voltage threshold setting	200.0V～2200.0V	Model dependent	

Monitoring Parameters:

Function code	Parameter name	Unit
Group D0 Monitoring parameters		
D0.00	Running frequency (Hz)	0.01Hz
D0.01	Set frequency (Hz)	0.01Hz
D0.02	Bus voltage (V)	0.1V
D0.03	Output voltage (V)	1V
D0.04	Output current (A)	0.01A
D0.05	Output power (kW)	0.1kW
D0.06	Output torque (%)	0.1%
D0.07	DI input state	1
D0.08	DO output state	1
D0.09	FIV voltage (V)	0.01V
D0.10	FIC voltage (V)	0.01V
D0.11	Reserved	

D0.12	Count value	1
D0.13	Length value	1
D0.14	Load speed display	1
D0.15	PID setting	1
D0.16	PID feedback	1
D0.17	PLC stage	1
D0.18	Input pulse frequency (kHz)	0.01kHz
D0.19	Motor speed	1rpm
D0.20	Remaining running time	0.1Min
D0.21	FIV voltage before correction	0.001V
D0.22	FIC voltage before correction	0.001V
D0.23	Reserved	
D0.24	Linear speed	1m/Min
D0.25	Current power on time	1Min
D0.26	Current running time	0.1Min
D0.27	Input pulse frequency	1Hz
D0.28	Communication setting	0.01%
D0.29	Reserved	
D0.30	Reserved	
D0.31	Auxiliary frequency Y display	0.01Hz
D0.32	View any memory address values	1
D0.33	Reserved	
D0.34	Motor temperature value	1℃
D0.35	Target torque (%)	0.1%
D0.36	Reserved	1
D0.37	Power factor angle	0.1°
D0.38	Reserved	1
D0.39	Target voltage upon V/F separation	1V
D0.40	Output voltage upon V/F separation	1V
D0.41	Reserved	
D0.42	Reserved	
D0.43	Reserved	
D0.44	Reserved	
D0.45	Fault information	0
D0.58	Z signal counter	1
D0.59	Setting frequency (%)	0.01%

D0.60	Running frequency (%)	0.01%
D0.61	AC drive state	1
D0.74	AC drive output torque	0.1

Appendix B T200 Modbus communication protocol

T200 series inverter provides RS485 communication interface, and support the Modbus communication protocol. Users can be achieved by computing machine or PLC central control, through the communication protocol set frequency converter running commands, modify or read function code parameters, read the inverter working condition and fault information, etc.

1、The agreement content

The serial communication protocol defines the serial communication transmission of information content and format. Including: host polling or wide planting format; Host encoding method, the content includes: the function of the required action code, data transmission and error checking, etc. From the ring of machine should be used is the same structure, content including: action confirmation, return the data and error checking, etc. If there was an error in receiving information from a machine, or cannot achieve the requirements of the host, it will organize a fault feedback information in response to the host.

2、Application methods

Application mode converter with RS485 bus access to the "from" single main PC/PLC control network.

3、Bus structure

- (1) The interface way RS485 interface hardware
- (2) Asynchronous serial transmission mode, half-duplex transmission mode. At the same time the host and the only one to send data from the machine and the other can only receive data. Data in the process of serial asynchronous communication, the form of a message, a frame of a frame to send
- (3) Topological structure from single host machine system. From the machine address set in the range of 1 ~ 247, 0 for broadcast communication address. In the network from the machine address must be unique.

4、Protocol Description

T200 series inverter is a kind of asynchronous serial port communication protocol of master-slave Modbus communication protocol, the network has only one equipment (host) to establish agreement (called "query/command"). Other equipment (machine) can only by providing data response of the main machine "query/command", or "query/command" according to the host to make the corresponding action. Host in this refers to the personal computer (PC), industrial control equipment or programmable logic controller (PLC), etc., from machine refers to z2000 inverter. The host can communicate to a separate from the machine, also can to all under a broadcast information from machine release. For

access to the host alone "query/command", from the machine to return to a information (called response), for radio host information, from the machine without feedback response to the host.

5、Communications data structure

Communication data structure T200 series frequency converter of the Modbus protocol communication data format is as follows: using the RTU mode, messages are sent at least begin with 3.5 characters pause time interval.

In network wave rate under varied characters of the time, this is the most easy to implement.Transmission equipment is the first domain address.

The transmission character of you can use is the hex 0...9, A...F. Continuously detect network bus network facilities, including pause interval of time.When the first domain (domain) to receive, every equipment decoding to determine whether to own.After the last transmission character, a pause at least 3.5 characters time calibration for the end of the message.A new message can be started after the pause.

The entire message frame must be as a continuous flow of transmission.If the time frame to complete more than 1.5 characters before pause time, receiving equipment will refresh incomplete message and assume that the next byte is a new message the address of the domain.Likewise, if a new message in less than 3.5 characters of time and then a message before, receiving equipment will think it is a continuation of the previous message.This will result in an error, because in the final CRC field value can't be right.

RTU frame format:

The frame header START	3.5 characters
Slave address ADR	Communication address: 1~247
command code CMD	03: Read the machine parameters; 06: write the machine parameters
Date content DATA (N-1)	Information content: Function code parameter address, function code number of parameters, function code parameter values, etc
Data content DATA (N-2)	
.....	
Data contentDATA0	
high-order position of CRC CHK	estimated value: CRC value
low-order position of CRC CHK	

END	3.5 characters' time
-----	----------------------

CMD（Command instruction）and DATA（the description of data word）
 command code: 03H，read N word（Word）（Can read the most words of 12）For example,From the machine address of 01 inverter startup F105
 continuous read for two consecutive values
 The host command information

ADR	01H
CMD	03H
high-order position of the starting address	F1H
low-order position of the starting address	05H
high-order position of register	00H
low-order position of register	02H
low-order position of CRC CHK	Wait to calculate the CRC CHK values
high-order position of CRC CHK	

In response to information from the slave machine
 Set PD.05 to 0:

ADR	01H
CMD	03H
High-order position of bytes	00H
Low-order position of bytes	04H
Data high -order position of F002H	00H
Data low -order position of F002H	00H
Data high -order position of F003H	00H
Data low -order position of F003H	01H
Low-order position of CRC CHK	Wait to calculate the CRC CHK value
High-order position of CRC CHK	

Set PD.05 to 1

ADR	01H
CMD	03H
The number of bytes	04H
Data high -order position of F002H	00H
Data low -order position of F002H	00H
Data high -order position of F003H	00H
Data low -order position of F003H	01H
Low -order position of CRC CHK	Wait to calculate the CRC CHK value
High -order position of CRC CHK	

The command code :06H write a word (word) for example, write 000(BB8H) to machine

Address 05H frequency converter's F00AH address

The host command information

ADR	05H
CMD	06H
High-order position of data address	F0H
Low-order position of data address	0AH
High-order position of information content	0BH
Low-order position of information content	B8H
Low-order position of CRC CHK	Wait to calculate the CRC CHK value
High-order position of CRC CHK	

In response to information from the slave machine

ADR	02H
CMD	06H
High-order position of data address	F0H
Low-order position of data address	0AH
High-order position of information content	13H
Low-order position of information content	88H
Low-order position of CRC CHK	Wait to calculate the CRC CHK value
High-order position of CRC CHK	

Check way——CRC Check way: CRC (Cyclical Redundancy Check) use RTU frame format, The message includes error detection field based on the method of CRC. CRC domain test the whole content of a message. CRC domain is two bytes, contains a 16-bit binary values. it is calculated by the transmission equipment, added to the message. receive messages the device recalculate. And compared with receives the CRC in the domain of value, if the two CRC value is not equal, then there is an error in transmission.

CRC is saved in 0xFFFF, Then call a process to continuous 8-bit bytes of the message and the values in the current register for processing. Only 8 bit data in each character of CRC is effective, Starting bit and stopping bit and parity bits are invalid.

In the process of CRC, Each of the eight characters are separate and dissimilar or register contents (XOR), The results move to the least significant bit direction, set the most significant bit to 0. LSB is extracted to test, if set LSB to 1, Register and preset value dissimilarity or alone, if set LSB to 0, is not to. The whole process will repeat 8CRC times. when the last time (the eighth time) is completed, next 8-bit bytes and separate and register under the current value of the alien or. The values in the final register, Is all bytes in the message is executed after the CRC value.

When CRC added to the messages .The low byte to join first and then high byte.CRC Simple function is as follows:

```
unsigned int crc_cal_value(unsigned char *data_value,unsigned char
data_length)
{
int i;
unsigned int crc_value=0xffff;
while(data_length--)
{
crc_value^=*data_value++;
for(i=0;i<8;i++)
{
If(crc_value&0x0001)
crc_value=(crc_value>>1)^0xa001;
else
crc_value=crc_value>>1;
}
}
Return(crc_value);
}
```

Address definition of communication parameters

This part is the content of the communication, used to control the operation of the inverter, inverter status and related parameters setting.Read and write functional code parameter (some function code which can not be changed, only for the use of manufacturers or monitoring) : function code parameter address label rules: By function block number and the label for the parameter address representation rules .High byte: F0~FF (P group) 、 A0~AF (C group) 、 70~7F (D group) low byte: 00~FF

Such as: P3.12, The address is expressed as F30C; attention: PF group: Neither read the parameters, and do not change parameters;Group D group: only can read, do not change the parameters.

When some parameters in converter is in operation, do not change;Some parameters of the frequency converter in any state, cannot be changed;Change function code parameters, but also pay attention to the range of parameters, units, and related instructions.

In addition, because the EEPROM is stored frequently, the service life of the block can reduce the the life of the block EPROM, so some function code under

the mode of communication, do not need to be stored, just change the value of RAM.

If it is P group of parameters, in order to realize the function, as long as putting this function code address high F into 0 can be achieved. If it is C group of parameters, in order to realize the function, as long as putting the function code the address of high A into 4 can be achieved. Corresponding function codes are shown as the following address: the high byte: 00 ~ 0F (P group), 40 ~ 4F (C group) low byte: 00 to FF.

Such as: Function code P3.12 is not stored in the EEPROM, The address is expressed as 030C; Function code C0-05 is not stored in the EEPROM, The address is expressed as 4005; The address representation can only do writing RAM, can't do reading action, when reading, it is invalid address.

Stopping/starting parameters:

Parameter address	Parameter description
1000	*Communication setting value (-10000~10000) (Decimal system)
1001	Operating frequency
1002	Bus voltage
1003	Output voltage
1004	Output current
1005	Output power
1006	Output torque
1007	Running velocity
1008	input flag
1009	output flag
100A	FIV voltage
100B	FIC voltage
100C	Reserved
100D	Count value input
100E	The length of the input
100F	The load speed
1010	PID setting
1011	PID feedback
1012	PLC steps
1013	PULSE input pulse frequency, unit: 0.01kHz
1014	Reserved
1015	The remaining running time

1016	FIV voltage before correction
1017	FIC voltage before correction
1018	Reserved
1019	Linear velocity
101A	Current power on time
101B	Current running time
101C	PULSE input pulse frequency,unit: 1Hz
101D	Communication setting value
101E	Reserved
101F	The main frequency X display
1020	The auxiliary frequency Y display

Attention:

Communication setting value is relative percentage, 10000 corresponds to 100.00% and - 10000-100.00%.The frequency of dimensional data, the percentage is relative to the percentage of maximum frequency (P0.12);Counter rotating torque dimensional data, the percentage is P2.10.

Control command input to the inverter:(write-only)

The command word address	Command function
2000	0001: Forward running
	0002: Reserve running
	0003: Forward JOG
	0004: Reserve JOG
	0005: Coast to stop
	0006: Deceleration to stop
	0007: Fault reset

Read the inverter state (read-only)

The command word address	Command function
3000	0001: Forward running
	0002: Reverse running
	0003: Stop

Parameter lock password check: (if return to 888H, it indicates that the password check through)

Password address	The content of the input password
1F00	*****

Command address	Command content
-----------------	-----------------

2001	BIT0: (Reserved)
	BIT1: YO output control
	BIT2: YA-YB-YC output control
	BIT3: Reserved
	BIT4: MOA- MOB-MOC output control

Analog output FOV control: (write-only)

Command address	Command content
2002	0～7FFF represent 0%～100%

Analog output FOC control: (write-only)

Command address	Command content
2003	0～7FFF represent 0%～100%

Pulse output control: (write-only)

Command address	Command content
2004	0～7FFF represent 0%～100%

Frequency converter fault description

Fault address	Fault information
8000	0000: No fault
	0001: Inverter unit protection
	0002: Over current during acceleration
	0003: Over current during deceleration
	0004: Over current at constant speed
	0005: Over-voltage during acceleration
	0006: Over-voltage during deceleration
	0007: Over-voltage at constant speed
	0008: Control power fault
	0009: Under voltage
	000A: AC drive overload
	000B: Motor overload
	000C: Reserved
	000D: Power output phase loss
	000E: Module overheat
	000F: External equipment fault
	0010: Communication fault

0011: Contactor fault
0012: Current detection fault
0013: Motor auto-tuning fault
0014: Reserved
0015: Parameters read-write error
0016: AC drive hardware fault
0017: Motor short circuit to ground
0018: Reserved
0019: Reserved
001A: Running time reached
001B: Reserved
001C: Reserved
001D: Power-on time reached
001E: Load becoming 0
001F: PID feedback lost during running
0028: Rapid limit overtime
0029: Switchover motor during running
002A: Speed deviation too large
002B: Motor over speed
002D: Motor over temperature
005A: The number of Encoder lines set incorrect
005B: Do not connect encoder
005C: Initial position fault
005E: Speed feedback error

Communication fault address	Fault function information
8001	0000: No fault 0001: Password mistake 0002: Command code error 0003: CRC check error 0004: Invalid address 0005: Invalid parameter 0006: Correcting parameter invalid 0007: System is locked 0008: Under EEPROM operation

Group PD Communication parameters display

PD.00	Baud rate	Default	5005
	Setting range	Unit's digit: MODUBS baud rate 0: 300BPS 1: 600BPS 2: 1200BPS 3: 2400BPS 4: 4800BPS 5: 9600BPS 6: 19200BPS 7: 38400BPS 8: 57600BPS 9: 115200BPS Thousand's digit: CAN 0: 20 1: 50 2: 100 3: 125 4: 250 5: 500 6: 1M	

This parameter is used to set data transfer rate between the PC and inverter.
 Notice: Setting the baud rate of upper machine and inverter must be corresponding. Otherwise, the communication can't carry on. The larger the baud rate, the faster the communication.

PD.01	The data format	Default	0
-------	-----------------	---------	---

		Setting range	0: No check: data format <8,N,2> 1: Even-parity: data format <8,E,1> 2: Odd-parity: data format <8,O,1> 3: No check: data format <8,N,1>
--	--	---------------	---

PC and data format must be set corresponding, otherwise, communication can't carry on.

PD.02	Machine address	Default	1
	Setting range	1~247, 0 is the broadcast address	

When the machine address set to 0, it is broadcast address, realize PC broadcasting functions,

The machine address has uniqueness (except the broadcast address), which is to achieve the basis of the upper machine and inverter peer to peer communications.

PD.03	Response delay	Default	2ms
	Setting range	0~20ms	

Response delay: refers to the frequency converter data to accept the end up to a upper machine to send data in the middle of the interval of time. If the response time delay is less than the system processing time, the response time delay will be subject to system processing time. Such as, response time delay is longer than system after processing the data, the system will delay waiting, until the response delay time is up to a upper machine to send data

PD.04	Communication timeout	Default	0.0 s
	Setting range	0.0 s (invalid) 0.1~60.0s	

When the function code is set to 0.0s, communication timeout parameter is invalid.

When the function code set to valid values, if a communication and interval time of the next communication beyond the communication timeout, system will be submitted to the communication fault error(CE). Usually, it is set to invalid. If in the continuous communication system, set the second parameter, it can monitor the communication status

PD.05	Communication protocol selection	Default	0
	Setting range	0: Non standard Modbus protocol 1: Standard Modbus protocol	

PD.05=1: Select standard Modbus protocol.

PD.05=0: When reading a command, the number of bytes returned by the slave

is one byte more than the standard Modbus protocol. For details, refer to the "Communication Data Structure" part of this protocol.

PD.06	Read the current resolution	Default	0
	Setting range	0: 0.01A 1: 0.1A	

Use to determine the communication while reading the output current, current value of the output units.